

Assignment -4

Assignment Date	29 October 2022
Student Name	MADHAN M
Student Roll Number	95071914054
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor.

Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

Upload document with wokwi share link and images of IBM cloud

Solution :

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>

WiFiClient wifiClient;

#define ORG "nhpwjc"
#define DEVICE_TYPE "raspberrypi"
#define DEVICE_ID "12345"
#define TOKEN "123456789"
#define speed 0.034
char server[] = ORG
".messaging.internetofthings.ibmcloud.com"; char
publishTopic[] = "iot-2/evt/Data/fmt/json"; char topic[] =
"iot-2/cmd/home/fmt/String"; char authMethod[] = "use-token-
auth"; char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient); void
publishData();

const int trigpin=5; const
int echopin=18;
String command;
String data="";

long duration;
int dist;

void setup()
{
  Serial.begin(115200);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}
void loop() {
  publishData();
  delay(500);
}
```

```


    if (!client.loop()) {
        mqttConnect();
    }
}


void wifiConnect() {
    Serial.print("Connecting to "); Serial.print("Wifi");
    WiFi.begin("Wokwi-GUEST", "", 6); while (WiFi.status()
    != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}


void mqttConnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting MQTT client to "); Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print("."); delay(1000);
        }
        initManagedDevice();
        Serial.println();
    }
}

void initManagedDevice() {
    if (client.subscribe(topic)) {
        Serial.println(client.subscribe(topic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    } } void
publishData()
{ digitalWrite(trigpin,LOW);
  digitalWrite(trigpin,HIGH);
  delayMicroseconds(10);
  digitalWrite(trigpin,LOW);
  duration=pulseIn(echopin,HIGH);
  dist=duration*speed/2;
  if(dist<100){
      DynamicJsonDocument doc(1024);
      String          payload;
      doc["AlertDistance:"]=dist;
      serializeJson(doc,  payload);
      delay(3000);
      Serial.print("\n");
      Serial.print("Sending payload: ");
      Serial.println(payload);
      if (client.publish(publishTopic, (char*) payload.c_str())) {
          Serial.println("Publish OK");
      } else {
          Serial.println("Publish FAILED");
      }
  }
}
}

```



01:38.369 100%



```
ending payload: {"Alert distance":93.99}
ublish OK

ending payload: {"Alert distance":93.96}
ublish OK

ending payload: {"Alert distance":93.96}
ublish OK

ending payload: {"Alert distance":93.96}
ublish OK

ending payload: {"Alert distance":93.96}
ublish OK

ending payload: {"Alert distance":93.96}
ublish OK
```

Add Device  Search by Device ID

Device Simulator   

Items per page 100 ▾ | 1-1 of 1 item 1 of 1 page < 1 ▾ >