

Assignment -3

Python Code for Blinking led & Traffic lights

Assignment Date	21 OCTOBER 2022
Student Name	ANISH B
Student Roll Number	513419106003
Maximum Marks	

Question-4:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

```
#include <WiFi.h>
#include <PubSubClient.h>
WiFiClient wifiClient;
String data3;
#define ORG "13b7j1"
#define DEVICE_TYPE "anish"
#define DEVICE_ID "12345"
#define TOKEN "2)1FVJT-5R?ndrdTwn"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();
```

```
const int trigpin=2;
const int echopin=4;
String command;
String data="";
```

```
long duration;
float dist;
```

```
void setup()
{
  Serial.begin(115200);
  pinMode(led, OUTPUT);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
```

```

    wifiConnect();
    mqttConnect();
}

void loop() {
    bool isNearby = dist < 100;
    digitalWrite(led, isNearby);

    publishData();
    delay(500);

    if (!client.loop()) {
        mqttConnect();
    }
}

void wifiConnect() {
    Serial.print("Connecting to "); Serial.print("Wifi");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}

void mqttConnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting MQTT client to "); Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(500);
        }
        initManagedDevice();
        Serial.println();
    }
}

void initManagedDevice() {
    if (client.subscribe(topic)) {
        // Serial.println(client.subscribe(topic));
        Serial.println("IBM subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void publishData()
{
    digitalWrite(trigpin, LOW);
    digitalWrite(trigpin, HIGH);
}

```

```

delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2;
if(dist<100){
    String payload = "{\"Normal Distance\":\"";
    payload += dist;
    payload += "\"}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }
}

if(dist>101 && dist<111){
    String payload = "{\"Alert distance\":\"";
    payload += dist;
    payload += "\"}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if(client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Warning crosses 110cm -- it automatically of the loop");
        digitalWrite(led,HIGH);
    }else {
        Serial.println("Publish FAILED");
    }
}

}

}

void callback(char* subscribeTopic, byte* payload, unsigned int payloadLength){
    Serial.print("callback invoked for topic:");
    Serial.println(subscribeTopic);
    for(int i=0; i<payloadLength; i++){
        dist += (char)payload[i];
    }
    Serial.println("data:" + data3);
    if(data3=="lighton"){
        Serial.println(data3);
        digitalWrite(led,HIGH);
    }
    data3="";
}

```

sketch.ino

diagram.json

libraries.txt

Library Manager

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 WiFiClient wificlient;
4 String data3;
5 #define ORG "13b7j1"
6 #define DEVICE_TYPE "anish"
7 #define DEVICE_ID "12345"
8 #define TOKEN "2)1FVJT-5R?ndrdTwn"
9 #define speed 0.034
10 #define led 14
11 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
12 char publishTopic[] = "iot-2/evt/Data/fmt/json";
13 char topic[] = "iot-2/cmd/home/fmt/String";
14 char authMethod[] = "use-token-auth";
15 char token[] = TOKEN;
16 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
17 PubSubClient client(server, 1883, wificlient);
18 void publishData();
19
20
21 const int trigpin=2;
22 const int echopin=4;
23 String command;
24 String data="";
25
26 long duration;
27 float dist;
28
29
30
31 void setup()
32 {
33   Serial.begin(115200);
```

Simulation

00:47.977

99%

Publish OK

Sending payload: {"Normal Distance":74.99}

Publish OK

Sending payload: {"Normal Distance":74.97}

Publish OK

🔍

⏸

🗑

[Browse](#) [Action](#) [Device Types](#) [Interfaces](#)

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Normal Distance":39.97}	json	2 minutes ago
Data	{"Normal Distance":39.97}	json	2 minutes ago
Data	{"Normal Distance":39.97}	json	2 minutes ago
Data	{"Normal Distance":39.97}	json	2 minutes ago
Data	{"Normal Distance":39.97}	json	2 minutes ago