

Assignment -4

Assignment Date	02 November 2022
Student Name	SRIDHAR R
Student Roll Number	922119106101
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor.

Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

Upload document with wokwi share link and images of IBM cloud

Solution :

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>
WiFiClient wifiClient;
#define ORG "djfg8g"
#define DEVICE_TYPE "Nalaiyathiran"
#define DEVICE_ID "ssvt369"
#define TOKEN "Ibmproject@369"
#define speed 0.034
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();
const int trigpin=5;
const int echopin=18;
String command;
String data="";
long duration;
int dist;
void setup()
{
  Serial.begin(115200);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}
void loop() {
  publishData();
  delay(500);
  if (!client.loop()) {
    mqttConnect();
  }
}
void wifiConnect() {
  Serial.print("Connecting to "); Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
```

```

Serial.print(".");
}
Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}
void mqttConnect() {
if (!client.connected()) {
Serial.print("Reconnecting MQTT client to "); Serial.println(server);
while (!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(1000);
}
initManagedDevice();
Serial.println();
}
}

void initManagedDevice() {
if (client.subscribe(topic)) {
Serial.println(client.subscribe(topic));
Serial.println("subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}

void publishData()
{
digitalWrite(trigpin,LOW);
digitalWrite(trigpin,HIGH);
delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2;
if(dist<100){
DynamicJsonDocument doc(1024);
String payload;
doc["Distance Alert:"]=dist;
serializeJson(doc, payload);
delay(3000);
Serial.print("\n");
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish OK");
} else {
Serial.println("Publish FAILED");
}
}
}
}

```

WOWKI SHARE LINK : <https://wokwi.com/projects/346971559645151828>

WOKWI

sketch.ino diagram.json libraries.txt Library Manager

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 #include <ArduinoJson.h>
4 WiFiClient wificlient;
5 #define ORG "dfg8g"
6 #define DEVICE_TYPE "Nalaiyathiran"
7 #define DEVICE_ID "ssvt369"
8 #define TOKEN "Ibmproject@369"
9 #define speed 0.034
10 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
11 char publishTopic[] = "iot-2/evt/data/fmt/json";
12 char topic[] = "iot-2/cmd/home/fmt/String";
13 char authMethod[] = "use-token-auth";
14 char token[] = TOKEN;
15 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
16 PubSubClient client(server, 1883, wificlient);
17 void publishData();
18 const int trigpin=5;
19 const int echopin=18;
20 String command;
21 String data="";
22 long duration;
23 int dist;
24 void setup()
25 {
26   Serial.begin(115200);
27   pinMode(trigpin, OUTPUT);
28   pinMode(echopin, INPUT);
29   wifiConnect();
30   mqttConnect();
31 }
32 void loop() {
33   publishData();
34 }
```

Simulation

Editing Ultrasonic Distance Sensor
Distance: 90cm

Sending payload: {"Distance Alert":89}
Publish OK

Sending payload: {"Distance Alert":89}
Publish OK

26°C Mostly cloudy

IBM Watson IoT Platform

922119106101@smartinternz.com
ID: dfg8g

Browse Action Device Types Interfaces

Add Device +

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location
ssvt369	Connected	Nalaiyathiran	Device	Oct 22, 2022 12:37 PM	

Identity Device Information Recent Events State Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Distance Alert":70}	json	a few seconds ago
Data	{"Distance Alert":89}	json	a few seconds ago
Data	{"Distance Alert":90}	json	a few seconds ago
Data	{"Distance Alert":89}	json	a few seconds ago

Items per page 50 | 1-1 of 1 item

1 of 1 page

26°C Mostly cloudy