

BATCH: B5-5M1E

# ASSIGNMENT-4

---

**QUESTION: Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud.**

## CODE:

```
#include <WiFi.h>
#include <PubSubClient.h>
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
#define ORG "ocknc6"
#define DEVICE_TYPE "esp32"
#define DEVICE_ID "12345"
#define TOKEN "12345678"
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribetopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback, wifiClient);
const int trigPin = 5;
const int echoPin = 18;
#define SOUND_SPEED 0.034
long duration;
float distance;
void setup() {
  Serial.begin(115200);
  pinMode(trigPin, OUTPUT);
  pinMode(echoPin, INPUT);
  wificonnect();
  mqttconnect();
}
void loop()
{
  digitalWrite(trigPin, LOW);
  delayMicroseconds(2);
  digitalWrite(trigPin, HIGH);
  delayMicroseconds(10);
  digitalWrite(trigPin, LOW);
```

```

duration = pulseIn(echoPin, HIGH);
distance = duration * SOUND_SPEED/2;
Serial.print("Distance (cm): ");
Serial.println(distance);
if(distance<100)
{
Serial.println("ALERT!!");
delay(1000);
PublishData(distance);
delay(1000);
if (!client.loop()) {
mqttconnect();
}
}
delay(1000);
}
void PublishData(float dist) {
mqttconnect();
String payload = "{"Distance\":";
payload += dist;
payload += ",\\"ALERT!!\":"\"Distance less than 100cms\\"";
payload += "}";
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
} else {
Serial.println("Publish failed");
}
}
void mqttconnect() {
if (!client.connected()) {
Serial.print("Reconnecting client to ");
Serial.println(server);
while (!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}
void wificonnect()
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
}

```

```

}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address: ");
Serial.println(WiFi.localIP());
}
void initManagedDevice() {
if (client.subscribe(subscribetopic)) {
Serial.println((subscribetopic));
Serial.println("subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);
for (int i = 0; i < payloadLength; i++)
{
data3 += (char)payload[i];
}
Serial.println("data: "+ data3);
data3="";
}

```

## OUTPUT:

The screenshot shows the Wokwi IDE interface. On the left, the 'sketch.ino' file is open, displaying the following code:

```

1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength) {
4 #define ORG "ocknc6"
5 #define DEVICE_TYPE "esp32"
6 #define DEVICE_ID "12345"
7 #define TOKEN "12345678"
8 String data3;
9 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
10 char publishTopic[] = "iot-2/evt/Data/fmt/json";
11 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
12 char authMethod[] = "use-token-auth";
13 char token[] = TOKEN;
14 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
15 WiFiClient wificlient;
16 PubSubClient client(server, 1883, callback, wificlient);
17 const int trigPin = 5;
18 const int echoPin = 18;
19 #define SOUND_SPEED 0.034
20 long duration;
21 float distance;
22 void setup() {
23 Serial.begin(115200);
24 pinMode(trigPin, OUTPUT);
25 pinMode(echoPin, INPUT);
26 wificlient.connect();
27 mqttconnect();
28 }

```

On the right, the 'Simulation' window shows a 3D model of an ESP32 microcontroller board connected to an HC-SR04 ultrasonic sensor. Below the simulation, a serial monitor displays the following output:

```

Distance (cm): 399.92
Distance (cm): 399.94
Distance (cm): 399.94
Distance (cm): 399.92
Distance (cm): 399.94
Distance (cm): 399.98

```

The bottom status bar of the IDE shows the temperature as 26°C, the language as ENG, and the date as 03-11-2022.