



```
#define Trigpin 7
```

```
#define Echopin 8
```

```
#define low_led 9
```

```
#define high_led 10
```

```
float distance;
```

```
int duration;
```

```
int H = 700;
```

```
void setup() {
```

```
  pinMode (Trigpin, OUTPUT);
```

```
  pinMode (low_led, OUTPUT);
```

```
  pinMode (high_led, OUTPUT);
```

```
  pinMode (Echopin, INPUT);
```

```
  Serial.begin(9600);
```

```
  Serial.println ("Welcome To Distance Meter");
```

```
  Serial.println ("Coded By Jevins Annson");
```

```
  digitalWrite (low_led, LOW);
```

```
  digitalWrite (high_led, LOW);
```

```
}
```

```
void loop() {
```

```
digitalWrite(Trigpin, LOW);
delayMicroseconds(2);
digitalWrite(Trigpin, HIGH);
delayMicroseconds(10);
digitalWrite(Trigpin, LOW);
duration = pulseIn(Echopin, HIGH);
distance = duration * 0.034 / 2;
delay (11);
Serial.println (" ");
Serial.print ("Distance = ");
Serial.print (distance);
Serial.print (" CM");
Serial.println (" ");

if (distance>=30)
{
  Serial.println ("Nobody Is Infront Of the Sensor");
  digitalWrite (low_led, HIGH);
  delay (500);
  digitalWrite (low_led, LOW);
  delay (500);
  digitalWrite (low_led, HIGH);
}
else
{
  Serial.println ("Someone Is Infront Of the Sensor");
  digitalWrite (high_led, HIGH);
  delay (100);
  digitalWrite (high_led, LOW);
  delay (100);
}
```

```
digitalWrite (high_led, HIGH);
```

```
delay (100);
```

```
}
```

```
}
```