

Assignment - 4

Assignment Date	20 OCTOBER 2022
Student Name	PAVITHRA
Student Roll Number	49621911094
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud

CODE 1 :

```
#include <WiFi.h>
#include <PubSubClient.h>
void callback(char* subscribtopic, byte* payload, unsigned int
payloadLength);
//-----credentials of IBM Accounts-----
#define ORG "acdg14"//IBM ORGANITION ID
#define DEVICE_TYPE "IOT_GAS_LEAKAGE_MONITORING"//Device type
mentioned in ibm watson IOT Platform#define DEVICE_ID "151617"//Device ID
mentioned in ibm watson IOT Platform #define TOKEN "1911094abcdefgh" //Token
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribtopic[] = "iot-2/cmd/test/fmt/String";char
authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
const int trigPin = 5;
const int echoPin = 18;
#define SOUND_SPEED 0.034
long duration;
float distance;
void setup() {
  Serial.begin(115200);
  pinMode(trigPin, OUTPUT);
  pinMode(echoPin, INPUT);
  wificonnect();
  mqttconnect();
}
void loop()
{
  digitalWrite(trigPin, LOW);
  delayMicroseconds(2);
  digitalWrite(trigPin, HIGH);
  delayMicroseconds(10);
  digitalWrite(trigPin, LOW);
  duration = pulseIn(echoPin, HIGH);
  distance = duration * SOUND_SPEED/2;
```

```

Serial.print("Distance (cm): ");
Serial.println(distance);
if(distance<100)
{
Serial.println("ALERT!!");
delay(1000);
PublishData(distance);
delay(1000);
if (!client.loop()) {
mqttconnect();
}
}
delay(1000);
}
void PublishData(float dist) {
mqttconnect();
String payload = "{"Distance\":";
payload += dist;
payload += ",\"ALERT!!\":"\"Distance less than 100cms\"";
payload += "}";
Serial.print("Sending payload: ");
Serial.println(payload);

if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
} else {
Serial.println("Publish failed");
}
}
void mqttconnect() {
if (!client.connected()) {
Serial.print("Reconnecting client to ");
Serial.println(server);
while (!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}
void wificonnect()
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address: ");
Serial.println(WiFi.localIP());
}
void initManagedDevice() {
if (client.subscribe(subscribetopic)) {
Serial.println((subscribetopic));
}
}

```

```
Serial.println("subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);
for (int i = 0; i < payloadLength; i++) {
//Serial.print((char)payload[i]);
data3 += (char)payload[i];
}
Serial.println("data: "+ data3);
data3="";
}
```

Wokwi Link :

<https://wokwi.com/projects/347021585567187540>

Output and Simulation :

The screenshot shows the Wokwi web interface with a sketch of an ESP32 microcontroller connected to an HC-SR04 Ultrasonic Distance Sensor. The sketch code is as follows:

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 void callback(char* topic, byte* payload, unsigned int
4   payloadLength);
5 //-----credentials of IBM Accounts-----
6 #define ORG "acd14"//IBM ORGANIZATION ID
7 #define DEVICE_TYPE "IOT_GAS_LEAKAGE_MONITORING"//Device type mentioned
8 #define DEVICE_ID "151617"//Device ID mentioned in ibm watson IOT Platform
9 #define TOKEN "1911094abcdefgh" //Token
10 String data3;
11 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
12 char publishTopic[] = "iot-2/evt/Data/fmt/json";
13 char subscribTopic[] = "iot-2/cmd/test/fmt/String";
14 char authMethod[] = "use-token-auth";
15 char token[] = TOKEN;
16 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
17 WiFiClient wifiClient;
18 PubSubClient client(server, 1883, callback, wifiClient);
19 const int trigPin = 5;
20 const int echoPin = 18;
21 #define SOUND_SPEED 0.034
22 long duration;
23 float distance;
24 void setup() {
25   Serial.begin(115200);
26   pinMode(trigPin, OUTPUT);
27   pinMode(echoPin, INPUT);
28 }
```

The simulation output shows the sensor reading 89.98 cm, which is less than 100 cm, triggering an alert and sending a JSON payload to the IBM cloud:

```
Distance (cm): 89.98
ALERT!!
Sending payload: {"Distance":89.98,"ALERT!!":"Distance less than 100cms"}
Publish ok
```

Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

The screenshot shows the IBM Watson IoT Platform dashboard for the device '151617'. The 'Recent Events' tab is selected, showing a list of events triggered by the device. The events are as follows:

Event	Value	Format	Last Received
Data	{"Distance":89.98,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":89.98,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":89.98,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":89.98,"ALERT!!":"Distance less than ...	json	a minute ago
Data	{"Distance":89.98,"ALERT!!":"Distance less than ...	json	a minute ago