

Assignment - 4

IOT - SMART WASTE MANAGEMENT SYSTEM

Assignment Date	17 October 2022
Student Name	Naveen Kumar N
Student Roll Number	910619106034
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud

CODE 1 :

```
#include <WiFi.h>
#include <PubSubClient.h>
void callback(char* subscribtopic, byte* payload, unsigned int
payloadLength);
//-----credentials of IBM Accounts-----
#define ORG "cbseji"//IBM ORGANITION ID
#define DEVICE_TYPE "abcd"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "1234"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "12345678" //Token
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribtopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
const int trigPin = 5;
const int echoPin = 18;
#define SOUND_SPEED 0.034
long duration;
float distance;
void setup() {
  Serial.begin(115200);
  pinMode(trigPin, OUTPUT);
  pinMode(echoPin, INPUT);
  wificonnect();
  mqttconnect();
}
void loop()
{
  digitalWrite(trigPin, LOW);
  delayMicroseconds(2);
  digitalWrite(trigPin, HIGH);
  delayMicroseconds(10);
  digitalWrite(trigPin, LOW);
  duration = pulseIn(echoPin, HIGH);
  distance = duration * SOUND_SPEED/2;
```

```

Serial.print("Distance (cm): ");
Serial.println(distance);
if(distance<100)
{
Serial.println("ALERT!!");
delay(1000);
PublishData(distance);
delay(1000);
if (!client.loop()) {
mqttconnect();
}
}
delay(1000);
}
void PublishData(float dist) {
mqttconnect();
String payload = "{\"Distance\": ";
payload += dist;
payload += ", \"ALERT!!\": \"\"Distance less than 100cms\"\"";
payload += "}";
Serial.print("Sending payload: ");
Serial.println(payload);

if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
} else {
Serial.println("Publish failed");
}
}
void mqttconnect() {
if (!client.connected()) {
Serial.print("Reconnecting client to ");
Serial.println(server);
while (!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}
void wificonnect()
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address: ");
Serial.println(WiFi.localIP());
}
void initManagedDevice() {
if (client.subscribe(subscribetopic)) {
Serial.println((subscribetopic));
}
}

```

```
Serial.println("subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);
for (int i = 0; i < payloadLength; i++) {
//Serial.print((char)payload[i]);
data3 += (char)payload[i];
}
Serial.println("data: "+ data3);
data3="";
}
```

Wokwi Link :

<https://wokwi.com/projects/347021585567187540>

Output and Simulation :

The screenshot displays the Wokwi IDE interface. On the left, the sketch.ino file contains the following code:

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3 void callback(char* topic, byte* payload, unsigned int
4 payloadLength);
5 //-----credentials of IBM Accounts-----
6 #define ORG "cbsej1"//IBM ORGANIZATION ID
7 #define DEVICE_TYPE "abcd"//Device type mentioned in ibm watson IOT Platform
8 #define DEVICE_ID "1234"//Device ID mentioned in ibm watson IOT Platform
9 #define TOKEN "12345678" //Token
10 String data3;
11 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
12 char publishTopic[] = "iot-2/evt/Data/fmt/json";
13 char subscribeTopic[] = "iot-2/cmd/test/fmt/String";
14 char authMethod[] = "use-token-auth";
15 char token[] = TOKEN;
16 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
17 WiFiClient wificlient;
18 PubSubClient client(server, 1883, callback ,wificlient);
19 const int trigPin = 5;
20 const int echoPin = 18;
21 #define SOUND_SPEED 0.034
22 long duration;
23 float distance;
24 void setup() {
25   Serial.begin(115200);
26   pinMode(trigPin, OUTPUT);
27   pinMode(echoPin, INPUT);
28   wificlient.connect();
29   mqttconnect();
30 }
31 void loop()
32 {
33   digitalWrite(trigPin, LOW);
34   delayMicroseconds(2);
35   digitalWrite(trigPin, HIGH);
36   delayMicroseconds(10);
37   digitalWrite(trigPin, LOW);
```

The simulation window on the right shows the Ultrasonic Distance Sensor connected to the ESP32. The distance is currently 41cm. The console output shows the following messages:

```
ALERT!!
Sending payload: {"Distance":93.94,"ALERT!!":"Distance less than 100cms"}
Publish ok
Distance (cm): 40.97
ALERT!!
Sending payload: {"Distance":40.97,"ALERT!!":"Distance less than 100cms"}
Publish ok
```

Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

The screenshot shows the IBM Watson IoT Platform dashboard. The device ID 1234 is selected, and the 'Recent Events' tab is active. The dashboard displays the following information:

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location	Added By
1234	Connected	abcd	Device	Oct 10, 2022 9:38 PM		910619106034@smartinternz.com

The 'Recent Events' tab shows the following events:

Event	Value	Format	Last Received
Data	{"Distance":93.94,"ALERT!!":"Distance less than ...	json	a few seconds ago
Data	{"Distance":93.96,"ALERT!!":"Distance less than ...	json	a few seconds ago

Items per page 50 | 1-1 of 1 Item

0 Simulations running