

Assignment - 4

Assignment Date	2 November 2022
Student Name	K.Arthi
Student Roll Number	912019106002
Maximum Marks	2 Marks

Question-1:

Write a code and make a connection in wokwi for ultrasonic sensor. Whenever distance is less than 100 send 'alert' to ibm cloud and display in device recent events.

Solution:

Code:

```
#include <WiFi.h>
#include <PubSubClient.h>
WiFiClient wifiClient;
String data3;
#define ORG "4yi0vc"
#define DEVICE_TYPE "nodeMcu"
#define DEVICE_ID "Assignment4"
#define TOKEN "123456789"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();
```

```
const int trigpin=5;
const int echopin=18;
String command;
String data="";
```

```
long duration;
float dist;
```

```
void setup()
{
  Serial.begin(115200);
```

```

    pinMode(led, OUTPUT);
    pinMode(trigpin, OUTPUT);
    pinMode(echopin, INPUT);
    wifiConnect();
    mqttConnect();
}

void loop() {
    bool isNearby = dist < 100;
    digitalWrite(led, isNearby);

    publishData();
    delay(500);

    if (!client.loop()) {
        mqttConnect();
    }
}

void wifiConnect() {
    Serial.print("Connecting to "); Serial.print("Wifi");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}

void mqttConnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting MQTT client to "); Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(500);
        }
        initManagedDevice();
        Serial.println();
    }
}

void initManagedDevice() {
    if (client.subscribe(topic)) {
        // Serial.println(client.subscribe(topic));
        Serial.println("IBM subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void publishData()
{

```

```

digitalWrite(trigpin,LOW);
digitalWrite(trigpin,HIGH);
delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2;
if(dist<100){
    String payload = "{\"Normal Distance\".";
    payload += dist;
    payload += "}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }
}

if(dist>101 && dist<111){
    String payload = "{\"Alert distance\".";
    payload += dist;
    payload += "}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if(client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Warning crosses 110cm -- it automaticaly of the loop");
        digitalWrite(led,HIGH);
    }else {
        Serial.println("Publish FAILED");
    }
}

}

}

void callback(char* subscribeTopic, byte* payload, unsigned int payloadLength){
    Serial.print("callback invoked for topic:");
    Serial.println(subscribeTopic);
    for(int i=0; i<payloadLength; i++){
        dist += (char)payload[i];
    }
    Serial.println("data:" + data3);
    if(data3=="lighton"){
        Serial.println(data3);
        digitalWrite(led,HIGH);
    }
    data3="";
}


```

WOKWI CODE:

<https://wokwi.com/projects/346937989346099796>


OUTPUT

Distance is greater than 100



IBM cloud is connected and LED is off state

Distance is less than 100



LED is on state

IBM Cloud foundry connection

IBM Watson IoT Platform

?

kannankaruppaiah07052002@gmail.com

ID: ks8ptj

Browse

Action

Device Types

Interfaces

Add Device

Event	Value	Format	Last Received
Kannan	{"Alert Distance":47.96}	json	a few seconds ago
Kannan	{"Alert Distance":47.96}	json	a few seconds ago
Kannan	{"Alert Distance":47.96}	json	a few seconds ago
Kannan	{"Alert Distance":47.96}	json	a few seconds ago
Kannan	{"Alert Distance":47.96}	json	a few seconds ago

Items per page 50 | 1-2 of 2 items

1 of 1 page

<

1

>

Getting alert message from wokwi