

Assignment -4

Assignment Date	November 2, 2022
Student Name	Krishna Anusha M
Student Roll Number	962819106027
Maximum Marks	2 Marks

Question-1:

1. Write code and connections in wokwi for the ultrasonic sensor.
2. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.
3. Upload document with wokwi share link and images of IBM cloud

Solution :

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>
WiFiClient wifiClient;
#define ORG "exals7"
#define DEVICE_TYPE "Anu123456"
#define DEVICE_ID "Anumeera122643"
#define TOKEN
"fsWRLz3(8SSMXFJO+" #define
speed 0.034
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json"; char topic[] =
"iot-2/cmd/home/fmt/String"; char authMethod[] = "use-token-
auth"; char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient); void
publishData(); const int trigpin=13; const int echopin=12;
String command;
String data="";
long duration;
int dist;
void setup()
{
  Serial.begin(115200);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}
void loop() {
  publishData();
  delay(500); if
  (!client.loop()) {
    mqttConnect();
  }
```

```

}
void wifiConnect() {
  Serial.print("Connecting to ");
  Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6); while
  (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.print("WiFi connected, IP address: ");
  Serial.println(WiFi.localIP());
}
void mqttConnect() { if
(!client.connected()) {
  Serial.print("Reconnecting MQTT client to ");
  Serial.println(server);
  while (!client.connect(clientId, authMethod, token)) {
    Serial.print(".");
    delay(1000);
  }
  initManagedDevice();
  Serial.println();
}
}
void initManagedDevice() {
  if (client.subscribe(topic)) {
    Serial.println(client.subscribe(topic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}
void publishData()
{
  digitalWrite(trigpin,LOW);
  digitalWrite(trigpin,HIGH);
  delayMicroseconds(10);
  digitalWrite(trigpin,LOW);
  duration=pulseIn(echopin,HIGH);
  dist=duration*speed/2;
  if(dist<100){ DynamicJsonDocument doc(1024);
  String payload; doc["AlertDistance:"]=dist;
  serializeJson(doc, payload); delay(3000);
  Serial.print("\n"); Serial.print("Sending
  payload: "); Serial.println(payload);
  if (client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish OK");
  } else {
    Serial.println("Publish FAILED");
  }
}

```

}
}

Simulation

00:31.851 61%

Editing Ultrasonic Distance Sensor

Distance: 64cm

HC-SR04

ESP32

SENDING PAYLOAD: {"ALERTDistance":45}
PUBLISH OK

SENDING PAYLOAD: {"ALERTDistance":87}
PUBLISH OK

SENDING PAYLOAD: {"ALERTDistance":54}
PUBLISH OK

SENDING PAYLOAD: {"ALERTDistance":64}
PUBLISH OK