

## PROJECT DEVELOPMENT PHASE DELIVERY OF SPRINT-2

Date	5 November 2022
Team ID	PNT2022TMID46732
Project Name	Industry Specific Intelligent Fire Management System

```
#include <WiFi.h>
#include <Wire.h>
#include <SPI.h>
#include
"ThingSpeak.h"
#include
<WiFiClient.h>
```

```
unsigned long myChannelNumber = 2;
const char * myWriteAPIKey = "25V40ZAPI6KIZFGY";
int LED_PIN = 32; // the current reading from the input
pin int BUZZER_PIN= 12;
const int mq2 =
4; int value = 0;
```

```
//Flame
int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital
output pin int flame_pin = HIGH ; // current state of sensor
```

```
char ssid[] = "jenito";
char pass[] = "jose
jenito"; WiFiClient
client; #define
PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0
#define RELAY_PIN 17
#define RELAY_PIN1 27
```

```
void setup()
{
  Serial.begin(115200);
  pinMode(RELAY_PIN, OUTPUT);
  pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to
"); Serial.println(ssid);
  WiFi.begin(ssid, pass);
  int wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(1000);
    Serial.print(".")
  }
  ;
```

```

}
Serial.println("WiFi
connected");
ThingSpeak.begin(client);
pinMode(LED_PIN, OUTPUT);
pinMode(mq2, INPUT);
pinMode ( flame_sensor_pin , INPUT ); // declaring sensor pin as input pin for
Arduino pinMode(BUZZER_PIN, OUTPUT);
}

```

```

void temperature()
{
  int adcVal = analogRead(PIN_LM35);
  float milliVolt = adcVal * (ADC_VREF_mV / ADC_RESOLUTION);
  float tempC = milliVolt / 10;
  Serial.print("Temperature:
"); Serial.print(tempC);
  Serial.print("°C");
  if(tempC > 60)
  {
    Serial.println("Alert");
    digitalWrite(BUZZER_PIN, HIGH); // turn
    on
  }
  else
  {
    digitalWrite(BUZZER_PIN, LOW); // turn on
  }
  int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);
}

```

```

void GasSensors()
{
  //mq2

  int gassensorAnalogmq2 =
  analogRead(mq2); Serial.print("mq2 Gas
Sensor: ");
  Serial.print(gassensorAnalogmq2);
  Serial.print("\t");
  Serial.print("\t");
  Serial.print("\t");

  if (gassensorAnalogmq2 > 1500)
  {
    Serial.println("mq2Gas"
); Serial.println("Alert");
  }
}

```

```

    digitalWrite(RELAY_PIN1, HIGH); // turn on fan 10
    seconds delay(100);
}
else
{
    Serial.println("No mq2Gas");
    digitalWrite(RELAY_PIN1, LOW); // turn off fan 10
    seconds delay(100);
}

int a = ThingSpeak.writeField(myChannelNumber,4,
gassensorAnalogmq2, myWriteAPIKey);
}

void flamesensor()
{
    flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from the
    sensor if (flame_pin == LOW ) // applying condition
    {
        Serial.println ( " ALERT: FLAME DETECTED" ) ;
        digitalWrite (BUZZER_PIN, HIGH ) ;// if state is high, then turn high the BUZZER
    }
    else
    {
        Serial.println ( " NO FLAME DETECTED " ) ;
        digitalWrite (BUZZER_PIN , LOW ) ; // otherwise turn it low
    }
    int value = digitalRead(flame_sensor_pin); // read the analog value from sensor

    if (value ==LOW) {
        Serial.print("FLAME");
        digitalWrite(RELAY_PIN, HIGH);
    } else {
        Serial.print("NO FLAME");
        digitalWrite(RELAY_PIN, LOW);
    }
}

void loop()
{
    temperature(
    );
    GasSensors()
    ;
    flamesensor(
    );
}

```