

Assignment -4

Ultrasonic Sensor

Assignment Date	10 November 2022
Student Name	Mr. ANTONY GUNAL
Student Roll Number	2019503006
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events.

Source Code:

```
#include <WiFi.h>
#include <PubSubClient.h>
void callback(char* subscribtopic, byte* payload, unsigned int payloadLength);
#define ORG "ir6i2l"
#define DEVICE_TYPE "node_assgn4"
#define DEVICE_ID "73585"
#define TOKEN "91766210"
String data3;
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribtopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
const int trigPin = 5;
const int echoPin = 18;
#define SOUND_SPEED 0.034
long duration;
float distance;
void setup() {
  Serial.begin(115200);
  pinMode(trigPin, OUTPUT);
  pinMode(echoPin, INPUT);
  wificonnect();
  mqttconnect();
}
void loop()
{
  digitalWrite(trigPin, LOW);
  delayMicroseconds(2);
  digitalWrite(trigPin, HIGH);
  delayMicroseconds(10);
  digitalWrite(trigPin, LOW);
  duration = pulseIn(echoPin, HIGH);
  distance = duration * SOUND_SPEED/2;
  Serial.print("Distance (cm): ");
```

```

Serial.println(distance);
if(distance<100)
{
Serial.println("ALERT!!");
delay(1000);
PublishData(distance);
delay(1000);
if (!client.loop()) {
mqttconnect();
}
}
delay(1000);
}
void PublishData(float dist) {
mqttconnect();
String payload = "{\"Distance\":\"";
payload += dist;
payload += "\",\"ALERT!!\":\"\"Distance less than 100cms\"";
payload += "\"}";
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish ok");
} else {
Serial.println("Publish failed");
}
}
void mqttconnect() {
if (!client.connected()) {
Serial.print("Reconnecting client to ");
Serial.println(server);
while (!!!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}
void wificonnect()
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address: ");
Serial.println(WiFi.localIP());
}

```

```

void initManagedDevice() {
  if (client.subscribe(subscribetopic)) {
    Serial.println((subscribetopic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
  Serial.print("callback invoked for topic: ");
  Serial.println(subscribetopic);
  for (int i = 0; i < payloadLength; i++)
  {
    data3 += (char)payload[i];
  }
  Serial.println("data: "+ data3);
  data3="";
}

```

Output:

The screenshot shows the Wokwi IDE interface. On the left, the 'sketch.ino' file is open, displaying the following code:

```

1  #include <WiFi.h>
2  #include <PubSubClient.h>
3  void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
4  #define ORG "ir612l"
5  #define DEVICE_TYPE "node_assgn4"
6  #define DEVICE_ID "73585"
7  #define TOKEN "91766210"
8  String data3;
9  char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
10 char publishTopic[] = "iot-2/evt/data/fmt/json";
11 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
12 char authMethod[] = "use-token-auth";
13 char token[] = TOKEN;
14 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
15 WiFiClient wificlient;
16 PubSubClient client(server, 1883, callback, wificlient);
17 const int trigPin = 5;
18 const int echoPin = 18;
19 #define SOUND_SPEED 0.034
20 long duration;
21 float distance;
22 void setup() {
23   Serial.begin(115200);
24   pinMode(trigPin, OUTPUT);
25   pinMode(echoPin, INPUT);
26   wifiConnect();
27   mqttConnect();
28 }
29 void loop()
30 {
31   digitalWrite(trigPin, LOW);
32   delayMicroseconds(2);
33   digitalWrite(trigPin, HIGH);

```

On the right, the 'Simulation' window shows a visual representation of the ESP32 and the ultrasonic sensor connected by wires. Below the simulation, the serial monitor displays the output:

```

ALERT!!! ALERT!!! Object Detected
ALERT!!! ALERT!!! Object Detected
ALERT!!! ALERT!!! Object Detected
ALERT!!! ALERT!!! Object Detected

```

IBM Watson IoT Platform

2019503559@smartinternz.com ID: lr6l2l

Browse

Action

Device Types

Interfaces

Add Device

Q

Search by Device ID

Device Simulator

	Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location
>	<input type="checkbox"/>	73585	Disconnected	DeviceNode	Device	Nov 22, 2022 10:35 PM
>	<input type="checkbox"/>	73585	Disconnected	NodeMCU	Device	Nov 21, 2022 10:52 PM
▼	<input checked="" type="checkbox"/>	73585	Disconnected	node_assign4	Device	Nov 25, 2022 10:41 AM

Identity

Device Information

Recent Events

State

Logs

×

Device ID

73585

Device Type

node_assign4

Date Added

Nov 25, 2022 10:41 AM

Added By

2019503559@smartinternz.com

Connection Status

Disconnected

>

☐

abcd_1

Disconnected

abcd

Device

Nc

2 Simulations running