

PROJECT DEVELOPMENT PHASE

DELIVERY OF SPRINT-3

Date	15 November 2022
Team ID	PNT2022TMID29501
Project Name	Industry Specific Intelligence Fire Management System

```
#include <WiFi.h>
#include <Wire.h>
#include <SPI.h>
#include "ThingSpeak.h"
#include
<WiFiClient.h>

unsigned long myChannelNumber = 2;
const char * myWriteAPIKey = "25V40ZAPI6KIZFGY";
int LED_PIN = 32;
// the current reading from the input pin
int BUZZER_PIN= 12;
const int mq2 = 4;
int value = 0;

//Flame int flame_sensor_pin = 10 ;
// initializing pin 10 as the sensor digital output pin int flame_pin = HIGH ;
// current state of sensor

char ssid[] = "RATHIDEVI";
char pass[] = "RATHIDEVI";
WiFiClient client;
#define PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0
#define RELAY_PIN 17
#define RELAY_PIN1 27
```

```

void setup()
{
  Serial.begin(115200);
  pinMode(RELAY_PIN, OUTPUT);
  pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to ");
  Serial.println(ssid);
  WiFi.begin(ssid, pass);
  int wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(1000);
    Serial.print(".");
  }
  Serial.println("WiFi connected");
  ThingSpeak.begin(client);
  pinMode(LED_PIN, OUTPUT);
  pinMode(mq2, INPUT);
  pinMode ( flame_sensor_pin , INPUT );
  // declaring sensor pin as input pin for Arduino  pinMode(BUZZER_PIN, OUTPUT);
}

```

```

void temperature()
{
  int adcVal = analogRead(PIN_LM35);
  float milliVolt = adcVal *
  (ADC_VREF_mV / ADC_RESOLUTION);
  float tempC = milliVolt / 10;
  Serial.print("Temperature: ");
  Serial.print(tempC);
  Serial.print("°C");
  if(tempC > 60)
  {
    Serial.println("Alert");
    digitalWrite(BUZZER_PIN, HIGH);
  } // turn on
  else

```

```

    {
        digitalWrite(BUZZER_PIN, LOW);
// turn on
    }
    int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);
}
void GasSensors()
{
    //mq2

    int gassensorAnalogmq2 = analogRead(mq2);
    Serial.print("mq2 Gas Sensor: ");
    Serial.print(gassensorAnalogmq2);
    Serial.print("\t");
    Serial.print("\t");
    Serial.print("\t");

    if (gassensorAnalogmq2 > 1500)
    {
        Serial.println("mq2Gas");
        Serial.println("Alert");
        digitalWrite(RELAY_PIN1, HIGH);
        // turn on fan 10 seconds  delay(100);
    }
    else
    {
        Serial.println("No mq2Gas");
        digitalWrite(RELAY_PIN1,
        LOW);
        // turn off fan 10 seconds  delay(100);

    }

    Int a = ThingSpeak.writeField(myChannelNumber,4,gassensorAnalogmq2,
    myWriteAPIKey);
}

```

```

void flamesensor()
{
  flame_pin = digitalRead ( flame_sensor_pin );
  // reading from the sensor if
  (flame_pin == LOW )
  // applying condition
  {
    Serial.println ( " ALERT: FLAME IS DETECTED" );
    digitalWrite (BUZZER_PIN, HIGH );
    // if state is high, then turn high the BUZZER
  }
  else
  {
    Serial.println ( " NO FLAME DETECTED " );
    digitalWrite (BUZZER_PIN , LOW );
    // otherwise turn it low
  }
  int value = digitalRead(flame_sensor_pin);
  // read the analog value from sensor
  if (value ==LOW)
  {
    Serial.print("FLAME");
    digitalWrite(RELAY_PIN, HIGH);
  }
  else
  {
    Serial.print("NO FLAME");
    digitalWrite(RELAY_PIN, LOW);
  }
}

void loop()
{
  temperature();
  GasSensors();
  flamesensor();
}

```