

Assignment 4

Date	19 Nov 2022
Name	Kamini S
Team ID	PNT2022TMID38177
Project Name	Project-IoTBasedSafetyGadgetForChild SafetyMonitoring& Notification

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100 cms send alert to ibm cloud and display in device recent events. Upload document with wokwi share link and images of ibmcloud

Code

```
#include <WiFi.h> #include
<PubSubClient.h>WiFiClient
wifiClient; String data3;
#define ORG "ozyf7e"
#define DEVICE_TYPE "AnuESP"
#define DEVICE_ID "Anu123"
#define TOKEN "12345678"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";char publishTopic[]
= "iot-2/evt/shreedharen/fmt/json";
char topic[] = "iot-2/cmd/led/fmt/String";char
authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
const int trigpin=5; const int
echopin=18;String
command; String data="";
long duration;float
dist; void setup()
{
  Serial.begin(115200);
  pinMode(led, OUTPUT);
```

```

    pinMode(trigpin, OUTPUT);
    pinMode(echopin, INPUT);
    wifiConnect(); mqttConnect();
}

void loop() {
    bool isNearby = dist < 100;
    digitalWrite(led, isNearby);
    publishData();
    delay(500);
    if (!client.loop()) {
        mqttConnect();
    }
}

void wifiConnect() {
    Serial.print("Connecting to "); Serial.print("Wifi");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.print("WiFi connected, IP address: ");
Serial.println(WiFi.localIP());
}

void mqttConnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting MQTT client to ");
Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(500);
        }
        initManagedDevice();
        Serial.println();
    }
}

void initManagedDevice() {
    if (client.subscribe(topic)) {
        // Serial.println(client.subscribe(topic));
        Serial.println("IBM subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void publishData()
{


```

```

digitalWrite(trigpin,LOW);
digitalWrite(trigpin,HIGH);
delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2; if(dist<100){
    String payload = "{\"Alert Distance\":\"";payload +=
    dist;
    payload += "}"; Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }
}
if(dist>100){
    String payload = "{\"Distance\":\"";payload +=
    dist;
    payload += "}"; Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if(client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    }else {
        Serial.println("Publish FAILED");
    }
}
}
}

```

Connections



Output:

