Assignment -4

NAME : SARASWATHI

ROLL NUMBER: 715319104026

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100 cms send "alert" to ibm cloud and display in device recent events. Upload document with wokwi share link and images of ibm cloud


CODE

```
#include <WiFi.h>
#include < PubSubClient.h >
WiFiClient wifiClient;
String data3;
#define ORG "4yi0vc"
#define DEVICE_TYPE "nodeMcu"
#define DEVICE ID "Assignment4"
#define TOKEN "123456789"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();
const int trigpin=5;
const int echopin=18;
String command;
String data="";
long duration;
float dist;
```

```
void setup()
 Serial.begin(115200);
 pinMode(led, OUTPUT);
 pinMode(trigpin, OUTPUT);
 pinMode(echopin, INPUT);
 wifiConnect();
 mqttConnect();
void loop() {
 bool is Nearby = dist < 100;
 digitalWrite(led, isNearby);
 publishData();
 delay(500);
 if (!client.loop()) {
  mqttConnect();
}
void wifiConnect() {
 Serial.print("Connecting to "); Serial.print("Wifi");
 WiFi.begin("Wokwi-GUEST", "", 6);
 while (WiFi.status() != WL_CONNECTED) {
  delay(500);
  Serial.print(".");
 Serial.print("WiFi connected, IP address: ");
Serial.println(WiFi.localIP());
void mqttConnect() {
 if (!client.connected()) {
  Serial.print("Reconnecting MQTT client to ");
Serial.println(server);
  while (!client.connect(clientId, authMethod, token)) {
   Serial.print(".");
   delay(500);
  initManagedDevice();
  Serial.println();
}
```

```
void initManagedDevice() {
 if (client.subscribe(topic)) {
  // Serial.println(client.subscribe(topic));
  Serial.println("IBM subscribe to cmd OK");
 } else {
  Serial.println("subscribe to cmd FAILED");
}
void publishData()
 digitalWrite(trigpin,LOW);
 digitalWrite(trigpin,HIGH);
 delayMicroseconds(10);
 digitalWrite(trigpin,LOW);
 duration=pulseIn(echopin,HIGH);
 dist=duration*speed/2;
 if(dist<100){
  String payload = "{\"Normal Distance\":";
  payload += dist;
  payload += "}";
  Serial.print("\n");
  Serial.print("Sending payload: ");
  Serial.println(payload);
  if (client.publish(publishTopic, (char*) payload.c_str())) {
   Serial.println("Publish OK");
  }
  if(dist>101 && dist<111){
  String payload = "{\"Alert distance\":";
  payload += dist;
  payload += "}";
  Serial.print("\n");
  Serial.print("Sending payload: ");
  Serial.println(payload);
   if(client.publish(publishTopic, (char*) payload.c_str())) {
   Serial.println("Warning crosses 110cm -- it automatically of the loop");
   digitalWrite(led,HIGH);
  }else {
   Serial.println("Publish FAILED");
  }
 }
```

```
void callback(char* subscribeTopic, byte* payload, unsigned int payloadLength){
Serial.print("callback invoked for topic:");
Serial.println(subscribeTopic);
for(int i=0; i<payloadLength; i++){
    dist += (char)payload[i];
}
Serial.println("data:"+ data3);
if(data3=="lighton"){
Serial.println(data3);
    digitalWrite(led,HIGH);
}
data3="";
}
</pre>
```



```
Sending payload: {"Normal Distance":89.95}
Publish OK

Sending payload: {"Normal Distance":89.95}
Publish OK


Sending payload: {"Normal Distance":89.95}
Publish OK

Sending payload: {"Normal Distance":89.98}
Publish OK

Sending payload: {"Normal Distance":89.95}
Publish OK

Sending payload: {"Normal Distance":89.95}
Publish OK

Sending payload: {"Normal Distance":89.95}
Publish OK
```



```
Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop


Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automaticaly of the loop
```



```
Sending payload: {"Alert distance":106.96}
Warning crosses 110cm -- it automatically of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automatically of the loop


Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automatically of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automatically of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automatically of the loop

Sending payload: {"Alert distance":106.98}
Warning crosses 110cm -- it automatically of the loop
```

OUTPUT



Connection Information

Basic connection information about this device.

Device ID Assignment4
Device Type nodeMcu

Date Added 23 Oct 2022 07:20

Added By 920219104302@smartinternz.com

Connection Status Disconnected

Last Connected: 23 Oct 2022 16:57 Client Address: 145.40.94.93 Insecure

Duration: 3 minutes Data Transferred: 14.4 KB

Recent Events

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"Normal Distance":92.99}	json	a few seconds ago
Data	{"Normal Distance":92.99}	json	a few seconds ago
Data	{"Normal Distance":92.99}	json	a few seconds ago
Data	{"Normal Distance":92.99}	json	a few seconds ago
Data	{"Normal Distance":92.99}	json	a few seconds ago