

Assignment -4

ESP32 Programming with IBM Cloud

| | |
|---------------------|-----------------|
| Assignment Date | 3 November 2022 |
| Student Name | Anuja.g |
| Student Roll Number | 821819104301 |
| Maximum Marks | 2 Marks |

Question-1:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100cms send "alert" to ibm cloud and display in device recent events.

Upload document with wokwi share link and images of ibm cloud.

Solution:

```
#include <WiFi.h> //library for wifi #include
<PubSubClient.h> //library for MQTT

#define ECHO_GPIO 12
#define TRIGGER_GPIO 13
#define MAX_DISTANCE_CM 100 // Maximum of 5 meters
#include "Ultrasonic.h"

Ultrasonic ultrasonic(13, 12); int distance;
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-----credentials of IBM Accounts-----

#define ORG "2melo1" //IBM ORGANITION ID
#define DEVICE_TYPE "Kruthika" //Device type mentioned in ibm Watson IOT
Platform
#define DEVICE_ID "0405" //Device ID mentioned in ibm watson IOT
Platform #define TOKEN "12345678" //Token
String data3; float h,
t;

//----- Customise the above values ----- char server[] = ORG
".messaging.internetofthings.ibmcloud.com"; // Server Name
char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and
format in which data to be send char subscribetopic[] = "iot-2/cmd/command/fmt/String"; //
cmd REPRESENT command type AND
COMMAND IS TEST OF FORMAT STRING char authMethod[] =
"use-token-auth"; // authentication method char token[] =
TOKEN; char clientId[] = "d:" ORG ":" DEVICE_TYPE ":"
DEVICE_ID; //client id
```

```

//-----
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by
passing parameter like server id,portand wificredential
void setup()// configuring the ESP32 {

  Serial.begin(115200);
  delay(10);  Serial.println();
  wificlient(); mqttconnect();
}

void loop()// Recursive Function
{

  distance = ultrasonic.read(CM); if(distance
< 100){
  Serial.print("Distance in CM: ");
  Serial.println(distance);
  PublishData(distance); delay(1000);
  if
  (!client.loop()) { mqttconnect();
  }
  }

  delay(1000);

}

/*.....retrieving to Cloud ..... */
void PublishData(float temp) {
  mqttconnect();//function call for connecting to ibm
  /* creating the String in in form JSon to update the data to ibm cloud
  */
  String payload = "{\"Alert Distance\":\""; payload
+= temp; payload
+= "\"}";

  Serial.print("Sending payload: ");
  Serial.println(payload);

  if (client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will
    print publish ok in Serial monitor or else it will print publish failed
  } else { Serial.println("Publish failed");
  }
}
}

```

```

void mqttconnect() { if (!client.connected()) {
    Serial.print("Reconnecting client to ");
    Serial.println(server); while
    (!client.connect(clientId, authMethod, token))
    { Serial.print("."); delay(500);
    }
}
initManagedDevice();
    Serial.println();
} } void wificonnect() //function defination for
wificonnect
{
    Serial.println();
    Serial.print("Connecting to ");

    WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish
the connection while (WiFi.status() != WL_CONNECTED) { delay(500);
Serial.print(".");
}
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}
void initManagedDevice() { if
(client.subscribe(subscribetopic))
    { Serial.println((subscribetopic));
      Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{

    Serial.print("callback invoked for topic: ");
    Serial.println(subscribetopic); for (int i = 0;
i < payloadLength; i++) {
        //Serial.print((char)payload[i]);
        data3 += (char)payload[i]; }
    Serial.println("data: "+ data3);
    if(data3=="lighton") {
        Serial .println(data3);
    } else
    {
        Serial .println(data3);
    } data3=
    "";
}

```

