

ДЗ 2

Вар 21

№	A	B
21.	70	47

Задание 1

A = 70, B = 47

$A > 0, B > 0.$

		Интерпретации	
		Знаковая	Беззнаковая
+	$ \begin{array}{r ccccccc} A_{\text{пр.}} & 0 & 1 & 0 & 0 & 0 & 1 & 1 & 0 \\ B_{\text{пр.}} & 0 & 0 & 1 & 0 & 1 & 1 & 1 & 1 \\ \hline C_{\text{пр.}} & 0 & 1 & 1 & 1 & 0 & 1 & 0 & 1 \end{array} $	$ \begin{array}{r} + 70 \\ + 47 \\ \hline 117 \end{array} $	$ \begin{array}{r} + 70 \\ + 47 \\ \hline 117 \end{array} $

CF=0, ZF=0, PF=0, AF=1, SF=0, OF=0.

$A > 0, B < 0.$

		Интерпретации	
		Знаковая	Беззнаковая
+	$ \begin{array}{r ccccccc} A_{\text{пр.}} & 0 & 1 & 0 & 0 & 0 & 1 & 1 & 0 \\ B_{\text{доп.}} & 1 & 1 & 0 & 1 & 0 & 0 & 0 & 1 \\ \hline C_{\text{пр.}} & 0 & 0 & 0 & 1 & 0 & 1 & 1 & 1 \end{array} $	$ \begin{array}{r} + 70 \\ + -47 \\ \hline 23 \end{array} $	$ \begin{array}{r} + 70 \\ + 209 \\ \hline 23? \end{array} $

CF=1, ZF=0, PF=1, AF=0, SF=0, OF=0.

$A < 0, B > 0.$

		Интерпретации	
		Знаковая	Беззнаковая
+	$ \begin{array}{r ccccccc} A_{\text{доп.}} & 1 & 0 & 1 & 1 & 1 & 0 & 1 & 0 \\ B_{\text{пр.}} & 0 & 0 & 1 & 0 & 1 & 1 & 1 & 1 \\ \hline C_{\text{доп.}} & 1 & 1 & 1 & 0 & 1 & 0 & 0 & 1 \\ \hline C_{\text{пр.}} & 1 & 0 & 0 & 1 & 0 & 1 & 1 & 1 \end{array} $	$ \begin{array}{r} + -70 \\ + 47 \\ \hline -23 \end{array} $	$ \begin{array}{r} + 186 \\ + 47 \\ \hline 233 \end{array} $

CF=0, ZF=0, PF=1, AF=1, SF=1, OF=0.

$$A < 0, B < 0.$$

										Интерпретации			
										Знаковая	Беззнаковая		
+	$A_{\text{доп.}}$	1	0	1	1	1	0	1	0	+	-70	+	186
	$B_{\text{доп.}}$	1	1	0	1	0	0	0	1	+	-47	+	209
	$C_{\text{доп.}}$	1	0	0	0	1	0	1	1				395?
	$C_{\text{пр.}}$	1	1	1	1	0	1	0	1	-	117		

CF=1, ZF=0, PF=0, AF=0, SF=1, OF=0.

Задание 2

$$A = 70$$

$A + B > 128$, значит $127 > B > 128 - A$, пусть $B = 100$.

$$A > 0, B > 0.$$

										Интерпретации			
										Знаковая	Беззнаковая		
+	$A_{\text{пр.}}$	0	1	0	0	0	1	1	0	+	70	+	70
	$B_{\text{пр.}}$	0	1	1	0	0	1	0	0	+	100	+	100
	$C_{\text{доп.}}$	1	0	1	0	1	0	1	0				170
	$C_{\text{пр.}}$	1	1	0	1	0	1	1	0	-	86?		

$$CF=0, ZF=0, PF=1, AF=0, SF=1, OF=1.$$

$$A < 0, B < 0.$$

										Интерпретации			
										Знаковая	Беззнаковая		
+	$A_{\text{доп.}}$	1	0	1	1	1	0	1	0	+	-70	+	70
	$B_{\text{доп.}}$	1	0	0	1	1	1	0	0	+	-100	+	100
	$C_{\text{пр.}}$	0	1	0	1	0	1	1	0		86?		86 ?

$$CF=1, ZF=0, PF=1, AF=1, SF=0, OF=1.$$

Задание 3

Значение числа B фиксируем ($B = 47$), а значение A подбираем согласно формуле $A + B = 128$. Тогда $A = 81$.

$$A > 0, B > 0.$$

										Интерпретации			
										Знаковая	Беззнаковая		
+	$A_{\text{пр.}}$	0	1	0	1	0	0	0	1	+	81	+	81
	$B_{\text{пр.}}$	0	0	1	0	1	1	1	1	+	47	+	47
	$C_{\text{доп.}}$	1	0	0	0	0	0	0	0				128
	$C_{\text{пр.}}$	1	0	0	0	0	0	0	0	-	128?		

$$\text{CF}=0, \text{ ZF}=0, \text{ PF}=0, \text{ AF}=1, \text{ SF}=1, \text{ OF}=1.$$
$$A < 0, B < 0.$$

Интерпретации

[illegible]
$$\text{CF}=1, \text{ ZF}=0, \text{ PF}=0, \text{ AF}=1, \text{ SF}=1, \text{ OF}=0.$$