

ДЗ 3

Вар 22

№	A	B
22.	85	34

Задание 1

A = 85, B = 34

$A > 0, B > 0$.

		Интерпретации	
		Знаковая	Беззнаковая
$A_{\text{пр.}}$	0 1 0 1 0 1 0 1	85	85
$B_{\text{пр.}}$	0 0 1 0 0 0 1 0	34	34
$C_{\text{пр.}}$	0 0 1 1 0 0 1 1	51	51

CF=0, ZF=0, PF=1, AF=0, SF=0, OF=0.

$A < 0, B > 0$.

		Интерпретации	
		Знаковая	Беззнаковая
$A_{\text{доп.}}$	1 0 1 0 1 0 1 1	-85	171
$B_{\text{пр.}}$	0 0 1 0 0 0 1 0	34	34
$C_{\text{доп.}}$	1 0 0 0 1 0 0 1		137
$C_{\text{пр.}}$	1 1 1 1 0 1 1 1	-119	

CF=0, ZF=0, PF=1, AF=0, SF=1, OF=0.

$A > 0, B < 0$.

		Интерпретации	
		Знаковая	Беззнаковая
$A_{\text{пр.}}$	0 1 0 1 0 1 0 1	85	85
$B_{\text{доп.}}$	1 1 0 1 1 1 1 0	-34	222
$C_{\text{пр.}}$	0 1 1 1 0 1 1 1	119	119?

CF=1, ZF=0, PF=1, AF=1, SF=0, OF=0.

$A < 0, B < 0$.

		Интерпретации	
		Знаковая	Беззнаковая
$A_{\text{доп.}}$	1 0 1 0 1 0 1 1	-85	171
$B_{\text{доп.}}$	1 1 0 1 1 1 1 0	-34	222
$C_{\text{доп.}}$	1 1 0 0 1 1 0 1		205?
$C_{\text{пр.}}$	1 0 1 1 0 0 1 1	-51	

CF=1, ZF=0, PF=1, AF=1, SF=1, OF=0.

Задание 2

$A = 85$

$A + B > 128$, значит $128 - A < B < 127$

$A = 85$, $B = 99$ (подбираем).

$A < 0$, $B > 0$.

		Интерпретации							
		Знаковая				Беззнаковая			
$A_{\text{доп.}}$	1	0	1	0	1	0	1	1	-85
$B_{\text{пр.}}$	0	1	1	0	0	0	1	1	99
$C_{\text{пр.}}$	0	1	0	0	1	0	0	0	72?

CF=0, ZF=0, PF=1, AF=0, SF=0, OF=1.

$A > 0$, $B < 0$.

		Интерпретации							
		Знаковая				Беззнаковая			
$A_{\text{пр.}}$	0	1	0	1	0	1	0	1	85
$B_{\text{доп.}}$	1	0	0	1	1	1	0	1	-99
$C_{\text{доп.}}$	1	0	1	1	1	0	0	0	
$C_{\text{пр.}}$	1	1	0	0	1	0	0	0	-72?

CF=1, ZF=0, PF=1, AF=1, SF=1, OF=1.

Задание 3

Значение числа B фиксируем ($B = 34$), а значение A подбираем согласно формуле $A + B = 128$. Тогда $A = 94$.

$A > 0$, $B < 0$.

		Интерпретации							
		Знаковая				Беззнаковая			
$A_{\text{пр.}}$	0	1	0	1	1	1	1	0	94
$B_{\text{доп.}}$	1	1	0	1	1	1	1	0	-34
C	1	0	0	0	0	0	0	0	-128?

CF=1, ZF=0, PF=0, AF=0, SF=1, OF=1.

$A < 0$, $B > 0$.

		Интерпретации							
		Знаковая				Беззнаковая			
$A_{\text{доп.}}$	1	0	1	0	0	0	1	0	-94
$B_{\text{пр.}}$	0	0	1	0	0	0	1	0	34
C	1	0	0	0	0	0	0	0	-128

CF=0, ZF=0, PF=0, AF=0, SF=1, OF=0.