copyright by Holistic Education

Inductance

Self Inductance

- Self inductance: property of a coil in which a change in current through the coil induces an emf in the coil itself.
- Lenz's law: the induced emf opposes the change in current that produces it.
- Inductance: $L = \frac{N\Phi_B}{I}$ (N: number of turns, Φ_B: magnetic flux through one turn, I: current)
- Unit: henry (H) = $T \cdot m^2/A = \Omega \cdot s$
- Inductance of a solenoid: $L = \frac{\mu_0 N^2 A}{l}$ (A: cross-sectional area, l: length)
- Inductance of a toroid: $L = \frac{\mu_0 N^2 A}{2\pi r}$ (r: mean radius)
- Induced emf: $\mathcal{E} = -L\frac{dI}{dt}$
- Energy stored in an inductor: $U = \frac{1}{2}LI^2$
- Energy density in a magnetic field: $u = \frac{B^2}{2\mu_0}$

Electrical oscillations

- Electrical oscillations: periodic variation of charge, current, and voltage in a circuit.
- Simple harmonic motion: $x = A\cos(\omega t + \phi)$ (A: amplitude, ω: angular frequency, ϕ: phase constant)
- Angular frequency: $\omega = 2\pi f = \frac{2\pi}{T}$ (f: frequency, T: period)
- Velocity: $v = -\omega A\sin(\omega t + \phi)$
- Acceleration: $a = -\omega^2 A\cos(\omega t + \phi) = -\omega^2 x$
- Maximum velocity: $v_{max} = \omega A$
- Maximum acceleration: $a_{max} = \omega^2 A$
- Kinetic energy: $K = \frac{1}{2}mv^2 = \frac{1}{2}m\omega^2 A^2\sin^2(\omega t + \phi)$
- Potential energy: $U = \frac{1}{2}kx^2 = \frac{1}{2}kA^2\cos^2(\omega t + \phi)$
- Total energy: $E = K + U = \frac{1}{2}kA^2 = \frac{1}{2}m\omega^2 A^2$
- Energy is conserved in simple harmonic motion.
- Mass-spring system: $\omega = \sqrt{\frac{k}{m}}$, $T = 2\pi\sqrt{\frac{m}{k}}$
- Simple pendulum: $\omega = \sqrt{\frac{g}{L}}$, $T = 2\pi\sqrt{\frac{L}{g}}$ (L: length of pendulum, g: acceleration due to gravity)
- Physical pendulum: $\omega = \sqrt{\frac{mgd}{I}}$, $T = 2\pi\sqrt{\frac{I}{mgd}}$ (I: moment of inertia about pivot, d: distance from pivot to center of mass)
- Damped oscillation: oscillation with decreasing amplitude due to energy loss.
- Damping force: $F_d = -bv$ (b: damping constant)
- Underdamped: $x = Ae^{-bt/2m}\cos(\omega' t + \phi)$, $\omega' = \sqrt{\omega^2 - (\frac{b}{2m})^2}$
- Critically damped: fastest return to equilibrium without oscillation.
- Overdamped: slow return to equilibrium without oscillation.
- Forced oscillation: oscillation driven by an external force.
- Resonance: maximum amplitude when driving frequency equals natural frequency.
- Resonance angular frequency: $\omega_0 = \sqrt{\frac{k}{m}}$
- Quality factor: $Q = \frac{\omega_0}{\Delta\omega}$ ($\Delta\omega$: width of resonance curve at half maximum)
- Higher Q means sharper resonance.

LC circuit

- LC circuit: a circuit containing an inductor and a capacitor.
- Angular frequency: $\omega = \frac{1}{\sqrt{LC}}$
- Frequency: $f = \frac{1}{2\pi\sqrt{LC}}$
- Period: $T = 2\pi\sqrt{LC}$
- Charge on capacitor: $q = Q\cos(\omega t + \phi)$
- Current in circuit: $I = -\omega Q\sin(\omega t + \phi)$
- Energy oscillates between electric field of capacitor and magnetic field of inductor.
- Maximum energy: $U = \frac{Q^2}{2C} = \frac{1}{2}LI^2$

RLC circuit

- RLC circuit: a circuit containing a resistor, an inductor, and a capacitor.
- Impedance: $Z = \sqrt{R^2 + (X_L - X_C)^2}$
- Inductive reactance: $X_L = \omega L$
- Capacitive reactance: $X_C = \frac{1}{\omega C}$
- Resonance occurs when $X_L = X_C$, i.e., $\omega = \frac{1}{\sqrt{LC}}$
- Current: $I = \frac{V}{Z}$
- Phase angle: $\tan\phi = \frac{X_L - X_C}{R}$
- Power factor: $\cos\phi = \frac{R}{Z}$
- Average power: $P_{avg} = I_{rms}^2 R = V_{rms} I_{rms}\cos\phi$
- Quality factor: $Q = \frac{\omega_0 L}{R} = \frac{1}{\omega_0 RC}$
- Bandwidth: $\Delta\omega = \frac{R}{L}$

Maxwell equations

- Maxwell's equations: four fundamental equations describing electromagnetism.
- Gauss's law for electricity: $\oint \vec{E} \cdot d\vec{A} = \frac{Q_{enc}}{\varepsilon_0}$
- Gauss's law for magnetism: $\oint \vec{B} \cdot d\vec{A} = 0$
- Faraday's law of induction: $\oint \vec{E} \cdot d\vec{l} = -\frac{d\Phi_B}{dt}$
- Ampère-Maxwell law: $\oint \vec{B} \cdot d\vec{l} = \mu_0 I_{enc} + \mu_0\varepsilon_0\frac{d\Phi_E}{dt}$
- Displacement current: $I_d = \varepsilon_0\frac{d\Phi_E}{dt}$
- Electromagnetic wave: self-propagating wave of electric and magnetic fields.
- Speed of electromagnetic wave: $c = \frac{1}{\sqrt{\mu_0\varepsilon_0}} = 3.00 \times 10^8$ m/s
- Relationship between E and B: $E = cB$
- Poynting vector: $\vec{S} = \frac{1}{\mu_0}\vec{E} \times \vec{B}$
- Intensity: $I = S_{avg} = \frac{E_{max}B_{max}}{2\mu_0} = \frac{E_{max}^2}{2\mu_0 c}$
- Radiation pressure: $P = \frac{I}{c}$ (absorbed), $P = \frac{2I}{c}$ (reflected)

Transformer

- Transformer: device that changes AC voltage.
- Turns ratio: $a = \frac{N_2}{N_1}$
- Voltage relation: $\frac{V_2}{V_1} = \frac{N_2}{N_1} = a$
- Current relation: $\frac{I_2}{I_1} = \frac{N_1}{N_2} = \frac{1}{a}$
- Power relation: $P_1 = P_2$ (ideal transformer)
- Efficiency: $\eta = \frac{P_2}{P_1} \times 100\%$
- Step-up transformer: $N_2 > N_1$, $V_2 > V_1$, $I_2 < I_1$
- Step-down transformer: $N_2 < N_1$, $V_2 < V_1$, $I_2 > I_1$

Motion of charged particle in magnetic field

- Magnetic force on moving charge: $\vec{F} = q\vec{v} \times \vec{B}$, $F = qvB\sin\theta$
- Right-hand rule: point fingers in direction of $\vec{v}$, curl toward $\vec{B}$, thumb points in direction of $\vec{F}$ for positive charge.
- Circular motion: $r = \frac{mv}{qB}$
- Cyclotron frequency: $f = \frac{qB}{2\pi m}$
- Cyclotron period: $T = \frac{2\pi m}{qB}$
- Velocity selector: $v = \frac{E}{B}$
- Mass spectrometer: $r = \frac{mv}{qB} = \frac{m}{qB}\sqrt{\frac{2qV}{m}}$
- Hall effect: $V_H = \frac{IB}{nqt}$ (n: charge carrier density, t: thickness)
- Hall coefficient: $R_H = \frac{1}{nq}$

Biot-Savart law

- Biot-Savart law: $d\vec{B} = \frac{\mu_0}{4\pi}\frac{I\,d\vec{l} \times \hat{r}}{r^2}$
- Magnetic field of a straight wire: $B = \frac{\mu_0 I}{2\pi r}$
- Magnetic field of a circular loop: $B = \frac{\mu_0 I}{2R}$
- Magnetic field of a solenoid: $B = \mu_0 nI$ ($n = \frac{N}{l}$)
- Magnetic field of a toroid: $B = \frac{\mu_0 NI}{2\pi r}$
- Magnetic field of a long straight wire: $B = \frac{\mu_0 I}{2\pi r}$
- Magnetic field of a circular arc: $B = \frac{\mu_0 I\theta}{4\pi R}$
- Magnetic field of a straight wire segment: $B = \frac{\mu_0 I}{4\pi r}(\sin\theta_2 - \sin\theta_1)$
- Magnetic field of a circular loop at a point on the axis: $B = \frac{\mu_0 IR^2}{2(R^2 + x^2)^{3/2}}$
- Magnetic field of a circular loop at the center: $B = \frac{\mu_0 I}{2R}$
- Magnetic field of a solenoid at the center: $B = \mu_0 nI$
- Magnetic field of a solenoid at the end: $B = \frac{1}{2}\mu_0 nI$