




HO CHI MINH CITY UNIVERSITY OF TECHNOLOGY
COMPUTER ENGINEERING

Microcontroller




Dr. Le Trong Nhan

Mục lục

Chapter 1. LED Animations	7
1 Introduction	8
2 First project on STM32Cube	9
3 Simulation on Proteus	15
4 Exercise and Report	21
4.1 Exercise 1	21
4.2 Exercise 2	22
4.3 Exercise 3	24
4.4 Exercise 4	26
4.5 Exercise 5	30
4.6 Exercise 6	32
4.7 Exercise 7	34
4.8 Exercise 8	35
4.9 Exercise 9	36
4.10 Exercise 10	37

CHƯƠNG 1

LED Animations



1 Introduction

In this manual, the STM32CubeIDE is used as an editor to program the ARM microcontroller. STM32CubeIDE is an advanced C/C++ development platform with peripheral configuration, code generation, code compilation, and debug features for STM32 microcontrollers and microprocessors.



Hình 1.1: STM32Cube IDE for STM32 Programming

The most interest of STM32CubeIDE is that after the selection of an empty STM32 MCU or MPU, or preconfigured microcontroller or microprocessor from the selection of a board, the initialization code generated automatically. At any time during the development, the user can return to the initialization and configuration of the peripherals or middleware and regenerate the initialization code with no impact on the user code. This feature can simplify the initialization process and speedup the development application running on STM32 micro-controller. The software can be downloaded from the link bellow:

https://ubc.sgp1.digitaloceanspaces.com/BKU_Softwares/STM32/stm32cubeide_1.7.0.zip

Moreover, for a hangout class, the program is firstly simulated on Proteus. Students are also supposed to download and install this software as well:

https://ubc.sgp1.digitaloceanspaces.com/BKU_Softwares/STM32/Proteus_8.10_SP0_Pro.exe


The rest of this manual consists of:

- Create a project on STM32Cube IDE
- Create a project on Proteus
- Simulate the project on Proteus

Finally, students are supposed to finish 10 different projects.

2 First project on STM32Cube


Step 1: Launch STM32CubeIDE, from the menu **File**, select **New**, then chose **STM32 Project**



Hình 1.2: Create a new project on STM32CubeIDE


The IDE needs to download some packages, which normally takes time in this first time a project is created.

Step 2: Select the STM32F103C6 in the following dialog, then click on **Next**



Hình 1.3: Select the target device

Step 3: Provide the **Name** and the **Location** for the project.



Hình 1.4: Select the target device

It is important to notice that the **Targeted Project Type** should be **STM32Cube**. In the case this option is disable, step 1 must be repeated. The location path should not contain special characters (e.g. the space). Finally, click on the **Next** button.

Step 4: On the last dialog, just keep the default firmware version and click on **Finish** button.

Step 5: The project is created and the wizard for configuration is display. This utility from CubeIDE can simplify the configuration process for an ARM micro-controller like the STM32.

From the configuration windows, select **Pin configuration**, select the pin **PA5** and set to **GPIO Output** mode, since this pin is connected to an LED in the STM32 development kit.

Step 6: Right click on PA5 and select **Enter user label**, and provide the name for this pin (e.g. **LED_RED**). This step helps programming afterward more memorable.


Finally, save the configuration process by pressing **Ctrl + S** and confirm this step by clicking on **OK** button. The code generation is started.

Step 7: Implement the first blinky project in the main function as follow:


```

1 int main(void)
2 {
3     /* USER CODE BEGIN 1 */
4
5     /* USER CODE END 1 */


```



Hình 1.5: Keep default firmware version



Hình 1.6: Set PA5 to GPIO Output mode



Hình 1.7: Provide a name for PA5

```

6  /* MCU Configuration
7  -----
8  */
9  /* Reset of all peripherals, Initializes the Flash
10   interface and the Systick. */
11 HAL_Init();
12
13 /* USER CODE BEGIN Init */
14
15 /* Configure the system clock */
16 SystemClock_Config();
17
18 /* USER CODE BEGIN SysInit */
19
20 /* USER CODE END SysInit */
21
22 /* Initialize all configured peripherals */
23 MX_GPIO_Init();
24
25 /* USER CODE BEGIN 2 */
26
27 /* USER CODE END 2 */
28
29 /* Infinite loop */
30 /* USER CODE BEGIN WHILE */
31
32 while (1)
33 {

```


```

34     HAL_GPIO_TogglePin(LED_RED_GPIO_Port, LED_RED_Pin);
35     HAL_Delay(1000);
36     /* USER CODE END WHILE */
37
38     /* USER CODE BEGIN 3 */
39 }
40 /* USER CODE END 3 */
41 }
```

Program 1.1: First blinky LED project

Actually, what is added to the main function is line number 34 and 35. Please put your code in a right place, otherwise it can be deleted when the code is generated (e.g. change the configuration of the project). When coding, frequently use the suggestions by pressing **Ctrl+Space**.

Step 7: Due to the simulation on Proteus, the hex file should be generated from STM32Cube IDE. From menu **Project**, select **Properties** to open the dialog bellow:



Hình 1.8: Config for hex file output

Navigate to **C/C++ Build**, select **Settings**, **MCU Post build outputs**, and check to the **Intel Hex file**.

Step 8: Build the project by clicking on menu **Project** and select **Build Project**. Please check on the output console of the IDE to be sure that the hex file is generated, as follow:

```

22:36:06 **** Incremental Build of configuration Debug for project Led_Animations ****
make -j8 all
arm-none-eabi-size  Led_Animations.elf
      text    data     bss     dec   hex filename
      4596       20    1572    6188   182c Led_Animations.elf
Finished building: default.size.stdout

22:36:06 Build Finished. 0 errors, 0 warnings. (took 272ms)
```

Hình 1.9: Compile the project and generate Hex file

The hex file is located under the **Debug** folder of your project, which is used for the simulation in Proteus afterward. In the case a development kit is connected to your PC, from menu **Run**, select **Run** to download the program to the hardware platform.

In the case there are multiple project in a work-space, double click on the project name to activate this project. Whenever a project is built, check the output files to make sure that you are working in a right project.

3 Simulation on Proteus


For an online training, a simulation on Proteus can be used. The details to create an STM32 project on Proteus are described below.

Step 1: Launch Proteus (**with administration access**) and from menu **File**, select **New Project**.




Hình 1.10: Create a new project on Proteus

Step 2: Provide the name and the location of the project, then click on **Next** button.




Hình 1.11: Provide project name and location

Step 3: For following dialog, just click on **Next** button as just a schematic is required for the lab.




Hình 1.12: Keep the default options by clicking on Next

Step 4: Finally, click on **Finish** button to close the project wizard.



Hình 1.13: Finish the project wizard


Step 5: On the main page of the project, right click to select **Place, Components, From Libraries**, as follows:



Hình 1.14: Select a component from the library


If there is an error with no library found, please restart the Proteus software with Run as administrator option.

Step 6: From the list of components in the library, select STM32F103C6, as follows:




Hình 1.15: Select STM32F103C6

Repeat step 5 and 6 to select an LED, named **LED-RED** in Proteus. Finally, these components are appeared on the **DEVICES** windows, which is on left hand side as follows:




Hình 1.16: STM32 and an LED in the project

Step 7: Place the components to the project: right click on the main page, select on **Place, Component**, and select device added in Step 6. To add the Power and the Ground, right click on the main page, select on **Place, Terminal**. The result in this step is expected as follows:



Hình 1.17: Place components to the project


Step 8: Start wiring the circuit. The negative pin of the LED is connected to PA5 while its positive pin is connected to the power supply. For the power and the ground on the right, just make a short wire, which will be labeled in the next step.



Hình 1.18: Connect components and set the power to 3.3V


In this step, also double click on the power supply in order to provide the String property to **+3.3V**.

Step 8: Right click on the wire of the power supply and the ground, and select Place wire Label




Hình 1.19: Place label for Power and Ground

This step is required as VDDA and VSSA of the STM32 must be connected to provide the reference voltage. Therefore, VDDA is connected to 3.3V, while the VSSA is connected to the Ground. Finally, the image of our schematic is shown bellow:




Hình 1.20: Finalize the schematic

Step 9: Double click on the STM32, and set the **Program File** to the Hex file, which is generated from Cube IDE, as following:



Hình 1.21: Set the program of the STM32 to the hex file from Cube IDE

From now, the simulation is ready to start by clicking on the menu **Debug**, and select on **Run simulation**. To stop the simulation, click on **Debug** and select **Stop VMS Debugging**. Moreover, there are some quick access bottom on the left corner of the Proteus to start or stop the simulation, as shown following:



Hình 1.22: Quick access buttons to start and stop the simulation

If everything is success, students can see the LED is blinking every second. Please stop the simulation before updating the project, either in Proteus or STM32Cube IDE. However, the step 9 (set the program file for STM32 in Proteus) is required to do once. Beside the toggle instruction, student can set or reset a pin as following:

```
1 while (1){  
2     HAL_GPIO_WritePin(LED_RED_GPIO_Port , LED_RED_Pin ,  
3                         GPIO_PIN_SET);  
4     HAL_Delay(1000);  
5     HAL_GPIO_WritePin(LED_RED_GPIO_Port , LED_RED_Pin ,  
6                         GPIO_PIN_RESET);  
7     HAL_Delay(1000);  
8 }
```


Program 1.2: An example for LED blinky

4 Exercise and Report

4.1 Exercise 1


From the simulation on Proteus, one more LED is connected to pin **PA6** of the STM32 (negative pin of the LED is connected to PA6). The component suggested in this exercise is **LED-YELLOW**, which can be found from the device list.

In this exercise, the status of two LEDs are switched every 2 seconds, as demonstrated in the figure bellow.



Hình 1.23: State transitions for 2 LEDs

Report 1: Depict the schematic from Proteus simulation in this report. The caption of the figure is a downloadable link to the Proteus project file (e.g. a github link).



Hình 1.24: Proteus Schematic of State transitions for 2 LEDs

Report 2: Present the source code in the infinite loop while of your project. If a user-defined functions is used, it is required to present in this part. A brief description can be added for this function (e.g. using comments). A template to present

your source code is presented below.

```
1 // initiate the state for 2 LEDs
2 HAL_GPIO_WritePin(RED_LED_GPIO_Port, RED_LED_Pin, SET);
    //RED-LED off
3 HAL_GPIO_WritePin(YELLOW_LED_GPIO_Port, YELLOW_LED_Pin,
    RESET); //YELLOW-LED on
4 while (1)
{
    5     HAL_GPIO_TogglePin(RED_LED_GPIO_Port, RED_LED_Pin);
        //toggle red-led on;
    6     HAL_GPIO_TogglePin(YELLOW_LED_GPIO_Port, YELLOW_LED_Pin);
        //toggle yellow-led off;
    7     HAL_Delay(2000);
}
}
```


Program 1.3: Source code for the problem

4.2 Exercise 2

Extend the first exercise to simulate the behavior of a traffic light. A third LED, named **LED-GREEN** is added to the system, which is connected to **PA7**. A cycle in this traffic light is 5 seconds for the RED, 2 seconds for the YELLOW and 3 seconds for the GREEN. The LED-GREEN is also controlled by its negative pin.

Similarly, the report in this exercise includes the schematic of your circuit and a your source code in the while loop.

Report 1: Present the schematic.



Report 2: Present the source code in while.


```

1 //initiate the states and counter
2 int sec = 0;
3 HAL_GPIO_WritePin(RED_GPIO_Port, RED_Pin, RESET);
4 HAL_GPIO_WritePin(YELLOW_GPIO_Port, YELLOW_Pin, SET);
5 HAL_GPIO_WritePin(GREEN_GPIO_Port, GREEN_Pin, SET);
6
7 while (1)
8 {
9     // RED_LED off after 5sec, YELLOW_LED light on
10    if (sec == 5){
11        HAL_GPIO_TogglePin(RED_GPIO_Port, RED_Pin);
12        HAL_GPIO_TogglePin(YELLOW_GPIO_Port, YELLOW_Pin);
13    }
14
15    // YELLOW_LED off after 2sec, GREEN_LED light on
16    else if (sec == 7){
17        HAL_GPIO_TogglePin(YELLOW_GPIO_Port, YELLOW_Pin);
18        HAL_GPIO_TogglePin(GREEN_GPIO_Port, GREEN_Pin);
19    }
20
21    // GREEN_LED off after 3sec, and reset the state
22    else if (sec == 10){
23        HAL_GPIO_TogglePin(GREEN_GPIO_Port, GREEN_Pin);
24        HAL_GPIO_TogglePin(RED_GPIO_Port, RED_Pin);
25        sec = 0;
26    }
27    ++sec;
28    HAL_Delay(1000);
29 }
```


Program 1.4: Source code for the problem

4.3 Exercise 3

Extend to the 4-way traffic light. Arrange 12 LEDs in a nice shape to simulate the behaviors of a traffic light. A reference design can be found in the figure bellow.



Hình 1.26: Reference design for a 4 way traffic light



Hình 1.27: Proteus Schematic of 4-way traffic light using stm32f103c6

```

1 //initiate the counter and states
2 int sec1 = 0;
3 int sec2 = 5; // Group 2 runs 5 seconds later than
4 Group 1
5
6 // Default states for group 1
7 HAL_GPIO_WritePin(RED1_GPIO_Port, RED1_Pin, RESET);
8 HAL_GPIO_WritePin(YELLOW1_GPIO_Port, YELLOW1_Pin, SET);

```

```

9      HAL_GPIO_WritePin(GREEN1_GPIO_Port , GREEN1_Pin , SET);
10
11 // Default states for group 2
12 HAL_GPIO_WritePin(RED2_GPIO_Port , RED2_Pin , RESET);
13 HAL_GPIO_WritePin(YELLOW2_GPIO_Port , YELLOW2_Pin , SET);
14 HAL_GPIO_WritePin(GREEN2_GPIO_Port , GREEN2_Pin , SET);
15
16 while (1)
17 {
18     ++sec1;
19     ++sec2;
20
21     switch(sec1) {
22         // GREEN_LED_1 light on at the 6th second, for 3
23         // seconds
24         case 6:
25             HAL_GPIO_WritePin(RED1_GPIO_Port , RED1_Pin , SET);
26             HAL_GPIO_WritePin(GREEN1_GPIO_Port , GREEN1_Pin ,
27             RESET);
28             break;
29         // GREEN_LED_1 light on at the 9th second, for 2
30         // seconds
31         case 9:
32             HAL_GPIO_WritePin(GREEN1_GPIO_Port , GREEN1_Pin , SET
33             );
34             HAL_GPIO_WritePin(YELLOW1_GPIO_Port , YELLOW1_Pin ,
35             RESET);
36             break;
37         // reset the state
38         case 11:
39             HAL_GPIO_WritePin(YELLOW1_GPIO_Port , YELLOW1_Pin ,
40             SET);
41             HAL_GPIO_WritePin(RED1_GPIO_Port , RED1_Pin , RESET);
42             sec1 = 1;
43             break;
44
45         default:
46             break;
47     }
48
49     // Same as above
50     switch(sec2) {
51         // den XANH2 sang
52         case 6:
53             HAL_GPIO_WritePin(RED2_GPIO_Port , RED2_Pin , SET
54             );
55             HAL_GPIO_WritePin(GREEN2_GPIO_Port , GREEN2_Pin ,
56             RESET);
57             break;

```

```


50         // den VANG2 sang
51         case 9:
52             HAL_GPIO_WritePin(GREEN2_GPIO_Port, GREEN2_Pin,
53             SET);
53             HAL_GPIO_WritePin(YELLOW2_GPIO_Port,
54             YELLOW2_Pin, RESET);
54             break;
55         // reset ve 1, den D02 sang
56         case 11:
57             HAL_GPIO_WritePin(YELLOW2_GPIO_Port,
58             YELLOW2_Pin, SET);
58             HAL_GPIO_WritePin(RED2_GPIO_Port, RED2_Pin,
59             RESET);
59             sec2 = 1;
60             break;
61
62         default:
63             break;
64     }
65
66     HAL_Delay(1000);
67 }
```

Program 1.5: Source code for the problem

4.4 Exercise 4

Add **only one 7 led segment** to the schematic in Exercise 3. This component can be found in Proteus by the keyword **7SEG-COM-ANODE**. For this device, the common pin should be connected to the power supply and other pins are supposed to be connected to PB0 to PB6. Therefore, to turn-on a segment in this 7SEG, the STM32 pin should be in logic 0 (0V).

Implement a function named **display7SEG(int num)**. The input for this function is from 0 to 9 and the outputs are listed as following:



Hình 1.28: Display a number on 7 segment LED


This function is invoked in the while loop for testing as following:

```

1 int counter = 0;
2 while (1){
3     if(counter >= 10) counter = 0;
4     display7SEG(counter++);
5     HAL_Delay(1000);
6
7 }
```

Program 1.6: An example for your source code

Report 1: Present the schematic.



Hình 1.29: Proteus Schematic of 7segments LED

Report 2: Present the source code for display7SEG function.

```

1 void display7SEG(int num){
2
3     switch(num) {
4         case 0:
5             HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
6             HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
7             HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
8             HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
9             HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , RESET);
10            HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
11            HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , SET);
12            break;
13        case 1:
14            HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , SET);
15            HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
16            HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
17            HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , SET);
18            HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
19            HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , SET);
20            HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , SET);
21            break;
22        case 2:
23            HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
24            HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
25            HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , SET);
26            HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
27            HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , RESET);
28            HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , SET);
29            HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
30            break;
31        case 3:
32            HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
33            HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
34            HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
35            HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
36            HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
37            HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , SET);
38            HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
39            break;
40        case 4:
41            HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , SET);
42            HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
43            HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
44            HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , SET);
45            HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
46            HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
47            HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
48            break;
49        case 5:

```

```


50     HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
51     HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , SET);
52     HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
53     HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
54     HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
55     HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
56     HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
57     break;
58 case 6:
59     HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
60     HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , SET);
61     HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
62     HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
63     HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , RESET);
64     HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
65     HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
66     break;
67 case 7:
68     HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
69     HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
70     HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
71     HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , SET);
72     HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
73     HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , SET);
74     HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , SET);
75     break;
76 case 8:
77     HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
78     HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
79     HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
80     HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
81     HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , RESET);
82     HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
83     HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
84     break;
85 case 9:
86     HAL_GPIO_WritePin(a_GPIO_Port , a_Pin , RESET);
87     HAL_GPIO_WritePin(b_GPIO_Port , b_Pin , RESET);
88     HAL_GPIO_WritePin(c_GPIO_Port , c_Pin , RESET);
89     HAL_GPIO_WritePin(d_GPIO_Port , d_Pin , RESET);
90     HAL_GPIO_WritePin(e_GPIO_Port , e_Pin , SET);
91     HAL_GPIO_WritePin(f_GPIO_Port , f_Pin , RESET);
92     HAL_GPIO_WritePin(g_GPIO_Port , g_Pin , RESET);
93     break;
94 default:
95     break;
96 }
97

```

4.5 Exercise 5

Integrate the 7SEG-LED to the 4 way traffic light. In this case, the 7SEG-LED is used to display countdown value.

In this exercise, only source code is required to present. The function `display7SEG` in previous exercise can be re-used.



Hình 1.30: Proteus Schematic of 7-segment LED and 4-way traffic lights

```
1 int sec1 = 0;
2 int sec2 = 5; // cum den 2 se chay cham hon cum-den-1
3 // dong ho cua 7segment bieu dien cho cum den 1
4 int temp_sec = 5; //bat dau dem nguoc 5 giay cua
5 RED_LED
6
7 // trang thai mac dinh cho cum den 1
8 HAL_GPIO_WritePin(RED1_GPIO_Port, RED1_Pin, RESET);
9 HAL_GPIO_WritePin(YELLOW1_GPIO_Port, YELLOW1_Pin, SET
10 );
11 HAL_GPIO_WritePin(GREEN1_GPIO_Port, GREEN1_Pin, SET);
12
13 // trang thai mac dinh cho cum den 2
14 HAL_GPIO_WritePin(RED2_GPIO_Port, RED2_Pin, RESET);
15 HAL_GPIO_WritePin(YELLOW2_GPIO_Port, YELLOW2_Pin, SET
16 );
17 HAL_GPIO_WritePin(GREEN2_GPIO_Port, GREEN2_Pin, SET);
```

```

16
17     while (1)
18 {
19         ++sec1;
20         ++sec2;
21
22         switch(sec1) {
23             // den XANH1 sang
24             case 6:
25                 HAL_GPIO_WritePin(RED1_GPIO_Port, RED1_Pin, SET);
26                 HAL_GPIO_WritePin(GREEN1_GPIO_Port, GREEN1_Pin, RESET);
27                 temp_sec = 3;      // 7segment dem nguoc 3 giay
28             sang cua den xanh
29                 break;
30             // den VANG1 sang
31             case 9:
32                 HAL_GPIO_WritePin(GREEN1_GPIO_Port, GREEN1_Pin, SET);
33                 HAL_GPIO_WritePin(YELLOW1_GPIO_Port, YELLOW1_Pin, RESET);
34                 temp_sec = 2;      // 7segment dem nguoc 2 giay
35             sang cua den vang
36                 break;
37             // reset ve 1, den DO1 sang
38             case 11:
39                 HAL_GPIO_WritePin(YELLOW1_GPIO_Port, YELLOW1_Pin, SET);
40                 HAL_GPIO_WritePin(RED1_GPIO_Port, RED1_Pin, RESET);
41                 temp_sec = 5;      // reset dem nguoc 5 giay den
42             do
43                 sec1 = 1;
44                 break;
45
46             default:
47                 break;
48 }
49
50         //Bieu dien LED 7segment hien tai, sau do giam gia
51         tri de dem nguoc.
52         display7SEG(temp_sec--);
53
54         switch(sec2) {
55             // den XANH2 sang
56             case 6:
57                 HAL_GPIO_WritePin(RED2_GPIO_Port, RED2_Pin, SET);

```

```

54             HAL_GPIO_WritePin(GREEN2_GPIO_Port ,
GREEN2_Pin , RESET);
55             break;
56         // den VANG2 sang
57         case 9:
58             HAL_GPIO_WritePin(GREEN2_GPIO_Port ,
GREEN2_Pin , SET);
59             HAL_GPIO_WritePin(YELLOW2_GPIO_Port ,
YELLOW2_Pin , RESET);
60             break;
61         // reset ve 1, den D02 sang
62         case 11:
63             HAL_GPIO_WritePin(YELLOW2_GPIO_Port ,
YELLOW2_Pin , SET);
64             HAL_GPIO_WritePin(RED2_GPIO_Port , RED2_Pin ,
RESET);
65             sec2 = 1;
66             break;
67
68         default:
69             break;
70     }
71
72     HAL_Delay(1000);
73 }
```


Program 1.8: Source code

4.6 Exercise 6

In this exercise, a new Proteus schematic is designed to simulate an analog clock, with 12 different number. The connections for 12 LEDs are supposed from PA4 to PA15 of the STM32. The arrangement of 12 LEDs is depicted as follows.


This github link is for all exercises from 6 to 10:

https://github.com/JackWrion/Microprocessor/tree/main/Ex6_AnalogClock



Hình 1.31: 12 LEDs for an analog clock

Report 1: Present the schematic.



Hình 1.32: Schematic of 12 LEDs for an analog clock

Report 2: Implement a simple program to test the connection of every single LED. This testing program should turn every LED in a sequence .

```

1 // turn on LEDs in order , it's up to counter.
2 switch(counter){
3     case 0:
4         HAL_GPIO_WritePin(LED0_GPIO_Port , LED0_Pin , RESET);
5             break;
6     case 1:
7         HAL_GPIO_WritePin(LED1_GPIO_Port , LED1_Pin , RESET);
8             break;
9     case 2:
10        HAL_GPIO_WritePin(LED2_GPIO_Port , LED2_Pin , RESET);
11            break;
12    case 3:

```

```

13     HAL_GPIO_WritePin(LED3_GPIO_Port, LED3_Pin, RESET);
14     break;
15 case 4:
16     HAL_GPIO_WritePin(LED4_GPIO_Port, LED4_Pin, RESET);
17     break;
18 case 5:
19     HAL_GPIO_WritePin(LED5_GPIO_Port, LED5_Pin, RESET);
20     break;
21 case 6:
22     HAL_GPIO_WritePin(LED6_GPIO_Port, LED6_Pin, RESET);
23     break;
24 case 7:
25     HAL_GPIO_WritePin(LED7_GPIO_Port, LED7_Pin, RESET);
26     break;
27 case 8:
28     HAL_GPIO_WritePin(LED8_GPIO_Port, LED8_Pin, RESET);
29     break;
30 case 9:
31     HAL_GPIO_WritePin(LED9_GPIO_Port, LED9_Pin, RESET);
32     break;
33 case 10:
34     HAL_GPIO_WritePin(LED10_GPIO_Port, LED10_Pin, RESET);
35     break;
36 case 11:
37     HAL_GPIO_WritePin(LED11_GPIO_Port, LED11_Pin, RESET);
38     break;
39 default:
40     break;
41 }
42 counter++;

```

Program 1.9: Source code

4.7 Exercise 7

Implement a function named **clearAllClock()** to turn off all 12 LEDs. Present the source code of this function.

```

1 void clearAllClock () {
2     HAL_GPIO_WritePin(LEDO_GPIO_Port, LED0_Pin, SET);
3     HAL_GPIO_WritePin(LED1_GPIO_Port, LED1_Pin, SET);
4     HAL_GPIO_WritePin(LED2_GPIO_Port, LED2_Pin, SET);
5     HAL_GPIO_WritePin(LED3_GPIO_Port, LED3_Pin, SET);
6     HAL_GPIO_WritePin(LED4_GPIO_Port, LED4_Pin, SET);
7     HAL_GPIO_WritePin(LED5_GPIO_Port, LED5_Pin, SET);
8     HAL_GPIO_WritePin(LED6_GPIO_Port, LED6_Pin, SET);
9     HAL_GPIO_WritePin(LED7_GPIO_Port, LED7_Pin, SET);
10    HAL_GPIO_WritePin(LED8_GPIO_Port, LED8_Pin, SET);
11    HAL_GPIO_WritePin(LED9_GPIO_Port, LED9_Pin, SET);

```

```

12     HAL_GPIO_WritePin(LED10_GPIO_Port , LED10_Pin , SET);
13     HAL_GPIO_WritePin(LED11_GPIO_Port , LED11_Pin , SET);
14 }
```

Program 1.10: Source code

4.8 Exercise 8

Implement a function named **setNumberOnClock(int num)**. The input for this function is from **0 to 11** and an appropriate LED is turn on. Present the source code of this function.

```

1 void setNumberOnClock(int num){
2
3     switch(num){
4         case 0:
5             HAL_GPIO_WritePin(LEDO_GPIO_Port , LED0_Pin , RESET);
6                 break;
7         case 1:
8             HAL_GPIO_WritePin(LED1_GPIO_Port , LED1_Pin , RESET);
9                 break;
10        case 2:
11            HAL_GPIO_WritePin(LED2_GPIO_Port , LED2_Pin , RESET);
12                break;
13        case 3:
14            HAL_GPIO_WritePin(LED3_GPIO_Port , LED3_Pin , RESET);
15                break;
16        case 4:
17            HAL_GPIO_WritePin(LED4_GPIO_Port , LED4_Pin , RESET);
18                break;
19        case 5:
20            HAL_GPIO_WritePin(LED5_GPIO_Port , LED5_Pin , RESET);
21                break;
22        case 6:
23            HAL_GPIO_WritePin(LED6_GPIO_Port , LED6_Pin , RESET);
24                break;
25        case 7:
26            HAL_GPIO_WritePin(LED7_GPIO_Port , LED7_Pin , RESET);
27                break;
28        case 8:
29            HAL_GPIO_WritePin(LED8_GPIO_Port , LED8_Pin , RESET);
30                break;
31        case 9:
32            HAL_GPIO_WritePin(LED9_GPIO_Port , LED9_Pin , RESET);
33                break;
34        case 10:
35            HAL_GPIO_WritePin(LED10_GPIO_Port , LED10_Pin , RESET)
36    };
37        break;
```

```

37     case 11:
38         HAL_GPIO_WritePin(LED11_GPIO_Port, LED11_Pin, RESET)
39     ;
40         break;
41     default:
42         break;
43 }

```

Program 1.11: Source code

4.9 Exercise 9

Implement a function named **clearNumberOnClock(int num)**. The input for this function is from **0 to 11** and an appropriate LED is turn off.

```

1 void clearNumberOnClock(int num){
2
3     switch(num){
4         case 0:
5             HAL_GPIO_WritePin(LEDO_GPIO_Port, LED0_Pin, SET);
6             break;
7         case 1:
8             HAL_GPIO_WritePin(LED1_GPIO_Port, LED1_Pin, SET);
9             break;
10        case 2:
11            HAL_GPIO_WritePin(LED2_GPIO_Port, LED2_Pin, SET);
12            break;
13        case 3:
14            HAL_GPIO_WritePin(LED3_GPIO_Port, LED3_Pin, SET);
15            break;
16        case 4:
17            HAL_GPIO_WritePin(LED4_GPIO_Port, LED4_Pin, SET);
18            break;
19        case 5:
20            HAL_GPIO_WritePin(LED5_GPIO_Port, LED5_Pin, SET);
21            break;
22        case 6:
23            HAL_GPIO_WritePin(LED6_GPIO_Port, LED6_Pin, SET);
24            break;
25        case 7:
26            HAL_GPIO_WritePin(LED7_GPIO_Port, LED7_Pin, SET);
27            break;
28        case 8:
29            HAL_GPIO_WritePin(LED8_GPIO_Port, LED8_Pin, SET);
30            break;
31        case 9:
32            HAL_GPIO_WritePin(LED9_GPIO_Port, LED9_Pin, SET);
33            break;

```

```

34     case 10:
35         HAL_GPIO_WritePin(LED10_GPIO_Port, LED10_Pin, SET);
36         break;
37     case 11:
38         HAL_GPIO_WritePin(LED11_GPIO_Port, LED11_Pin, SET);
39         break;
40     default:
41         break;
42     }
43 }
```

Program 1.12: Source code

4.10 Exercise 10

Integrate the whole system and use 12 LEDs to display a clock. At a given time, there are only 3 LEDs are turn on for hour, minute and second information.

```

1 //initiate hour, minute and second
2 int sec = 0;
3 int min = 58;
4 int hour = 8;
5
6 // initiate turn off all LEDs.
7 clearAllClock();
8
9 while (1){
10    //Xoa thoi gian cu
11    clearNumberOnClock((sec-1)/5);
12    clearNumberOnClock((min-1)/5);
13    clearNumberOnClock(hour-1);
14
15    //Xu ly tinh toan
16    if (sec == 60 ){
17        sec = 0;
18        ++min;
19    }
20    if (min == 60){
21        min = 0;
22        ++hour;
23    }
24    if (hour == 24){
25        hour = 0;
26    }
27
28
29    //Cap nhat lai thoi gian
30    setNumberOnClock(sec/5);      //5 giay thi chuyen 1 LED
31    setNumberOnClock(min/5);      //5 phut thi chuyen 1 LED
```

```
32     setNumberOnClock(hour);  
33  
34     ++sec;  
35     HAL_Delay(1000);  
36 }
```

Program 1.13: Source code