Lab-experiment

Internetworking with Using Cisco packet tracer

AIM:-

To design and configure simple internetwork using router and test connectivity between 2 PC's.

Network:

1 Router ; 2PC's

copper straight-through cables.

Procedure:

configure routers

*open Router → CLI & enter

enable configure terminal

Interface fastethernet 0/0

ip address 192.168.10.1 255.255.255.0

no shutdown.

exit

interface fastethernet 0/1

ip address 192.168.20.1 255.255.255.0

no shutdown

exit

configure PC's

PC → Desktop → IP configuration.

Device	IP Address	Subnet Mask	gateway
PC0	192.168.10.2	255.255.255.0	192.168.10.1
PC1	192.168.20.2	255.255.255.0	192.168.20.1

connect PC's to router

* connect PC0 FastEthernet 0 → Router FastEthernet 0/0
* connect PC1 Fast ethernet 0 → Router ethernet 0/1
* use copper straight - Through cable.

Test connectivity :-

1) Select PC0
2) use add simple PDU
3) click PC1
4) check whether PDU is successfully delivered.
5) An acknowledge should be received from PC1 to PC0.

Result :-

Thus, simple internetwork using router was successfully designed and configured.