

GE Dishwasher Control PCB - Current Board Map

Work in progress. Solid relationships shown here are measured/confirmed; unknown functions and voltages are explicitly marked TBD.

POWER ENTRY / TRANSFORMER

```
J1-1 ----- V1-1 ----- T1 bottom pin 3
                |
                [ V1 ]
                |
J1-3 ----- V1-2 ----- T1 bottom pin 4 ----- V2 pad 2
J1-2 ----- V2 pad 1
```

Transformer secondary / rectifier / low-voltage rails: [TBD]

RELAY COIL CONTROL

```
          SHARED RELAY COIL RAIL [VOLTAGE TBD]
          |       |       |       |       |
        K1 p3  K2 p3  K3 p3  K4 p3  K5 p3
          +-----+-----+-----+-----+
                |
            D22 RIGHT

K1 p5 ----- U6 p16
K2 p5 ----- U6 p15
K3 p5 ----- U6 p14      U6 = MC1413-family Darlington array
K4 p5 ----- U6 p10      Individual coil paths consistent
K5 p5 ----- U6 p11      with low-side switching.
                |
U6 p9 ----- D22 LEFT
```

RELAY CONTACT / LOAD SIDE

```
K1 p2 ----- J2 p1
K2 p2 ----- J2 p2
K3 p2 ----- J2 p3-4

K1-K5 p4 SHARED WIDE CONTACT BUS ---- J2 p7-8
Bus identity: [TBD]
```

LOGIC / PANEL

U7 bottom-right -- R44 1.001k -- C23 left -- J7 fourth-from-bottom

```
LOGIC GROUND -- C23 right -- J7 first-from-bottom
                |-- C22 negative
                |-- C9 negative
                +-- U5 pin5 (93C86 GND)
```

C8 negative is NOT continuous with logic ground.