

Traffic Light Control

AIM:

Interface Traffic light controller with 8085 using 8255

PROGRAM:

ADDRESS	OPCODE	MNEMONICS
9100	21 00 92	START: LXI H, 9200
9103	0E 08	MVI C, 08
9105	7E	MOV A, M
9106	D3 33	OUT 33
9108	23	INX H
9109	7E	LOOP1: MOV A, M
910A	D3 30	OUT 30
910C	23	INX H
910D	7E	MOV A, M
910E	D3 31	OUT 31
9110	CD 1B 91	CALL DELAY
9113	23	INX H
9114	0D	DCR C
9115	C2 09 91	JNZ LOOP1
9118	C3 00 91	JMP START
911B	C5	DELAY: PUSH B
911C	0E 05	MVI C, 05
911E	11 FF FF	LOOP3: LXI D, FFFF
9121	1B	LOOP2: DCX D
9122	7A	MOV A, D
9123	B3	ORA E
9124	C2 21 91	JNZ LOOP2
9127	0D	DCR C
9128	C2 1E 91	JNZ LOOP3
912B	C1	POP B
912C	C9	RET

ORG 9200H

9200	80
9201	21 09 31 09
9205	0C 09 8C 09
9209	64 08 64 0C
920D	24 03 26 03

DB 80H

DB 21H,09H,31H,09H

DB 0CH,09H,8CH,09H

DB 64H,08H,64H,0CH

DB 24H,03H,26H,03H

END