Lab Assignment 5—Pardon the …Interruption…

Using Hardware Interrupts

Overview

In this lab you'll write assembly code that uses the ReadyAVR's **joystick** to control the blink rate of an on-board LED. Specifically, you'll enable the joystick to generate *hardware interrupts* that trigger the ATmega128A processor to run an interrupt service routine (ISR) which updates a register used by the main program to control the LED's blink rate. You will also have to understand working with memory mapped IO (PORTA, PORTB, PORTD) to configure and control the joystick and LED pins. The ISR routines will cause four other on-board LEDs to show the current blink rate (~1 to 15 Hz) in 4-bit binary and update the blink speed of the onboard LED.

See files **EECE3624_Lab05_Demo.mp4** and **EECE3624LectureWeek05-Interrupts.pdf** on **Canvas→Labs** for more information.

Prelab

Create your Lab05 Repository locally and on cloud

Download Lab05 Starter Files, create local repository, publish your local repository on GitHub, and share your GitHub repository link with your instructor in the same document for prelab questions.

Prelab questions

Do some research by yourself to answer the following questions.

Question 1: State the function of each I/O port register: DDRx, PORTx, and PINx. Then, if DDRD2 = 0 and PORTD2 = 1, explain how PD2 is configured.

DDRx:

_____

PORTx:

_____

PINx:

_____

PD2 configuration:

_____

Question 2: Complete the joystick interrupt wiring below, and briefly explain why the external jumper wires are required.

Joystick UP: PB3 → _____ / INT____

Joystick DOWN: PB1 → _____ / INT____

Why are the jumper wires required?

_____

_____

Question 3: For external interrupts, state the purpose of EICRA, EIMSK, the SREG I-bit/SEI, and the interrupt vector. Which one determines whether the interrupt is triggered by a rising or falling edge?

EICRA:

_____

EIMSK:

_____

SREG I-bit / SEI:

_____

Interrupt vector:

_____

Rising/falling-edge selection is controlled by: _____

Question 4: The ISRs change BlinkFreq while the main program uses BlinkFreq to control the blink rate. Complete the logic below and state what should happen at the two limits.

UP ISR: if BlinkFreq _____ 15, then _____ BlinkFreq

DOWN ISR: if BlinkFreq _____ 1, then _____ BlinkFreq

If BlinkFreq = 15 and UP is selected:

_____

If BlinkFreq = 1 and DOWN is selected:

_____

Question 5: LED0–LED3 display BlinkFreq in 4-bit binary on PORTC.3:0 (PC3 = MSB, PC0 = LSB). Write the four output bits for each value.

BlinkFreq = 1: PC3 PC2 PC1 PC0 = ____ ____ ____ ____

BlinkFreq = 5: PC3 PC2 PC1 PC0 = ____ ____ ____ ____

BlinkFreq = 10: PC3 PC2 PC1 PC0 = ____ ____ ____ ____

BlinkFreq = 15: PC3 PC2 PC1 PC0 = ____ ____ ____ ____

Question 6: Assume BlinkFreq = 6. The user presses and releases the UP joystick. Number the following events in the order they occur.

___ A rising edge occurs on the interrupt pin.

___ The corresponding ISR begins.

___ BlinkFreq becomes 7.

___ LEDs 0–3 display 0111.

___ RETI returns control to the main program.

___ The main program uses the new blink rate.

Lab Procedure

Initial Code Edits

Open the `Lab05.asm` file and notice that it's the same code you used to begin your `Lab02` assignment a few weeks ago. Make the following changes to the file:

1. **Update the program header** to reflect the new program's operation. Mention that the program blinks the "BOOT" LED (connected to **PORTA.7**) at a rate of ~1 to 15 Hz, adjustable in 15 steps, as the joystick is toggled up (faster) or down (slower), and that the blink rate is displayed in 4-bit binary on LEDs 0-3, which are connected to **PORTC.0 (LSB) through PORTC.3 (MSB)**.
   Note: The blink rate and the display must only update after the joystick is ***released***. Pressing the joystick up and *holding it* should have no effect until released. Only then should the rate increase by one (assuming, of course, that it wasn't already at 15, in which case nothing should change).
2. Create and use these define and equate statements to make your code more readable:

```
.def BlinkFreq        = R20 ; holds current blink rate (1-15 Hz)
.equ BlinkFreqMin     = 1
```

```
.equ BlinkFreqMax     = 15
.equ InitialBlinkFreq = BlinkFreqMin
```

3. Since you'll be using PORTA.7 for the blinking LED and PORTC.3:0 for displaying the 4-bit blink rate, configure those five pins as **output pins** via the DDRA and DDRC registers. The remaining pins should be set as inputs. You'll need to update the `sbi` and `cbi` instructions as well. And be sure to **update any and all related code comments**.

4. In both outer delay loops, don't load R16 with 40, but rather with

$$16_{10} - BlinkFreq$$

(Remember, `BlinkFreq` is updated by the ISRs and holds the most current blink rate.) Loading R24 and R25 with `0xFFFF` instead of `0x4000` should give an ~1Hz blink rate when `BlinkFreq` has a value of 1. Your program must default to a ~1Hz blink rate at startup.

Question 1: Why do we use the equation in this section. (Can do a short answer for this question, but you should give more background in your report.)

5. **Test that the "BOOT" LED actually blinks at about 1 Hz** with a 50% duty cycle. **DO NOT GO ON UNTIL THE LED BLINKS AT ABOUT 1 HZ.**

Interrupt Code

Next, design and implement the **Interrupt Service Routines** (ISRs) that will be executed whenever the joystick is toggled up or down. The following **pseudocode** gives a general idea of how the ISRs should behave.

```
Initialize the interrupt system (explained in class and in your book)

mainLoop
   Blink PORTA.7 LED on and off once
      (according to the value in BlinkFreq)
   goto mainLoop

ISRJoystickUp
      (invoked when joystick is released after being pressed up)
   if BlinkFreq < BlinkFreqMax then
      increment BlinkFreq
      display new blink rate on the PORTC.3:0 LEDs
   return from interrupt

ISRJoystickDown
      (invoked when joystick is released after pressed down)
   if BlinkFreq > BlinkFreqMin then
      decrement BlinkFreq
```

```
    display new blink rate on the PORTC.3:0 LEDs
return from interrupt
```

As shown above, the `main loop` continuously blinks the PORTA.7 LED at a rate determined by the current value of `BlinkFreq`. The key is that **`BlinkFreq` is changed by the ISRs—the main program never changes `BlinkFreq`. All both ISRs do is change the value of BlinkFreq and update the four LEDs!**

Question 2: What are the five key ingredients for setting up and enabling interrupts with assembly code? (Include specific commands in your report.)

The joystick is a set of five buttons. The two that represent "up" and "down" are connected to ATmega128A pins PORTB.3 and PORTB.1, respectively. However, **PORTB pins cannot generate interrupts, but PORTD pins can**, so use PORTD.3 (for "up") and PORTD.1 (for "down") to actually generate the necessary interrupts when their inputs go **from low to high**. Of course, PORTD.1 and PORTD.3 are not internally connected to the joystick switches, so **you'll have to wire PORTB.1 to PORTD.1 and PORTB.3 to PORTD.3 using two external jumper wires**. This way, the joystick signals will cause the "up" and "down" ISRs to be invoked. If your Ready AVR board came with jumper wires attached, be sure to double check that these connections are correct (or remove all wires and just rewire yourself).

Question 3: Use your textbook, slides, or the web to state the three registers associated with every IO Port bank and what each one is used for.

Question 4: Show your wiring (picture is great) and briefly explain the concept of a "wired OR".

Assuming everything has been properly initialized, and your main program is happily blinking the "BOOT" LED, here's how the ISRs are used to change the blink rate:

1. The user presses and releases the up or down joystick button, causing a low-to-high transition on either pin PORTB.1 or PORTB.3 (which are connected externally to pins PORTD.1 or PORTD.3).
   Don't forget to enable pull-ups on the two PORTB pins!
2. The low-to-high transition on PORTD.1 or PORTD.3 generates an interrupt which in turn causes the ATmega128A to invoke the corresponding ISR which increments or decrements the `BlinkFreq` value and updates the 4-bit blink rate on the four LEDs.
3. The ISR ends and control returns to the main program, where the PORTA.7 LED begins blinking at the new rate. Simple, right?

The key to success in this lab is **understanding how to configure ports and interrupts** on the ATmega128A. Your instructor should have already presented some material to get you started, but your "go to" text for such information is the **AVR ATmega128A data sheet**. Specifically, you should refer to the chapters on "Interrupts," "External Interrupts," and "I/O Ports."

Report

This is a **one-week lab**. In this case, "everything" includes:

1. A live demonstration of your working hardware and code (in class),
2. Your PDF formal Lab Report lab report using the provided template, submitted via Canvas,

    Be sure you answer all **Questions** from the lab procedure.

3. Your code pushed to your GitHub repository.

As always, you'll be graded on the correctness, completeness, readability and organization of your report and your pushed code, so make sure everything looks professional! And, of course, have fun!

(And if you're lucky, you'll be able to complete this lab without too many interruptions…)