Starting torque = BG × power scale $\times \frac{60}{2\pi N_s}$ N-m

$= ____ \times ____ \times \frac{60}{2\pi N_s} = ____$ N-m

To find the maximum torque, draw the perpendicular to torque line from centre C to meet the circle at I and the vertical I I' represents maximum torque to scale.

Maximum torque = I I' = $____ \times ____ \times \frac{60}{2\pi \times N_s} = ____$ N-m

To find the maximum output, draw the perpendicular to output line from centre C to meet the circle at H and the vertical H H' represents maximum output to scale.

Maximum output = H H' = _____×_____= _____W

TABULATION FROM CIRCLE DIAGRAM

	Line current		Motor output		Torque		Rotor Cu Loss	Motor input		efficiency	slip	Power factor
	OP		PQ		PR		QR	PT		PQ/PT	QR/PR	PT/OP
	cm	A	cm	W	cm	N-m	cm	cm	W	%	%	