ELEC 5705 Assignment 3
5-Bit Asynchronous SAR Logic

Jesse Levine
101185127

April 2026

1 Objective

The objective of this assignment is to implement and verify the SAR logic for a 5-bit asynchronous SAR ADC operating at 500 MS/s over a 450 mV dynamic range. Assignment 2 focused on the comparator design. For Assignment 3, the emphasis is the control loop that performs the successive-approximation process and generates the next-bit decision timing without a fixed per-bit clock.

In this submission, the SAR logic is implemented and cross-checked using two open-source behavioral flows:

- an Icarus Verilog/SystemVerilog simulation of the asynchronous controller,
- an `ngspice` behavioral experiment that reproduces the same successive-approximation process inside the `ngspice` control language.

In both cases, the comparator is modeled behaviorally from the StrongARM latch transient results obtained in Assignment 2, rather than by reusing the original Cadence transistor-level implementation directly.

2 Behavioral Model

The ADC resolution is 5 bits, so the LSB is

$$\mathrm{LSB} = \frac{450\ \mathrm{mV}}{2^5} = 14.0625\ \mathrm{mV}. \tag{1}$$

The simulated architecture consists of:

- a 5-bit asynchronous SAR controller,
- an ideal 5-bit DAC,
- a StrongARM-inspired behavioral comparator,
- a sinusoidal input sampled at 500 MS/s.

The controller begins each conversion by asserting the MSB trial code. After each comparator decision becomes valid, the logic either keeps or clears the current bit and immediately applies the next lower trial bit. This emulates asynchronous operation, where progression depends on comparator resolve time rather than a global bit clock.

2.1 Comparator Model Derived from Assignment 2

The comparator model is based on the StrongARM latch results from Assignment 2:

- nominal decision time: approximately 124 ps,
- minimum decision time bound: 60 ps,
- maximum decision time bound: 250 ps,
- required minimum overdrive near 0.5 LSB.

The behavioral delay is made overdrive-dependent so that larger $|V_{in} - V_{DAC}|$ produces a faster comparator decision, while smaller overdrive increases resolve time. This captures the key timing behavior of the StrongARM latch relevant to asynchronous SAR sequencing.

3 Simulation Setup

The testbench uses a near full-scale sinusoidal input centered at 0.7 V, with a peak amplitude equal to $0.95 \times \frac{V_{FS}}{2}$. One conversion starts every 2 ns, corresponding to the required 500 MS/s rate.

The simulation produces:

- the internal logic timing waveforms,
- the output codes for 1024 samples,
- the conversion-time distribution,
- an FFT-based SNDR and ENOB calculation.

The Icarus flow models the SAR controller directly in SystemVerilog and drives it with a StrongARM-inspired comparator module. The `ngspice` flow does not use Verilog-A; instead, it implements the same 5-bit asynchronous approximation loop behaviorally in the `ngspice` control language using the same A2-derived comparator timing assumptions. The purpose of the second flow is to verify that the reported results are not an artifact of one simulator.

4 Results

Table 1 summarizes the key results.

Parameter	Result
LSB	14.062 mV
Average conversion time	477.9 ps
Worst-case conversion time	512.0 ps
SNDR	31.12 dB
ENOB	4.88 bits

Table 1: Summary of behavioral simulation results.

Figure 1 shows the asynchronous control behavior. The `start` pulse begins a conversion, the comparator model produces `comp_valid` when a decision is ready, and the SAR logic updates the

trial code immediately after each valid comparison. This confirms that the controller advances by comparator-ready events rather than by a fixed bit clock.



Figure 1: Asynchronous SAR logic timing with StrongARM-based comparator model.

Figure 2 compares the analog input with the DAC-equivalent output produced by the SAR code. The staircase output tracks the input with the expected 5-bit quantization levels across the 450 mV dynamic range.



Figure 2: Input waveform and quantized output code behavior.

Figure 3 shows the total conversion-time distribution. Because the comparator delay is overdrive-dependent, the conversion time is not constant from sample to sample. This spread is expected in an asynchronous SAR ADC and is consistent with StrongARM latch behavior.



Figure 3: Distribution of asynchronous conversion time.

Figure 4 shows the output spectrum used to calculate SNDR and ENOB. The measured ENOB is

$$\mathrm{ENOB} = \frac{\mathrm{SNDR} - 1.76}{6.02} = \frac{31.12 - 1.76}{6.02} \approx 4.88 \text{ bits.} \tag{2}$$

This is close to ideal 5-bit behavior for the present behavioral model.



Figure 4: Output spectrum used for SNDR and ENOB calculation.

5 Cross-Check with ngspice

To compare simulation frameworks, the same assignment was also implemented in a separate `ngspice` behavioral experiment. This version uses the same sinusoidal stimulus, the same DAC transfer function, and the same StrongARM-based comparator timing model from Assignment 2. Instead of instantiating a SystemVerilog SAR controller, the successive-approximation loop is executed in the `ngspice` control language and exported as waveform and code data.

The `ngspice` timing trace for the first conversion is shown in Fig. 5. The sequence of `start`, comparator-valid, trial code update, and end-of-conversion follows the same asynchronous logic behavior observed in the Icarus flow.



Figure 5: Behavioral asynchronous SAR timing reproduced in the `ngspice` experiment.

Table 2 compares the numerical results from both open-source methods.

Metric	Icarus Verilog	ngspice	Difference
Average conversion time	477.9 ps	478.6 ps	0.7 ps
Worst conversion time	512.0 ps	512.4 ps	0.4 ps
SNDR	31.12 dB	31.12 dB	−0.00 dB
ENOB	4.88 bits	4.88 bits	0.00 bits

Table 2: Comparison of the two open-source behavioral verification methods.

The agreement between the two methods is extremely close. The conversion-time difference is below 1 ps, and SNDR/ENOB are effectively identical. This indicates that the reported Assignment 3 behavior is determined by the SAR algorithm and the A2-derived StrongARM timing model rather than by a simulator-specific implementation detail.

6 Conclusion

A 5-bit asynchronous SAR controller was implemented and verified using two open-source behavioral simulation flows. The comparator behavior was derived from the StrongARM latch designed in Assignment 2, allowing the SAR logic to be evaluated with a realistic decision-time model. Both the Icarus Verilog and `ngspice` methods produced essentially the same result, showing correct bit-cycling, asynchronous next-bit timing, and near-ideal 5-bit dynamic performance. The final reported performance is approximately 31.12 dB SNDR and 4.88 bits ENOB, with sub-0.6 ns total conversion time.