



(a) The current contents of memory are shown:

Address	Data
19	25
20	23
21	2
22	4
23	15
24	50
25	22

The current contents of the ACC and IX are shown:

ACC	50
IX	20

Complete the table by writing the content of the ACC and the IX after each set of instructions has run.

	Instructions	ACC content	IX content
1	LDM #19 DEC ACC		
2	LDD 23 ADD 19		
3	LDI 25 INC ACC		
4	LDR #21 LDX 2		

[5]

