

East West University
Department of Computer Science and Engineering
Course Title: Computer Architecture, Course code: CSE360(3)
Fall 2021, Quiz 2, Total Mark: 10, Time: 25 Minutes, Set B
Instructor: Dr. Md. Nawab Yousuf Ali
Date: December 7, 2021

Answer all of the following questions.

Total Marks: 10

Name:

Id:

Sec:

Roll:

		Marks
Q1.	Calculate the memory access time when cycle time is 520ms and recovery is 108.25ms.	1
Q2.	Calculate the average time to read or write 100000 bits of data, when the data transfer rate is 10000 bps, and average access time is 50ns.	3
Q3.	A disk rotates at 7200 RPM. What is the rotational latency of the disk?	2
Q4.	A magnetic disk has 5 platters. Upper part of each platter has 1024 tracks and lower part has 512 tracks. Each track has 32 sectors and sector size is 2048 bytes. Calculate the size of the magnetic disk	4