




DR. B. C. ROY ENGINEERING COLLEGE, DURGAPUR

AN AUTONOMOUS INSTITUTE

AFFILIATED TO: MAULANA ABUL KALAM AZAD UNIVERSITY OF TECHNOLOGY, WEST
BENGAL

Week 3-4: Reliability Theory and Methods



PSM-104
M. Tech (EE)
EE B2025-27

Comprehensive Class Notes

Prepared by:
Kingsuk Majumdar

Department of Electrical Engineering


Academic Year 2025-26 (ODD Semester)

Contents

1	Module Overview & Weekly Structure	4
1.1	Weekly Learning Structure	4
2	Reliability Fundamentals	4
2.1	Basic Reliability Concepts	4
2.1.1	Reliability Definition	4
2.1.2	Failure Rate and Hazard Function	5
2.2	Time-Related Reliability Metrics	5
2.2.1	Mean Time To Failure (MTTF)	5
2.2.2	Mean Time To Repair (MTTR)	5
2.2.3	Mean Time Between Failures (MTBF)	5
2.3	Availability and Unavailability	6
2.3.1	Steady-State Availability	6
2.3.2	Forced Outage Rate (FOR)	6
3	Failure Analysis and Probability Theory	6
3.1	Probability Distributions in Reliability	7
3.1.1	Exponential Distribution	7
3.1.2	Weibull Distribution	7
3.1.3	Normal and Lognormal Distributions	7
3.2	Series and Parallel System Reliability	8
3.2.1	Series Systems	8
3.2.2	Parallel Systems	8
3.3	Statistical Data Analysis	9
3.3.1	Failure Data Collection	9
3.3.2	Parameter Estimation	9
4	Markov Process Applications	9
4.1	Markov Chain Fundamentals	10
4.1.1	State Space and Transition Probabilities	10
4.2	Two-State Markov Model	10
4.2.1	Model Formulation	10
4.2.2	Differential Equations	10
4.2.3	Steady-State Solution	10
4.2.4	Transient Solution	11
4.3	Multi-State Markov Models	11
4.3.1	Three-State Model with Maintenance	11
4.3.2	Multi-Component Systems	12
5	Recursive Reliability Techniques	12
5.1	Recursive Algorithm Fundamentals	13
5.1.1	Capacity Outage Probability Table (COPT)	13
5.2	Network Reduction Techniques	14
5.2.1	Series-Parallel Reduction	14
5.2.2	Decomposition Method	14

6	Frequency and Duration Analysis	14
6.1	Fundamental Frequency-Duration Concepts	15
6.1.1	Frequency of System State	15
6.1.2	Average Duration in State	15
6.2	Two-State System Frequency-Duration	15
6.3	Series System Frequency-Duration	16
6.4	Load Point Reliability Indices	16
6.4.1	Customer-Oriented Indices	16
7	Stochastic Interruption Prediction	17
7.1	Monte Carlo Simulation Fundamentals	17
7.1.1	Basic Monte Carlo Concept	17
7.2	Sequential Monte Carlo Simulation	17
7.2.1	State Duration Sampling	17
7.2.2	Sequential Simulation Algorithm	18
7.3	Non-Sequential Monte Carlo Simulation	19
7.3.1	State Sampling Method	19
7.4	Variance Reduction Techniques	19
7.4.1	Importance Sampling	19
7.4.2	Stratified Sampling	19
7.4.3	Confidence Intervals	19
8	Reliability Cost Analysis	20
8.1	Cost Components in Reliability Analysis	20
8.1.1	Utility Costs	20
8.1.2	Customer Interruption Costs	20
8.2	Economic Reliability Assessment	21
8.2.1	Expected Interruption Cost (EIC)	21
8.2.2	Interrupted Energy Assessment Rate (IEAR)	21
8.3	Cost-Benefit Analysis Framework	21
8.3.1	Reliability Investment Evaluation	21
8.4	Optimal Reliability Level	22
8.4.1	Marginal Analysis	22
9	Adequacy Assessment	23
9.1	Hierarchical Levels of Adequacy	23
9.1.1	Three-Level Hierarchy	23
9.2	Generation Adequacy Indices	23
9.2.1	Loss of Load Probability (LOLP)	23
9.2.2	Loss of Load Expectation (LOLE)	23
9.2.3	Expected Energy Not Served (EENS)	23
9.2.4	Expected Unserved Energy (EUE)	23
9.3	Composite System Adequacy	24
9.3.1	Load Point Indices	24
9.4	Adequacy Standards and Criteria	24
9.4.1	Deterministic Criteria	24
9.4.2	Probabilistic Criteria	25
9.5	Comprehensive Adequacy Assessment Case Study	25

10 Summary and Key Learning Outcomes	26
10.1 Fundamental Concepts Mastered	26
10.2 Practical Applications	26
10.3 Key Mathematical Relationships	27
10.4 Assessment and Evaluation	27
10.5 Next Module Preview	28
11 Practice Problems	28
11.1 Reliability Fundamentals	28
11.2 Probability Theory	28
11.3 Markov Process	29
11.4 Frequency-Duration Analysis	29
11.5 Adequacy Assessment	30
12 References	30



1 Module Overview & Weekly Structure

The main aim of Module 2 is to establish comprehensive understanding of reliability theory fundamentals, probabilistic analysis techniques, and computational methods essential for power system reliability assessment. This module provides the mathematical foundation required for analyzing generation, transmission, and distribution system reliability in subsequent modules.

Definition 1.1 (Module Philosophy): *Reliability theory represents the quantitative framework for evaluating power system performance, enabling engineers to predict system behavior under various operating conditions and make informed decisions about infrastructure investments and operational strategies.*

1.1 Weekly Learning Structure

Table 1: Reliability Theory Course Structure - Week 3-4

Lecture	Topic	Duration	Learning Activities
2.1	Reliability Fundamentals	50 min	Conceptual framework development
2.2	Failure Analysis & Probability Theory	50 min	Statistical data analysis
2.3	Markov Process Applications	50 min	State transition modeling
2.4	Recursive Reliability Techniques	50 min	Algorithm implementation
2.5	Frequency and Duration Analysis	50 min	Computational workshop
2.6	Stochastic Interruption Prediction	50 min	Monte Carlo concepts
2.7	Reliability Cost Analysis	50 min	Economic evaluation methods
2.8	Adequacy Assessment	50 min	Comprehensive problem solving

2 Reliability Fundamentals

Reliability engineering provides the quantitative foundation for evaluating power system performance under uncertain operating conditions. Understanding these fundamentals enables systematic assessment of system adequacy and security.

2.1 Basic Reliability Concepts

2.1.1 Reliability Definition

Definition 2.1 (System Reliability): *Reliability is defined as the probability that a system or component will perform its required function under stated conditions for a specified period of time. Mathematically:*

$$R(t) = P(\text{System operates successfully during } [0, t]) \quad (1)$$

The complementary concept is unreliability or failure probability:

$$F(t) = 1 - R(t) = P(\text{System fails during } [0, t]) \quad (2)$$

2.1.2 Failure Rate and Hazard Function

The failure rate, also known as hazard rate, characterizes the instantaneous rate of failure:

$$\lambda(t) = \frac{f(t)}{R(t)} = -\frac{d}{dt} \ln R(t) \quad (3)$$

where $f(t)$ is the probability density function of failure time.

Definition 2.2 (Bathtub Curve): *Component failure rates typically follow three distinct phases:*

- **Infant mortality period:** *Decreasing failure rate due to manufacturing defects*
- **Useful life period:** *Constant failure rate representing random failures*
- **Wear-out period:** *Increasing failure rate due to aging and degradation*

For power system components, the useful life period with constant failure rate is most commonly analyzed:

$$\lambda(t) = \lambda = \text{constant} \quad (4)$$

2.2 Time-Related Reliability Metrics

2.2.1 Mean Time To Failure (MTTF)

MTTF represents the expected time until first failure for non-repairable components:

$$\text{MTTF} = E[T] = \int_0^\infty t \cdot f(t) dt = \int_0^\infty R(t) dt \quad (5)$$

For constant failure rate:

$$\text{MTTF} = \frac{1}{\lambda} \quad (6)$$

2.2.2 Mean Time To Repair (MTTR)

MTTR characterizes the expected repair time for failed components:

$$\text{MTTR} = E[T_r] = \int_0^\infty t \cdot g(t) dt \quad (7)$$

where $g(t)$ is the repair time probability density function.

For exponential repair distribution with constant repair rate μ :

$$\text{MTTR} = \frac{1}{\mu} \quad (8)$$

2.2.3 Mean Time Between Failures (MTBF)

For repairable systems, MTBF characterizes the average time between consecutive failures:

$$\text{MTBF} = \text{MTTF} + \text{MTTR} \quad (9)$$

Example 2.1 (Reliability Metric Calculation):

Consider a transmission line with the following characteristics:

- Failure rate: $\lambda = 0.5$ failures/year

- Repair rate: $\mu = 365$ repairs/year (average repair time = 1 day)

Calculate reliability metrics:

$$\text{MTTF} = \frac{1}{0.5} = 2 \text{ years} \quad (10)$$

$$\text{MTTR} = \frac{1}{365} = 0.00274 \text{ years} \approx 1 \text{ day} \quad (11)$$

$$\text{MTBF} = 2 + 0.00274 \approx 2.003 \text{ years} \quad (12)$$

2.3 Availability and Unavailability

2.3.1 Steady-State Availability

Availability represents the probability that a system is operational at any random time:

$$A = \frac{\text{MTTF}}{\text{MTTF} + \text{MTTR}} = \frac{\mu}{\lambda + \mu} \quad (13)$$

Unavailability is the complementary measure:

$$U = 1 - A = \frac{\text{MTTR}}{\text{MTTF} + \text{MTTR}} = \frac{\lambda}{\lambda + \mu} \quad (14)$$

2.3.2 Forced Outage Rate (FOR)

In power system terminology, unavailability is often expressed as Forced Outage Rate:

$$\text{FOR} = U = \frac{\text{Hours on Forced Outage}}{\text{Hours on Forced Outage} + \text{Service Hours}} \quad (15)$$

Example 2.2 (Availability Calculation):

For the transmission line in the previous example:

$$A = \frac{2}{2 + 0.00274} = \frac{2}{2.00274} = 0.99863 \quad (16)$$

$$U = 1 - 0.99863 = 0.00137 \quad (17)$$

$$\text{FOR} = 0.137\% \quad (18)$$

This indicates the line is unavailable approximately 0.137% of the time, or about 5 days per year.

3 Failure Analysis and Probability Theory

Probability theory provides the mathematical framework for reliability analysis, enabling quantification of uncertainty in system performance and component behavior.

3.1 Probability Distributions in Reliability

3.1.1 Exponential Distribution

The exponential distribution is fundamental in reliability analysis, representing time-to-failure for constant failure rate components:

$$f(t) = \lambda e^{-\lambda t}, \quad t \geq 0 \quad (19)$$

Key properties:

$$R(t) = e^{-\lambda t} \quad (20)$$

$$F(t) = 1 - e^{-\lambda t} \quad (21)$$

$$E[T] = \frac{1}{\lambda} \quad (22)$$

$$\text{Var}(T) = \frac{1}{\lambda^2} \quad (23)$$

Definition 3.1 (Memoryless Property): *The exponential distribution exhibits the memoryless property:*

$$P(T > t + s \mid T > t) = P(T > s) \quad (24)$$

This implies that the probability of surviving additional time s is independent of how long the component has already operated.

3.1.2 Weibull Distribution

The Weibull distribution provides flexibility in modeling various failure rate patterns:

$$f(t) = \frac{\beta}{\eta} \left(\frac{t}{\eta} \right)^{\beta-1} e^{-(t/\eta)^\beta}, \quad t \geq 0 \quad (25)$$

where:

- β = shape parameter (controls failure rate behavior)
- η = scale parameter (characteristic life)

The failure rate function:

$$\lambda(t) = \frac{\beta}{\eta} \left(\frac{t}{\eta} \right)^{\beta-1} \quad (26)$$

Interpretation:

- $\beta < 1$: Decreasing failure rate (infant mortality)
- $\beta = 1$: Constant failure rate (exponential distribution)
- $\beta > 1$: Increasing failure rate (wear-out)

3.1.3 Normal and Lognormal Distributions

Normal Distribution:

$$f(t) = \frac{1}{\sigma\sqrt{2\pi}} e^{-(t-\mu)^2/(2\sigma^2)} \quad (27)$$

Used for modeling wear-out failures and maintenance times.

Lognormal Distribution:

$$f(t) = \frac{1}{t\sigma\sqrt{2\pi}} e^{-(\ln t - \mu)^2/(2\sigma^2)} \quad (28)$$

Appropriate for modeling repair times and component degradation processes.

3.2 Series and Parallel System Reliability

3.2.1 Series Systems

A series system fails if any component fails. For n independent components:

$$R_{\text{series}}(t) = \prod_{i=1}^n R_i(t) \quad (29)$$

For identical components with constant failure rate λ :

$$R_{\text{series}}(t) = e^{-n\lambda t} \quad (30)$$

The equivalent failure rate:

$$\lambda_{\text{series}} = \sum_{i=1}^n \lambda_i \quad (31)$$

Example 3.1 (Series System Analysis):

A transmission path consists of three line segments in series:

- Segment 1: $\lambda_1 = 0.3$ failures/year
- Segment 2: $\lambda_2 = 0.4$ failures/year
- Segment 3: $\lambda_3 = 0.5$ failures/year

System failure rate:

$$\lambda_{\text{system}} = 0.3 + 0.4 + 0.5 = 1.2 \text{ failures/year} \quad (32)$$

One-year reliability:

$$R_{\text{system}}(1) = e^{-1.2 \times 1} = 0.3012 = 30.12\% \quad (33)$$

3.2.2 Parallel Systems

A parallel system succeeds if at least one component operates. For n independent components:

$$R_{\text{parallel}}(t) = 1 - \prod_{i=1}^n [1 - R_i(t)] \quad (34)$$

For identical components:

$$R_{\text{parallel}}(t) = 1 - [1 - R(t)]^n \quad (35)$$

Example 3.2 (Parallel System Analysis):

Two parallel transmission lines with identical characteristics:

- Individual reliability: $R(t) = e^{-0.5t}$

System reliability:

$$R_{\text{system}}(t) = 1 - [1 - e^{-0.5t}]^2 \quad (36)$$

$$= 1 - 1 + 2e^{-0.5t} - e^{-t} \quad (37)$$

$$= 2e^{-0.5t} - e^{-t} \quad (38)$$

One-year reliability:

$$R_{\text{system}}(1) = 2e^{-0.5} - e^{-1} \quad (39)$$

$$= 2(0.6065) - 0.3679 \quad (40)$$

$$= 0.8451 = 84.51\% \quad (41)$$

Compared to single line reliability of 60.65%, parallel configuration significantly improves system reliability.

3.3 Statistical Data Analysis

3.3.1 Failure Data Collection

Reliability analysis requires systematic collection of failure and repair data:

Essential data elements:

- Component identification and type
- Failure date and time
- Failure mode and cause
- Repair initiation and completion times
- Weather conditions and operating state
- Maintenance history

3.3.2 Parameter Estimation

Maximum Likelihood Estimation for Exponential Distribution:

Given n observed failure times $t_1, t_2, \dots, t_n$:

$$\hat{\lambda} = \frac{n}{\sum_{i=1}^n t_i} \quad (42)$$

Confidence Intervals:

The $(1 - \alpha)$ confidence interval for λ :

$$\left[\frac{\chi_{\alpha/2, 2n}^2}{2T}, \frac{\chi_{1-\alpha/2, 2n}^2}{2T} \right] \quad (43)$$

where $T = \sum_{i=1}^n t_i$ is the total observation time.

4 Markov Process Applications

Markov processes provide powerful analytical tools for modeling repairable system behavior, enabling calculation of time-dependent and steady-state reliability metrics.

4.1 Markov Chain Fundamentals

4.1.1 State Space and Transition Probabilities

Definition 4.1 (Markov Property): A stochastic process $\{X(t), t \geq 0\}$ possesses the Markov property if:

$$P(X(t+s) = j \mid X(t) = i, X(u) = x(u), 0 \leq u < t) = P(X(t+s) = j \mid X(t) = i) \quad (44)$$

Future states depend only on the present state, not on past history.

Transition Rate Matrix:

For continuous-time Markov chains, transitions are characterized by rates:

$$\mathbf{Q} = \begin{bmatrix} -(\lambda_1 + \lambda_2 + \dots) & \lambda_1 & \lambda_2 & \dots \\ \mu_1 & -\mu_1 & 0 & \dots \\ \mu_2 & 0 & -\mu_2 & \dots \\ \vdots & \vdots & \vdots & \ddots \end{bmatrix} \quad (45)$$

where diagonal elements ensure row sums equal zero.

4.2 Two-State Markov Model

4.2.1 Model Formulation

The simplest repairable system model considers two states:

- State 1: Component operating (UP)
- State 0: Component failed (DOWN)

Transition rate matrix:

$$\mathbf{Q} = \begin{bmatrix} -\lambda & \lambda \\ \mu & -\mu \end{bmatrix} \quad (46)$$

4.2.2 Differential Equations

The Chapman-Kolmogorov equations govern state probabilities:

$$\frac{dP_1(t)}{dt} = -\lambda P_1(t) + \mu P_0(t) \quad (47)$$

$$\frac{dP_0(t)}{dt} = \lambda P_1(t) - \mu P_0(t) \quad (48)$$

with constraint: $P_1(t) + P_0(t) = 1$

4.2.3 Steady-State Solution

As $t \rightarrow \infty$, derivatives approach zero:

$$0 = -\lambda P_1 + \mu P_0 \quad (49)$$

$$1 = P_1 + P_0 \quad (50)$$

Solving yields:

$$P_1 = \frac{\mu}{\lambda + \mu} = A \quad (51)$$

$$P_0 = \frac{\lambda}{\lambda + \mu} = U \quad (52)$$

4.2.4 Transient Solution

For initial condition $P_1(0) = 1$ (component starts in operating state):

$$P_1(t) = \frac{\mu + \lambda e^{-(\lambda+\mu)t}}{\lambda + \mu} \quad (53)$$

$$P_0(t) = \frac{\lambda[1 - e^{-(\lambda+\mu)t}]}{\lambda + \mu} \quad (54)$$

Example 4.1 (Two-State Markov Analysis):

Consider a generator with:

- Failure rate: $\lambda = 0.1$ failures/year
- Repair rate: $\mu = 52$ repairs/year (1 week MTTR)

Steady-state availability:

$$A = \frac{52}{0.1 + 52} = \frac{52}{52.1} = 0.9981 \quad (55)$$

Transient availability at $t = 0.1$ years:

$$P_1(0.1) = \frac{52 + 0.1 \cdot e^{-52.1 \times 0.1}}{52.1} \quad (56)$$

$$= \frac{52 + 0.1 \times 0.0054}{52.1} \quad (57)$$

$$= 0.9981 \quad (58)$$

System reaches steady-state very quickly due to high repair rate.

4.3 Multi-State Markov Models

4.3.1 Three-State Model with Maintenance

Extended model including preventive maintenance:

- State 1: Operating
- State 0: Failed (corrective repair)
- State M: Maintenance (preventive)

Transition rate matrix:

$$\mathbf{Q} = \begin{bmatrix} -(\lambda + \lambda_m) & \lambda & \lambda_m \\ \mu & -\mu & 0 \\ \mu_m & 0 & -\mu_m \end{bmatrix} \quad (59)$$

where λ_m is maintenance initiation rate and μ_m is maintenance completion rate.

4.3.2 Multi-Component Systems

For n components, the state space includes 2^n possible combinations. State vector:

$$\mathbf{S} = [s_1, s_2, \dots, s_n] \quad (60)$$

where $s_i \in \{0, 1\}$ indicates component i status.

Transition from state $\mathbf{S}_i$ to $\mathbf{S}_j$ occurs at rate:

$$q_{ij} = \begin{cases} \lambda_k & \text{if component } k \text{ fails} \\ \mu_k & \text{if component } k \text{ is repaired} \\ 0 & \text{otherwise} \end{cases} \quad (61)$$

Example 4.2 (Two-Component System):

System with two identical components in parallel:

- Individual failure rate: $\lambda = 0.5$ failures/year
- Individual repair rate: $\mu = 50$ repairs/year

State space:

- State 2: Both components up
- State 1: One component up, one down
- State 0: Both components down

Transition rate matrix:

$$\mathbf{Q} = \begin{bmatrix} -1.0 & 1.0 & 0 \\ 50 & -50.5 & 0.5 \\ 0 & 100 & -100 \end{bmatrix} \quad (62)$$

Steady-state probabilities: Solving $\mathbf{PQ} = \mathbf{0}$ with $\sum P_i = 1$:

$$P_2 = 0.9802 \quad (63)$$

$$P_1 = 0.0196 \quad (64)$$

$$P_0 = 0.0002 \quad (65)$$

System availability (at least one component up):

$$A = P_2 + P_1 = 0.9998 = 99.98\% \quad (66)$$

5 Recursive Reliability Techniques

Recursive algorithms provide computationally efficient methods for calculating system reliability, particularly valuable for complex multi-component systems.

5.1 Recursive Algorithm Fundamentals

5.1.1 Capacity Outage Probability Table (COPT)

The COPT method evaluates generation system reliability by recursively building probability distributions of available capacity.

Definition 5.1 (Capacity State): Each capacity state represents a possible system capacity level with associated probability:

$$\text{State } i : (\text{Capacity}_i, \text{Probability}_i) \quad (67)$$

Recursive Algorithm:

Starting with an empty system, add units sequentially:

1. Initialize: $C_0 = 0$, $P_0 = 1.0$
2. For each unit k with capacity c_k and availability a_k :
 - Create new states by adding c_k to existing capacities
 - Update probabilities using availability and unavailability
3. Combine identical capacity states

Mathematical formulation:

$$P(\text{Capacity} = C) = \sum_{\text{all combinations}} \prod_{i \in \text{available}} a_i \prod_{j \in \text{unavailable}} (1 - a_j) \quad (68)$$

Example 5.1 (COPT Construction):

System with two generators:

- Unit 1: 100 MW, $a_1 = 0.95$
- Unit 2: 150 MW, $a_2 = 0.98$

Initial state:

Capacity (MW)	Probability
0	1.000

After adding Unit 1:

Capacity (MW)	Probability
0	$1.000 \times 0.05 = 0.050$
100	$1.000 \times 0.95 = 0.950$

After adding Unit 2:

Capacity (MW)	Probability
0	$0.050 \times 0.02 = 0.001$
100	$0.950 \times 0.02 = 0.019$
150	$0.050 \times 0.98 = 0.049$
250	$0.950 \times 0.98 = 0.931$

Final COPT (sorted by capacity):

Capacity (MW)	Individual Prob.	Cumulative Prob.
0	0.001	0.001
100	0.019	0.020
150	0.049	0.069
250	0.931	1.000

5.2 Network Reduction Techniques

5.2.1 Series-Parallel Reduction

Complex networks can often be simplified through recursive series-parallel reduction:

Algorithm Steps:

1. Identify series components and combine
2. Identify parallel components and combine
3. Repeat until network reduces to single equivalent element

Series combination:

$$\lambda_{eq} = \sum_{i=1}^n \lambda_i \quad (69)$$

$$\frac{1}{\mu_{eq}} = \sum_{i=1}^n \frac{\lambda_i}{\mu_i} / \lambda_{eq} \quad (70)$$

Parallel combination (for two components):

$$\lambda_{eq} = \frac{\lambda_1 \lambda_2}{\lambda_1 + \lambda_2 + \mu_1 + \mu_2} \quad (71)$$

$$\mu_{eq} = \mu_1 + \mu_2 \quad (72)$$

5.2.2 Decomposition Method

For non-series-parallel networks, decomposition technique applies:

$$R_{system} = P(\text{component } k \text{ works}) \cdot R_{system|k=1} + P(\text{component } k \text{ fails}) \cdot R_{system|k=0} \quad (73)$$

This recursively reduces network complexity by conditioning on key component states.

Example 5.2 (Bridge Network):

Five-component bridge configuration with identical components:

- Each component: $R = 0.9$

Using decomposition on bridge element:

$$R_{bridge} = 0.9 \times R_{bridge \text{ up}} + 0.1 \times R_{bridge \text{ down}} \quad (74)$$

$$R_{bridge \text{ up}} = 1 - (1 - 0.9^2)(1 - 0.9^2) = 0.9919 \quad (75)$$

$$R_{bridge \text{ down}} = 0.9^2 + 0.9^2 - 0.9^4 = 0.9639 \quad (76)$$

$$R_{bridge} = 0.9 \times 0.9919 + 0.1 \times 0.9639 = 0.9891 \quad (77)$$

6 Frequency and Duration Analysis

Frequency and duration methods extend reliability analysis beyond simple probability calculations, providing insights into dynamic system behavior and customer experience.

6.1 Fundamental Frequency-Duration Concepts

6.1.1 Frequency of System State

Definition 6.1 (State Frequency): The frequency of entering state i , denoted f_i , represents the expected number of transitions into state i per unit time:

$$f_i = \sum_{j \neq i} P_j \cdot q_{ji} \quad (78)$$

where P_j is steady-state probability of state j and q_{ji} is transition rate from j to i .

6.1.2 Average Duration in State

Definition 6.2 (State Duration): The average duration in state i , denoted D_i , is:

$$D_i = \frac{P_i}{f_i} \quad (79)$$

This represents the expected time spent in state i per visit.

6.2 Two-State System Frequency-Duration

For a repairable component with states UP (1) and DOWN (0):

Failure frequency:

$$f_0 = P_1 \cdot \lambda = \frac{\mu}{\lambda + \mu} \cdot \lambda = \frac{\lambda\mu}{\lambda + \mu} \quad (80)$$

Repair frequency:

$$f_1 = P_0 \cdot \mu = \frac{\lambda}{\lambda + \mu} \cdot \mu = \frac{\lambda\mu}{\lambda + \mu} \quad (81)$$

Note: $f_0 = f_1$ (frequency balance)

Average downtime per failure:

$$D_0 = \frac{P_0}{f_0} = \frac{1}{\mu} = \text{MTTR} \quad (82)$$

Average uptime per repair:

$$D_1 = \frac{P_1}{f_1} = \frac{1}{\lambda} = \text{MTTF} \quad (83)$$

Example 6.1 (Frequency-Duration Calculation):

Distribution feeder with:

- $\lambda = 2$ failures/year
- $\mu = 365$ repairs/year (24-hour repair time)

Calculate metrics:

$$\text{Availability} = \frac{365}{2 + 365} = 0.9945 \quad (84)$$

$$\text{Failure frequency} = \frac{2 \times 365}{367} = 1.989 \text{ failures/year} \quad (85)$$

$$\text{Average downtime} = \frac{1}{365} = 0.00274 \text{ years} = 24 \text{ hours} \quad (86)$$

$$\text{Average uptime} = \frac{1}{2} = 0.5 \text{ years} = 182.5 \text{ days} \quad (87)$$

6.3 Series System Frequency-Duration

For n components in series:

System failure frequency:

$$f_{\text{system}} = \sum_{i=1}^n f_i \prod_{j \neq i} A_j \quad (88)$$

For independent components with high availability ($A_j \approx 1$):

$$f_{\text{system}} \approx \sum_{i=1}^n f_i \quad (89)$$

Average system repair time:

$$\text{MTTR}_{\text{system}} = \frac{\sum_{i=1}^n f_i \cdot \text{MTTR}_i}{f_{\text{system}}} \quad (90)$$

Example 6.2 (Series System):

Three feeder sections in series:

Section	λ (fail/yr)	μ (rep/yr)	MTTR (hrs)
1	0.5	365	24
2	0.8	730	12
3	1.0	438	20

System failure frequency:

$$f_{\text{system}} = 0.5 + 0.8 + 1.0 = 2.3 \text{ failures/year} \quad (91)$$

Average system repair time:

$$\text{MTTR}_{\text{system}} = \frac{0.5 \times 24 + 0.8 \times 12 + 1.0 \times 20}{2.3} \quad (92)$$

$$= \frac{12 + 9.6 + 20}{2.3} = \frac{41.6}{2.3} = 18.1 \text{ hours} \quad (93)$$

System unavailability:

$$U_{\text{system}} = \frac{f_{\text{system}} \times \text{MTTR}_{\text{system}}}{8760} = \frac{2.3 \times 18.1}{8760} = 0.00475 \quad (94)$$

6.4 Load Point Reliability Indices

6.4.1 Customer-Oriented Indices

Average Failure Rate at Load Point i :

$$\lambda_i = \sum_{k \in \text{path to } i} \lambda_k \quad (95)$$

Average Outage Duration at Load Point i :

$$r_i = \frac{\sum_{k \in \text{path to } i} \lambda_k r_k}{\lambda_i} \quad (96)$$

Annual Unavailability at Load Point i :

$$U_i = \lambda_i \times r_i \quad (97)$$

Expected Energy Not Supplied:

$$\text{ENS}_i = U_i \times P_i \times 8760 \text{ (kWh/year)} \quad (98)$$

where P_i is average demand at load point i .

7 Stochastic Interruption Prediction

Stochastic simulation techniques, particularly Monte Carlo methods, provide powerful tools for analyzing complex systems where analytical solutions become intractable.

7.1 Monte Carlo Simulation Fundamentals

7.1.1 Basic Monte Carlo Concept

Definition 7.1 (Monte Carlo Method): *Monte Carlo simulation estimates system behavior by:*

1. *Generating random samples from probability distributions*
2. *Simulating system operation under sampled conditions*
3. *Accumulating statistics over many trials*
4. *Estimating reliability metrics from simulation results*

Advantages:

- Handles complex system configurations
- Incorporates detailed operational characteristics
- Provides distribution information beyond mean values
- Natural representation of time-dependent phenomena

Disadvantages:

- Computationally intensive for rare events
- Results subject to statistical uncertainty
- Requires many trials for accurate estimates

7.2 Sequential Monte Carlo Simulation

7.2.1 State Duration Sampling

For exponentially distributed times, sample component state durations:

Time to failure (operating state):

$$t_{\text{fail}} = -\frac{\ln(U)}{\lambda} \quad (99)$$

Time to repair (failed state):

$$t_{\text{repair}} = -\frac{\ln(U)}{\mu} \quad (100)$$

where $U \sim \text{Uniform}(0, 1)$ is a random number.

7.2.2 Sequential Simulation Algorithm

Basic procedure:

1. Initialize all components in operating state at $t = 0$
2. For each component, sample time to next state change
3. Advance simulation time to nearest event
4. Update component state and system configuration
5. Evaluate system adequacy at current time
6. Accumulate reliability statistics
7. Repeat until simulation time reaches target
8. Calculate reliability indices from accumulated data

Example 7.1 (Sequential Monte Carlo):

Simulate one-year operation of a two-component parallel system:

- Component A: $\lambda_A = 2$ fail/yr, $\mu_A = 365$ rep/yr
- Component B: $\lambda_B = 3$ fail/yr, $\mu_B = 730$ rep/yr

Sample simulation trial:

Time (days)	Event	System State	Status
0	Start	AB	UP
45	A fails	B	UP
46	A repairs	AB	UP
120	B fails	A	UP
121	B repairs	AB	UP
300	A fails	B	UP
301	A repairs	AB	UP

Trial results:

- System failures: 0
- System downtime: 0 hours
- Component A failures: 3
- Component B failures: 1

Repeat for thousands of trials to obtain reliable estimates.

7.3 Non-Sequential Monte Carlo Simulation

7.3.1 State Sampling Method

Non-sequential approach samples system states directly rather than simulating chronological events.

Algorithm:

1. For each time period (e.g., year):
2. Sample number of failures from Poisson distribution
3. Sample repair durations from appropriate distribution
4. Calculate annual downtime
5. Evaluate system adequacy
6. Accumulate statistics over many years

Annual failure count sampling:

$$N_{\text{failures}} \sim \text{Poisson}(\lambda) \quad (101)$$

Probability mass function:

$$P(N = k) = \frac{e^{-\lambda} \lambda^k}{k!} \quad (102)$$

7.4 Variance Reduction Techniques

7.4.1 Importance Sampling

Modify sampling distribution to emphasize critical events:

$$E[X] = \int x f(x) dx = \int x \frac{f(x)}{g(x)} g(x) dx \quad (103)$$

Sample from $g(x)$ (importance distribution) and weight results by $f(x)/g(x)$.

7.4.2 Stratified Sampling

Divide probability space into strata and sample proportionally from each:

$$E[X] = \sum_{i=1}^k w_i E[X_i] \quad (104)$$

where w_i is stratum weight and $E[X_i]$ is mean within stratum i .

7.4.3 Confidence Intervals

Estimate precision of Monte Carlo results:

$$\text{CI} = \bar{X} \pm z_{\alpha/2} \frac{s}{\sqrt{n}} \quad (105)$$

where:

- $\bar{X}$ = sample mean

- s = sample standard deviation
 - n = number of trials
 - $z_{\alpha/2}$ = standard normal critical value
- For 95% confidence: $z_{0.025} = 1.96$

8 Reliability Cost Analysis

Economic evaluation of reliability integrates technical performance with financial implications, enabling cost-effective decision-making in power system planning and operation.

8.1 Cost Components in Reliability Analysis

8.1.1 Utility Costs

Investment Costs:


- Capital expenditure for equipment
- Installation and commissioning costs
- System integration expenses

Operating Costs:

- Routine maintenance
- Preventive maintenance programs
- Spare parts inventory
- Personnel training

Failure Costs:

- Emergency repair expenses
- Equipment replacement costs
- Revenue loss during outages



8.1.2 Customer Interruption Costs

Definition 8.1 (Customer Damage Function): The customer damage function $C(d)$ represents the cost incurred by customers due to an interruption of duration d :

$$C(d) = C_0 + c_1d + c_2d^2 \quad (106)$$

where:

- C_0 = fixed cost per interruption
- c_1 = linear cost coefficient
- c_2 = quadratic cost coefficient

Sector-specific costs (typical values in USD/kW):

Customer Type	1-hour	4-hour
Residential	1.5	4.0
Commercial	8.0	25.0
Industrial	15.0	50.0

8.2 Economic Reliability Assessment

8.2.1 Expected Interruption Cost (EIC)

$$\text{EIC} = \sum_{i=1}^N f_i \cdot P_i \cdot C(d_i) \quad (107)$$

where:

- f_i = interruption frequency at load point i
- P_i = average load at point i
- $C(d_i)$ = customer damage function
- d_i = average interruption duration

8.2.2 Interrupted Energy Assessment Rate (IEAR)

$$\text{IEAR} = \frac{\text{Total Customer Interruption Cost}}{\text{Total Energy Not Supplied}} \quad (108)$$

Typical IEAR values range from 5-50 USD/kWh depending on customer mix.

8.3 Cost-Benefit Analysis Framework

8.3.1 Reliability Investment Evaluation

Compare costs and benefits of reliability improvements:

Net Present Value:

$$\text{NPV} = -C_0 + \sum_{t=1}^T \frac{B_t - C_t}{(1+r)^t} \quad (109)$$

where:

- C_0 = initial investment
- B_t = annual benefits (reduced interruption costs)
- C_t = annual costs (maintenance, operation)
- r = discount rate
- T = project lifetime

Benefit-Cost Ratio:

$$\text{BCR} = \frac{\sum_{t=1}^T \frac{B_t}{(1+r)^t}}{C_0 + \sum_{t=1}^T \frac{C_t}{(1+r)^t}} \quad (110)$$

Investment justified if $\text{BCR} > 1$.

Example 8.1 (Reliability Investment Analysis):

Utility considers installing automatic switching equipment:

- Initial cost: USD 500,000
- Annual maintenance: USD 20,000
- Project life: 20 years

- Discount rate: 7%
- Current SAIDI: 4.0 hours/customer-year
- Current SAIFI: 1.5 interruptions/customer-year
- Customers affected: 10,000
- Average load per customer: 2 kW
- IEAR: USD 10/kWh

Expected improvement:

- SAIDI reduction: 2.0 hours/customer-year
- SAIFI reduction: 0.5 interruptions/customer-year

Annual benefits:

$$\text{ENS reduction} = 10,000 \times 2 \times 2.0 = 40,000 \text{ kWh/year} \quad (111)$$

$$\text{Cost savings} = 40,000 \times 10 = \text{USD } 400,000/\text{year} \quad (112)$$

NPV calculation:

$$\text{PV of benefits} = 400,000 \times \frac{1 - (1.07)^{-20}}{0.07} = \text{USD } 4,238,000 \quad (113)$$

$$\text{PV of costs} = 20,000 \times \frac{1 - (1.07)^{-20}}{0.07} = \text{USD } 211,900 \quad (114)$$

$$\text{NPV} = -500,000 + 4,238,000 - 211,900 = \text{USD } 3,526,100 \quad (115)$$

BCR:

$$\text{BCR} = \frac{4,238,000}{500,000 + 211,900} = 5.95 \quad (116)$$

Investment is highly justified with positive NPV and $\text{BCR} > 1$.

8.4 Optimal Reliability Level

8.4.1 Marginal Analysis

Optimal reliability occurs where marginal cost equals marginal benefit:

$$\frac{dC_{\text{utility}}}{dR} = -\frac{dC_{\text{customer}}}{dR} \quad (117)$$

Total social cost:

$$C_{\text{total}}(R) = C_{\text{utility}}(R) + C_{\text{customer}}(R) \quad (118)$$

Minimize to find optimal reliability level R^* .

Definition 8.2 (Worth of Reliability): *The worth of reliability improvement is measured by the difference between customer interruption cost reduction and utility investment increase:*

$$W = \Delta C_{\text{customer}} - \Delta C_{\text{utility}} \quad (119)$$

Improvements with $W > 0$ provide net social benefit.

9 Adequacy Assessment

Adequacy assessment synthesizes reliability theory and methods into comprehensive evaluation frameworks for power system planning and operation.

9.1 Hierarchical Levels of Adequacy

9.1.1 Three-Level Hierarchy

Definition 9.1 (Adequacy Assessment Levels): *Power system adequacy assessment is organized hierarchically:*

- **HL-I (Generation):** *Generating capacity adequacy*
- **HL-II (Composite):** *Generation and transmission adequacy*
- **HL-III (Distribution):** *Complete system including distribution*

Each level requires progressively more detailed modeling and computational resources.

9.2 Generation Adequacy Indices

9.2.1 Loss of Load Probability (LOLP)

$$\text{LOLP} = \sum_{C < D} P(\text{Available Capacity} = C) \cdot P(\text{Demand} = D) \quad (120)$$

Typically expressed as days per year or percentage.

9.2.2 Loss of Load Expectation (LOLE)

$$\text{LOLE} = \sum_{t=1}^T \text{LOLP}_t \cdot \Delta t \quad (121)$$

Standard criterion: $\text{LOLE} \leq 0.1$ days/year (one day in ten years).

9.2.3 Expected Energy Not Served (EENS)

$$\text{EENS} = \sum_{t=1}^T P(\text{Capacity} < \text{Demand})_t \cdot E[\text{Deficit}]_t \quad (122)$$

9.2.4 Expected Unserved Energy (EUE)

$$\text{EUE} = \sum_i P(\text{outage}_i) \cdot \text{Energy deficit}_i \quad (123)$$

Example 9.1 (Generation Adequacy Assessment):

System with peak load 1000 MW and the following generation:

Unit	Capacity (MW)	FOR	Number
A	200	0.05	3
B	150	0.08	2
C	100	0.10	2

Total installed capacity:

$$C_{\text{total}} = 3(200) + 2(150) + 2(100) = 1100 \text{ MW} \quad (124)$$

Reserve margin:

$$\text{RM} = \frac{1100 - 1000}{1000} \times 100\% = 10\% \quad (125)$$

Using COPT method (simplified for illustration):

Capacity Out (MW)	Probability	Cumulative
0	0.7500	0.7500
100	0.1800	0.9300
200	0.0500	0.9800
>200	0.0200	1.0000

LOLP calculation:

$$\text{LOLP} = P(\text{Available} < 1000) \quad (126)$$

$$= P(\text{Outage} > 100) \quad (127)$$

$$= 0.0500 + 0.0200 = 0.0700 \quad (128)$$

LOLE:

$$\text{LOLE} = 0.0700 \times 365 = 25.55 \text{ days/year} \quad (129)$$

This exceeds the standard criterion of 0.1 days/year, indicating additional capacity is needed.

9.3 Composite System Adequacy

9.3.1 Load Point Indices

For composite generation-transmission systems, adequacy is evaluated at individual load points:

Probability of Load Curtailment (PLC):

$$\text{PLC}_i = \sum_{k \in \text{contingencies}} P_k \cdot I_k(i) \quad (130)$$

where $I_k(i) = 1$ if contingency k causes load curtailment at point i , 0 otherwise.

Expected Demand Not Supplied (EDNS):

$$\text{EDNS}_i = \sum_k P_k \cdot C_k(i) \quad (131)$$

where $C_k(i)$ is load curtailment at point i under contingency k .

9.4 Adequacy Standards and Criteria

9.4.1 Deterministic Criteria

N-1 Security Criterion: System must withstand loss of any single component without load curtailment.

N-2 Criterion: System must handle simultaneous loss of two components for critical facilities.

Reserve Margin Requirements:

- Generation reserve: 15-20%
- Transmission reserve: 10-15%
- Operating reserve: 3-5%

9.4.2 Probabilistic Criteria

Generation adequacy:

- $\text{LOLE} \leq 0.1$ days/year
- $\text{LOLP} \leq 0.0003$ (approximately)

Composite system adequacy:

- System $\text{LOLE} \leq 0.1$ days/year
- Load point $\text{EDNS} \leq 0.001$ MWh/MW-year

Distribution system adequacy:

- $\text{SAIFI} \leq 1.5$ interruptions/customer-year
- $\text{SAIDI} \leq 3.0$ hours/customer-year
- $\text{CAIDI} \leq 2.0$ hours/interruption

9.5 Comprehensive Adequacy Assessment Case Study

Example 9.2 (Integrated System Assessment):

Evaluate adequacy of a regional power system:

System characteristics:

- Peak load: 2500 MW
- Load factor: 0.65
- Installed generation: 3000 MW
- Number of customers: 500,000
- Average customer load: 3 kW

Generation data:

Type	Capacity (MW)	Units	FOR
Coal	400	3	0.06
Gas	250	4	0.04
Hydro	200	2	0.02

Assessment results (using COPT method):

- LOLE : 0.085 days/year (meets criterion)
- EENS : 850 MWh/year
- EUE : 0.34 MWh/MW-year

Distribution system data:

- Total interruptions/year: 750,000
- Total customer-hours interrupted: 1,500,000

Calculate distribution indices:

$$\text{SAIFI} = \frac{750,000}{500,000} = 1.5 \text{ interruptions/customer-year} \quad (132)$$

$$\text{SAIDI} = \frac{1,500,000}{500,000} = 3.0 \text{ hours/customer-year} \quad (133)$$

$$\text{CAIDI} = \frac{3.0}{1.5} = 2.0 \text{ hours/interruption} \quad (134)$$

Adequacy assessment summary:

- Generation adequacy: PASS (LOLE < 0.1 days/year)
- Reserve margin: 20% (adequate)
- Distribution reliability: MARGINAL (at criterion limits)
- Recommendation: Monitor distribution performance, consider targeted improvements

10 Summary and Key Learning Outcomes

10.1 Fundamental Concepts Mastered

Through comprehensive coverage of Module 2, students have developed thorough understanding of:

1. **Reliability fundamentals:** Core concepts including failure rates, repair rates, availability, and time-dependent reliability functions
2. **Probability theory applications:** Exponential, Weibull, and other distributions for modeling component behavior
3. **Markov process analysis:** State-space modeling, transition rate matrices, and steady-state/transient solutions
4. **Recursive techniques:** COPT method, network reduction, and decomposition algorithms
5. **Frequency-duration methods:** Dynamic reliability metrics characterizing system behavior over time
6. **Stochastic simulation:** Monte Carlo techniques for complex system analysis
7. **Economic evaluation:** Cost-benefit analysis and optimal reliability determination
8. **Adequacy assessment:** Comprehensive evaluation frameworks and industry standards

10.2 Practical Applications

The theoretical foundations enable practical applications in:

- **Component reliability analysis:** Evaluating individual equipment performance characteristics
- **System reliability evaluation:** Assessing complex multi-component system adequacy

- **Planning studies:** Supporting capacity expansion and infrastructure investment decisions
- **Operational planning:** Developing maintenance strategies and outage schedules
- **Economic justification:** Quantifying benefits of reliability improvements
- **Regulatory compliance:** Meeting industry standards and performance criteria
- **Customer impact assessment:** Evaluating service quality from customer perspective

10.3 Key Mathematical Relationships

Essential reliability equations:

$$\text{Availability: } A = \frac{\mu}{\lambda + \mu} \quad (135)$$

$$\text{MTTF: } \text{MTTF} = \frac{1}{\lambda} \quad (136)$$

$$\text{Series reliability: } R_s = \prod_{i=1}^n R_i \quad (137)$$

$$\text{Parallel reliability: } R_p = 1 - \prod_{i=1}^n (1 - R_i) \quad (138)$$

$$\text{Failure frequency: } f = \frac{\lambda\mu}{\lambda + \mu} \quad (139)$$

Definition 10.1 (Module Learning Progression): *The comprehensive reliability theory and methods developed in Module 2 provide the essential analytical foundation for Module 3 (Generation Planning and Reliability), Module 4 (Transmission Planning and Reliability), and Module 5 (Distribution Planning and Reliability), where these techniques will be applied to specific power system contexts.*

10.4 Assessment and Evaluation

Module 2 assessment components:

- **Class Discussion (15%):** Probability applications and reliability concepts
- **Programming Assignment (20%):** Markov chain reliability analysis implementation
- **Class Test (5%):** Comprehensive examination of reliability theory

Programming assignment deliverables:

1. Two-state Markov model implementation
2. Multi-state system reliability calculator
3. COPT generation algorithm
4. Monte Carlo simulation framework
5. Comprehensive documentation and test cases

10.5 Next Module Preview

Module 3 will build upon these reliability foundations to explore:

- **Generation planning methodologies:** Capacity expansion optimization strategies
- **Resource adequacy assessment:** Generation system reliability evaluation
- **Integrated resource planning:** Multi-criteria generation planning frameworks
- **Renewable integration:** Reliability implications of variable generation resources
- **Interconnected systems:** Multi-area generation reliability assessment
- **Emergency assistance protocols:** Coordinated system reliability management

11 Practice Problems

11.1 Reliability Fundamentals

Problem 11.1 (Basic Reliability Metrics):

A distribution transformer has the following characteristics:

- Failure rate: $\lambda = 0.02$ failures/year
- Average repair time: 48 hours

Calculate: (a) MTTF, (b) MTTR, (c) Availability, (d) Annual downtime hours

Solution:

$$(a) \text{ MTTF} = \frac{1}{0.02} = 50 \text{ years} \quad (140)$$

$$(b) \text{ MTTR} = \frac{48}{8760} = 0.00548 \text{ years} = 48 \text{ hours} \quad (141)$$

$$(c) \text{ Availability} = \frac{50}{50 + 0.00548} = 0.99989 = 99.989\% \quad (142)$$

$$(d) \text{ Downtime} = 0.02 \times 48 = 0.96 \text{ hours/year} \quad (143)$$

11.2 Probability Theory

Problem 11.2 (Series-Parallel Configuration):

A system consists of two parallel branches, each containing two components in series. All components are identical with reliability $R = 0.95$. Calculate system reliability.

Solution:

$$R_{\text{branch}} = 0.95 \times 0.95 = 0.9025 \quad (144)$$

$$R_{\text{system}} = 1 - (1 - 0.9025)^2 = 1 - 0.0095 = 0.9905 = 99.05\% \quad (145)$$

11.3 Markov Process

Problem 11.3 (Three-State System):

A component has three states: Operating (2), Derated (1), and Failed (0). Transition rates:

- $\lambda_{21} = 0.1$ /year (Operating to Derated)
- $\lambda_{20} = 0.05$ /year (Operating to Failed)
- $\lambda_{10} = 0.2$ /year (Derated to Failed)
- $\mu_{12} = 20$ /year (Derated to Operating)
- $\mu_{02} = 50$ /year (Failed to Operating)

Calculate steady-state probabilities.

Solution:

Transition rate matrix:

$$\mathbf{Q} = \begin{bmatrix} -50 & 0 & 50 \\ 0.2 & -20.2 & 20 \\ 0.05 & 0.1 & -0.15 \end{bmatrix} \quad (146)$$

Solving $\mathbf{PQ} = \mathbf{0}$ with $\sum P_i = 1$:

$$P_2 = 0.9926 \quad (147)$$

$$P_1 = 0.0050 \quad (148)$$

$$P_0 = 0.0024 \quad (149)$$

System availability (States 2 and 1): $A = 0.9976 = 99.76\%$

11.4 Frequency-Duration Analysis

Problem 11.4 (Load Point Reliability):

A radial feeder supplies a load point through three line sections with the following data:

Section	λ (fail/yr)	r (hrs)
1	0.6	10
2	0.8	8
3	1.2	6

Calculate load point reliability indices.

Solution:

$$\lambda_{LP} = 0.6 + 0.8 + 1.2 = 2.6 \text{ failures/year} \quad (150)$$

$$r_{LP} = \frac{0.6(10) + 0.8(8) + 1.2(6)}{2.6} = \frac{19.6}{2.6} = 7.54 \text{ hours} \quad (151)$$

$$U_{LP} = \frac{2.6 \times 7.54}{8760} = 0.00224 = 0.224\% \quad (152)$$

11.5 Adequacy Assessment

Problem 11.5 (Generation Adequacy):

A system has peak load 800 MW and the following generation units:

- 2×300 MW units, FOR = 0.05
- 3×200 MW units, FOR = 0.08

Estimate LOLP using simplified approach.

Solution:

Total capacity: $2(300) + 3(200) = 1200$ MW

Reserve margin: $\frac{1200-800}{800} = 0.50 = 50\%$

Major contingencies:

- Loss of one 300 MW unit: Available = 900 MW (adequate)
- Loss of two 300 MW units: Available = 600 MW (deficiency)

Probability of losing both 300 MW units:

$$P = 0.05 \times 0.05 = 0.0025 \quad (153)$$

LOLP ≈ 0.0025 (simplified estimate)

LOLE = $0.0025 \times 365 = 0.91$ days/year

This exceeds the 0.1 day/year criterion, indicating inadequate capacity.

12 References

1. R. Billinton and R. N. Allan, *Reliability Evaluation of Power Systems*, 2nd ed. New York: Springer, 1996.
2. R. Billinton and W. Li, *Reliability Assessment of Electric Power Systems Using Monte Carlo Methods*. New York: Plenum Press, 1994.
3. A. K. S. Jardine and A. H. C. Tsang, *Maintenance, Replacement, and Reliability: Theory and Applications*, 2nd ed. Boca Raton: CRC Press, 2013.
4. P. O'Connor and A. Kleyner, *Practical Reliability Engineering*, 5th ed. Chichester: Wiley, 2012.
5. IEEE Std 493-2007, *IEEE Recommended Practice for the Design of Reliable Industrial and Commercial Power Systems (Gold Book)*.
6. R. E. Brown, *Electric Power Distribution Reliability*, 2nd ed. Boca Raton: CRC Press, 2009.
7. L. Goel and R. Billinton, "Evaluation of interrupted energy assessment rates in distribution systems," *IEEE Trans. Power Delivery*, vol. 6, no. 4, pp. 1876-1882, Oct. 1991.
8. J. Endrenyi, *Reliability Modeling in Electric Power Systems*. Chichester: Wiley, 1978.
9. C. Singh and R. Billinton, *System Reliability Modelling and Evaluation*. London: Hutchinson, 1977.
10. M. Rausand and A. Høyland, *System Reliability Theory: Models, Statistical Methods, and Applications*, 2nd ed. Hoboken: Wiley, 2004.