

EN - Addendum instruction

Nice S.p.A.
Via Callalta, 1
31046 Oderzo TV Italy
info@niceforyou.com

www.niceforyou.com

Nice




The new MCA2R10 control unit (fig.1) replaces the MCA2 control unit (fig.2) and is compatible with the following motors: WG2024, WG3524, WG4024, WG5024, TOO3024, TOO4524 and XME2024 (including for very old models).

• Changes made to the MCA2R10 control unit terminals:

- **M1 output:** has been moved to the side of the **M2 output**
- **RADIO:** a radio receiver with capacity for 100 transmitters has been integrated and the programming key has been added
- **Transformer:** the transformer connection has been modified because the diode bridge is no longer present
- **MOTOR SELECTION:** 4 dip switches have been added for motor type selection
- **OVVIEW:** a connector for the IBT4N adapter has been added (connector for the Oview control unit programmer)
- P.P. **Terminal:** renamed "**Sbs**" = the function has not changed
- **S.C.A.:** renamed "**OGI**" = the function has not changed
- **OK Led:** under normal conditions, the LED light is green

⚠ **All programming procedures are different from the old control unit; it is therefore advisable to read the instruction manual before programming or to check the website www.niceforyou.com or read the QR Code on the control unit silver label.**

• Replacing the MCA2 control unit with the new MCA2R10 control unit:

3 A - Remove the 4 screws from the transformer support 	B - Remove the 2 wires that connect the bridge to the transformer 	C - Remove the wires and the diode bridge 	D - Close the transformer support box with the 4 screws 	E - Fix the control unit and connect the transformer cable (a) and the grounding cable (b) 
---	--	--	---	---

EN - Addendum instruction

Nice S.p.A.
Via Callalta, 1
31046 Oderzo TV Italy
info@niceforyou.com

www.niceforyou.com

Nice





The new MCA2R10 control unit (fig.1) replaces the MCA2 control unit (fig.2) and is compatible with the following motors: WG2024, WG3524, WG4024, WG5024, TOO3024, TOO4524 and XME2024 (including for very old models).

• Changes made to the MCA2R10 control unit terminals:

- **M1 output:** has been moved to the side of the **M2 output**
- **RADIO:** a radio receiver with capacity for 100 transmitters has been integrated and the programming key has been added
- **Transformer:** the transformer connection has been modified because the diode bridge is no longer present
- **MOTOR SELECTION:** 4 dip switches have been added for motor type selection
- **OVVIEW:** a connector for the IBT4N adapter has been added (connector for the Oview control unit programmer)
- P.P. **Terminal:** renamed "**Sbs**" = the function has not changed
- **S.C.A.:** renamed "**OGI**" = the function has not changed
- **OK Led:** under normal conditions, the LED light is green

⚠ **All programming procedures are different from the old control unit; it is therefore advisable to read the instruction manual before programming or to check the website www.niceforyou.com or read the QR Code on the control unit silver label.**

• Replacing the MCA2 control unit with the new MCA2R10 control unit:

3 A - Remove the 4 screws from the transformer support 	B - Remove the 2 wires that connect the bridge to the transformer 	C - Remove the wires and the diode bridge 	D - Close the transformer support box with the 4 screws 	E - Fix the control unit and connect the transformer cable (a) and the grounding cable (b) 
--	---	---	--	--