$${}_{0}^{1}T = \begin{bmatrix} \cos(q_{1}) & -\sin(q_{1}) & 0 & -L_{1}\sin(q_{1}) \\ \sin(q_{1}) & \cos(q_{1}) & 0 & L_{1}\cos(q_{1}) \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}$$

$$(2)$$

$${}_{1}^{2}T = \begin{bmatrix} \cos(q_{2}) & -\sin(q_{2}) & 0 & -L_{2}\sin(q_{2}) \\ \sin(q_{2}) & \cos(q_{2}) & 0 & L_{2}\cos(q_{2}) \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}$$
(3)

$${}_{2}^{3}T = \begin{bmatrix} \cos(q_{3}) & -\sin(q_{3}) & 0 & -L_{3}\sin(q_{3}) \\ \sin(q_{3}) & \cos(q_{3}) & 0 & L_{3}\cos(q_{3}) \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}$$

$$(4)$$

$$com_0 = \begin{bmatrix} 0 \\ l_0 \cos(q_0) \\ l_0 \sin(q_0) \\ 1 \end{bmatrix}$$
 (5)

$$com_1 = \begin{bmatrix} -l_1 \sin(q_1) \\ l_1 \cos(q_1) \\ 0 \\ 1 \end{bmatrix}$$

$$(6)$$

$$com_2 = \begin{bmatrix} -l_2 \sin(q_2) \\ l_2 \cos(q_2) \\ 0 \\ 1 \end{bmatrix}$$
 (7)

$$com_3 = \begin{bmatrix} -l_3 \sin(q_3) \\ l_3 \cos(q_3) \\ 0 \\ 1 \end{bmatrix}$$
 (8)

$$x_{ee} = \begin{bmatrix} 0\\0\\0\\1 \end{bmatrix} \tag{9}$$

$${}^{1}_{org}T = {}^{0}_{org}T {}^{1}_{0}T \tag{10}$$

$$_{org}^{2}T = _{org}^{0}T_{0}^{1}T_{1}^{2}T \tag{11}$$

$${}_{org}^{3}T = {}_{org}^{0}T {}_{0}^{1}T {}_{1}^{2}T {}_{2}^{3}T \tag{12}$$

$$Jacobian = \begin{bmatrix} \frac{\partial x}{\partial q_0} & \frac{\partial x}{\partial q_1} & \frac{\partial x}{\partial q_2} & \frac{\partial x}{\partial q_3} \\ \frac{\partial y}{\partial q_0} & \frac{\partial y}{\partial q_1} & \frac{\partial y}{\partial q_2} & \frac{\partial y}{\partial q_3} \\ \frac{\partial z}{\partial q_0} & \frac{\partial z}{\partial q_1} & \frac{\partial z}{\partial q_2} & \frac{\partial z}{\partial q_3} \\ \frac{\partial \omega_x}{\partial q_0} & \frac{\partial \omega_x}{\partial q_1} & \frac{\partial \omega_x}{\partial q_2} & \frac{\partial \omega_x}{\partial q_3} \\ \frac{\partial \omega_y}{\partial q_0} & \frac{\partial \omega_y}{\partial q_1} & \frac{\partial \omega_y}{\partial q_2} & \frac{\partial \omega_y}{\partial q_3} \end{bmatrix}$$

$$(13)$$

$$J_{1} = Jacobian\begin{pmatrix} 0 & -l_{1}\cos(q_{1}) & 0 & 0\\ -(L_{0}+l_{1}\cos(q_{1}))\sin(q_{0}) & -l_{1}\sin(q_{1})\cos(q_{0}) & 0 & 0\\ (L_{0}+l_{1}\cos(q_{1}))\cos(q_{0}) & -l_{1}\sin(q_{0})\sin(q_{1}) & 0 & 0\\ 0 & 1 & 0 & 0 & 0\\ 0 & 0 & 1 & 0 & 0 \end{pmatrix}$$

$$(15)$$

$$J_2 = Jacobian({}^{1}_{org}T com_2) \tag{16}$$

$$J_3 = Jacobian(^2_{org}T com_3) \tag{17}$$

$$J_{EE} = Jacobian(^{3}_{org}T x_{ee})$$

$$\tag{18}$$

$$x = \begin{bmatrix} \theta_x \\ \theta_y \\ \theta_z \\ p_x \\ p_y \\ p_z \\ \omega_x \\ \omega_y \\ \omega_z \\ \dot{p}_x \\ \dot{p}_y \\ \dot{p}_z \end{bmatrix}$$

$$(19)$$

$$f = \begin{bmatrix} f_{1x} \\ f_{1y} \\ f_{1z} \\ f_{2x} \\ f_{2y} \\ f_{2z} \end{bmatrix}$$
(20)

$$g = \begin{bmatrix} 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ gravity \end{bmatrix}$$
 (21)

```
0
                                                                                                                                                                                                                                                        0
                  0
                                                                0
                                                                                                               0
                                                                                                                                                           0
                                                                                                                                                                                                         0
                                                                                                                                                                                                                                                        0
                  0
                                                                0
                                                                                                               0
                                                                                                                                                           0
                                                                                                                                                                                                         0
                                                                                                                                                                                                                                                        0
                  0
                                                                0
                                                                                                               0
                                                                                                                                                           0
                                                                                                                                                                                                         0
                                                                                                                                                                                                                                                        0
                  0
                                                                0
                                                                                                               0
                                                                                                                                                           0
                                                                                                                                                                                                         0
                                                                                                                                                                                                                                                       0
                                                                0
                                                                                                                                                           0
                                                                                                                                                                                                         0
dt\left(i_{12}r1z - i_{13}r1y\right)
                                           dt \left( -i_{11}r1z + i_{13}r1x \right)
                                                                                            dt\left(i_{11}r1y - i_{12}r1x\right)
                                                                                                                                        dt\left(i_{12}r2z - i_{13}r2y\right)
                                                                                                                                                                                    dt \left( -i_{11}r2z + i_{13}r2x \right)
dt\left(i_{22}r1z - i_{23}r1y\right)
                                           dt \left( -i_{21}r1z + i_{23}r1x \right)
                                                                                            dt\left(i_{21}r1y - i_{22}r1x\right)
                                                                                                                                        dt\left(i_{22}r2z - i_{23}r2y\right)
                                                                                                                                                                                    dt\left(-i_{21}r2z+i_{23}r2x\right)
                                                                                                                                                                                                                                    dt \left( i_{21}r2y - i_2 \right)
                                           dt\left(-i_{31}r1z+i_{33}r1x\right)
                                                                                           dt\left(i_{31}r1y - i_{32}r1x\right)
                                                                                                                                        dt\left(i_{32}r2z - i_{33}r2y\right)
                                                                                                                                                                                    dt\left(-i_{31}r2z+i_{33}r2x\right)
dt\left(i_{32}r1z-i_{33}r1y\right)
                                                                                                                                                                                                                                    dt \left( i_{31}r2y - i_3 \right)
                 dt
                                                                                                                                                          dt
              \frac{\overline{mass}}{dt}
              \frac{\frac{dt}{mass}}{mass}
                                                             \frac{\overline{mass}}{dt}
                                                                                                           \frac{mass}{dt}
                                                                                                                                                        \frac{mass}{dt}
                                                                                                                                                                                                      \frac{\overline{mass}}{dt}
                                                                                                                                                                                                                                                    \frac{\overline{mass}}{dt}
                                                             \overline{mass}
                                                                                                           \overline{mass}
                                                                                                                                                        \overline{mass}
                                                                                                                                                                                                      \overline{mass}
                                                                                                                                                                                                                                                     \overline{mass}
                                                                                                                                                                                                                                         (23)
```

$$x(k+1) = \begin{bmatrix} dt\omega_{x}rz_{11} + dt\omega_{y}rz_{12} + dt\omega_{z}rz_{13} + \theta_{x} + \theta_{y} + \theta_{z} \\ dt\omega_{x}rz_{21} + dt\omega_{y}rz_{22} + dt\omega_{z}rz_{23} + \theta_{x} + \theta_{y} + \theta_{z} \\ dt\omega_{x}rz_{31} + dt\omega_{y}rz_{32} + dt\omega_{z}rz_{33} + \theta_{x} + \theta_{y} + \theta_{z} \\ dt\dot{p}_{x} + dt\dot{p}_{y} + dt\dot{p}_{z} + p_{x} + p_{y} + p_{z} \\ dt\dot{p}_{x} + dt\dot{p}_{y} + dt\dot{p}_{z} + p_{x} + p_{y} + p_{z} \\ dt\dot{p}_{x} + dt\dot{p}_{y} + dt\dot{p}_{z} + p_{x} + p_{y} + p_{z} \\ dtf_{1x}\left(i_{12}r1z - i_{13}r1y\right) + dtf_{1y}\left(-i_{11}r1z + i_{13}r1x\right) + dtf_{1z}\left(i_{11}r1y - i_{12}r1x\right) + dtf_{2x}\left(i_{12}r2z - i_{13}r2y\right) + dtf_{2y}\left(-i_{11}r2z + i_{21}r1x\right) + dtf_{1x}\left(i_{22}r1z - i_{23}r1y\right) + dtf_{1y}\left(-i_{21}r1z + i_{23}r1x\right) + dtf_{1z}\left(i_{21}r1y - i_{22}r1x\right) + dtf_{2x}\left(i_{22}r2z - i_{23}r2y\right) + dtf_{2y}\left(-i_{21}r2z + i_{21}r2x\right) + dtf_{2x}\left(i_{21}r2z - i_{23}r2y\right) + dtf_{2y}\left(-i_{21}r2z + i_{22}r2x\right) + dt$$

$$||f(k)||_R = \sqrt{f(k)_R} = \sqrt{f(k)^T R f(k)}$$
 (25)