

Microprocessors And Microcontrollers

Assignment 6- Week 6

TYPE OF QUESTION: MCQ

Number of questions: 15

Total mark: 15 X 1 = 15

QUESTION 1:

Correct Answer: c

Detailed Solution:

In register addressing mode one of the source or destination should be CPU register

QUESTION 2:

Correct Answer: c

Detailed Solution:

In immediate addressing mode source operand is constant. But the value should be less than FFFFH. So option C is correct

QUESTION 3:


Correct Answer: b

Detailed Solution:

The SFR (Special Function Register) can be accessed by their names or by their addresses
Register A address is 0E0H, so option B is correct

QUESTION 4:

Correct Answer: b



Detailed Solution:

```
CLR A           ;A=0
MOV R1,#60H     ;load pointer. R1=60H
MOV R7,#16      ;load counter, R7=16
AGAIN: MOV @R1,A ;clear RAM R1 points to
INC R1          ;increment R1 pointer
DJNZ R7,AGAIN   ;loop until counter=zero
```

option b is correct

QUESTION 5:

Correct Answer: a

Detailed Solution:

RAM locations from 20H-2FH are both bit addressable and byte addressable, so option a is correct

QUESTION 6:


Correct Answer: C

Detailed Solution:

QUESTION 7:

Correct Answer: d

Detailed Solution:



mov a,#54h ; a = 54H
swap a ; a = 45H
RL a ; Rotate left contents of A , so A = 8AH

QUESTION 8:

a)

Correct Answer: d

Detailed Solution:

MUL AB → Multiply A by B, put the low-order byte in A , High-order byte in B

Carry flag(CY) is always cleared after this operation.

QUESTION 9:

Correct Answer: b

Detailed Solution:

MOV A,#2Fh ; A = 2fh
MOV 0F0h,#12h ; B = 12h
DIV AB ; A = 02h, B = 0Bh
DIV AB ; A = 00h, B = 02h
option b is correct


QUESTION 10:

Correct Answer: a

Detailed Solution:

QUESTION 11:

Correct Answer: b



Detailed Solution:

Timer in mode2 acts as 8-bit auto reload, THx holds a value which is to be reloaded TLx each time it overflows.

QUESTION 12:

Correct Answer: b

Detailed Solution:

The DA instruction is provided to correct the aforementioned problem associated with BCD addition; it will add 6 to the lower nibble or higher nibble if need

QUESTION 13:

Correct Answer: c

Detailed Solution:

Decrement of data pointer is not allowed

QUESTION 14:

Correct Answer: C

Detailed Solution:

QUESTION 15:

Correct Answer: a

Detailed Solution:

XCHD:Exchanges bits 0-3 of the Accumulator with bits 0-3 of the Internal RAM address pointed to indirectly by R0. Bits 4-7 of each register are unaffected.



NPTEL Online Certification Courses
Indian Institute of Technology Kharagpur



*****END*****