

Homework — 2.1.4 Thinking Logically — ANSWER SHEET

Separate answer sheet / mark scheme — keep for marking.

Mark scheme

Part A (14 marks)

1. (a) [1] IF height $\geq$ 1.4 (accept $\geq$ 140 if cm stated). Must use $\geq$ for "at least".
- (b) [2] 1 mark TRUE: the rider is allowed on / admitted. 1 mark FALSE: the rider is refused / turned away.
2. [2] 1 mark condition: IF amount $\leq$ balance AND amount $\leq$ dailyLimit (accept equivalent variable names). 1 mark FALSE outcome: the withdrawal is **refused/declined** (insufficient funds or over the daily limit) and no cash is dispensed. Must use a logical operator (AND).
3. (a) [2] 1 mark: IF level $<$ 20 (THEN pump ON). 1 mark: IF level $>$ 80 (THEN pump OFF). (Accept $\leq$ / $\geq$ only if consistent with the wording; strict $<$ / $>$ match "below"/"above".)
- (b) [1] Three outcomes: turn ON, turn OFF, or leave unchanged.
4. [2] 1 mark: under spent $>$ 100, a customer who has spent exactly £100 does **not** qualify (100 is not greater than 100). 1 mark: rewrite as IF spent $\geq$ 100.
5. [4] Up to 4: First decision IF score $\geq$ 70 $\rightarrow$ TRUE: Distinction (1 for condition, 1 for outcome). Otherwise IF score $\geq$ 40 $\rightarrow$ TRUE: Pass; ELSE: Fail (1 for the second condition, 1 for both its branch outcomes). Recognise the conditions are **ordered/nested** so 70+ is tested first (credit within the marks above). Conditions must be exact Booleans with both branches stated and applied to this scenario; vague "if it's high" wording earns no condition mark.

Part B (6 marks)

6. [2] 1 mark: the tax step uses the **gross pay** figure produced by the previous step. 1 mark: it therefore depends on that output (a data dependency), so it cannot run until gross pay has been calculated — the order is fixed/sequential.
7. [2] 1 mark: a **primary key** is an attribute (or set of attributes) that **uniquely identifies** each record in a table. 1 mark: a **foreign key** is an attribute in one table that refers to the primary key of another table, linking the two (enforcing referential integrity).
8. [2] 00101101. 1 mark for correct binary value (101101), 1 mark for correct 8-bit form with leading zeros. (45 = 32 + 8 + 4 + 1.)

Total: 14 + 6 = 20 marks