

Mock Paper 1B — Computer Systems (H446/01)

Time allowed: 2 hours 30 minutes · Total: 140 marks · Answer all questions.

Instructions: Show all working on calculations and logic questions. Mark against the mark scheme at the end.

AO key: **AO1** = knowledge & understanding · **AO2** = application · **AO3** = analysis/evaluation/design.

A running mark tally is shown beside each question. The whole-paper total is verified at the very end.

Questions

Question 1 — Processors, the FDE cycle and performance (8 marks)

A games console uses a multi-core processor that supports pipelining.

1(a) During the **decode** and **execute** stages of the fetch–decode–execute cycle, state the role of the **Current Instruction Register (CIR)** and the **Arithmetic Logic Unit (ALU)**. [2] (AO1)

1(b) Explain how **pipelining** can increase the number of instructions completed per second, and state **one** situation in which the pipeline must be flushed. [3] (AO2)

1(c) The processor's clock speed is **3.2 GHz**. State what this value means and explain why simply increasing the clock speed is **not** always the best way to improve performance. [3] (AO2)

(Running total: 8)

Question 2 — Storage (7 marks)

2(a) Explain the difference between **primary** and **secondary** storage, giving **one** example of each. **[3]** (AO1)

2(b) A data centre must archive large volumes of data that are accessed only rarely but must be retained for many years at the lowest possible cost per gigabyte. State the **most appropriate** storage technology and justify your choice. **[2]** (AO2)

2(c) Explain why **virtual storage** (e.g. cloud storage) is described as a form of secondary storage, and state **one** disadvantage of relying on it. **[2]** (AO2)

(Running total: 15)

Question 3 — Operating systems, scheduling and interrupts (9 marks)

3(a) An operating system uses a **round robin** scheduling algorithm. Explain how round robin scheduling works and state **one** advantage it has over **first come first served (FCFS)**. **[4]** (AO2)

3(b) Describe how the operating system uses an **interrupt** to handle input arriving from a keyboard while a program is running, referring to the role of the **stack**. **[3]** (AO1)

3(c) State what is meant by a **device driver** and explain why an operating system needs them. **[2]** (AO1)

(Running total: 24)

Question 4 — Translators and the stages of compilation (9 marks)

4(a) Explain the role of an **assembler** and state why assembly language is described as a **low-level** language. **[3]** (AO1)

4(b) During compilation, **code generation** and **optimisation** are the final two stages. Describe what happens during each. **[4]** (AO1)

4(c) A team is developing in a language that is compiled to an intermediate form and run by a virtual machine. Explain **one** advantage and **one** disadvantage of this approach compared with compiling directly to native machine code. **[2]** (AO2)

(Running total: 33)

Question 5 — Software development methodologies (7 marks)

5(a) Describe the key stages of the **Waterfall** lifecycle and explain why it is described as a **sequential** model. **[4]** (AO1)

5(b) A company is developing safety-critical control software for a medical device, where requirements are fixed by regulation and full documentation is required. Justify why a **Waterfall** approach may be more suitable than **Rapid Application Development (RAD)** in this case. **[3]** (AO2)

(Running total: 40)

Question 6 — Object-oriented programming (9 marks)

A program models a school's vehicles. A base class `Vehicle` has the private attributes `registration` and `maxSpeed`, and a method `describe()`. A subclass `Minibus` adds the private attribute `seats`.

6(a) Explain what is meant by a **class** and an **object**, using this scenario to illustrate the difference. **[2]** (AO2)

6(b) Write the class definition for `Vehicle` in pseudocode (or a language of your choice). Include a constructor, private attributes, a public getter for `maxSpeed`, and a `describe()` method that returns a string containing both attributes. **[4]** (AO3)

6(c) Explain how **inheritance** would be used to define `Minibus`, and state **one** benefit of inheritance to the programmer. **[3]** (AO2)

(Running total: 49)

Question 7 — Assembly language and addressing modes (9 marks)

A processor uses a Little Man Computer (LMC)-style instruction set. Consider this program:

```

      INP
      STA a
      INP
      STA b
loop  LDA b
      BRZ end
      LDA total
      ADD a
      STA total
      LDA b
      SUB one
      STA b
      BRA loop
end   LDA total
      OUT
      HLT
a     DAT
b     DAT
total DAT 0
one   DAT 1
```

7(a) Trace the program for the inputs **4** then **3** (in that order). State the value output and describe in one sentence the arithmetic operation this program performs. **[5]** (AO3)

7(b) Explain the difference between **indirect** addressing and **direct** addressing, and state **one** advantage of indirect addressing. **[4]** (AO1)

(Running total: 58)

Question 8 — Compression, encryption and hashing (10 marks)

8(a) Describe how **dictionary-based compression** reduces file size. **[3]** (AO1)

8(b) Explain what is meant by a **hashing algorithm** and describe how hashing is used to store and check **passwords** securely. **[4]** (AO2)

8(c) A hash table of size 11 stores keys using the hash function $h(k) = k \text{ MOD } 11$. The keys **14**, **25** and **36** are inserted in that order. Show the index each key maps to, identify any **collision**, and state one method of resolving it. **[3]** (AO3)

(Running total: 68)

Question 9 — Databases and SQL (10 marks)

A library uses the following tables:

```
Member(MemberID, Surname, JoinDate)
Loan(LoanID, MemberID, ISBN, DueDate, Returned)
```

Returned holds the value 'Y' or 'N'.

9(a) Explain what is meant by **referential integrity** and describe **one** problem that could occur in the **Loan** table if it were not enforced. **[3]** (AO2)

9(b) Write an SQL statement to add a new member with **MemberID** **207**, surname **'Okafor'** and **JoinDate** **'2026-06-27'**. **[3]** (AO3)

9(c) Write an SQL statement that lists the **Surname** of each member together with the **ISBN** and **DueDate** of every loan they have **not yet returned**, sorted by **DueDate** (earliest first). **[4]** (AO3)

(Running total: 78)

Question 10 — Networks and TCP/IP (10 marks)

10(a) Explain the difference between a **MAC address** and an **IP address**, stating at which layer of the TCP/IP stack each is used. [3] (AO1)

10(b) Explain how **protocols** such as **TCP** ensure that data sent across a network arrives **reliably and in the correct order**. [4] (AO2)

10(c) A company hosts a website. Explain the difference between the **client-server** and **peer-to-peer** models, and justify why client-server is appropriate for the company's website. [3] (AO2)

(Running total: 88)

Question 11 — Number representation (12 marks)

11(a) Convert the denary number **−53** into **8-bit two's complement**. Show your working and verify your answer. **[3]** (AO2)

11(b) A floating-point number uses an **8-bit mantissa** and a **4-bit exponent**, both in two's complement, with an assumed binary point after the first mantissa bit. The stored value is:

mantissa = 0110 1000 exponent = 0010

Calculate the denary value this represents. Show your working, and state whether the number is **normalised**, justifying your answer. **[5]** (AO3)

11(c) Perform the binary addition 0101 1010 + 0011 0110 in 8 bits. State the 8-bit result and explain whether **overflow** has occurred if the values are interpreted as **signed two's complement**. **[4]** (AO3)

(Running total: 100)

Question 12 — Data structures (10 marks)

12(a) Explain what is meant by a **linked list**, and state **one** advantage and **one** disadvantage of a linked list compared with a static array. **[3]** (AO1)

12(b) A **binary search tree (BST)** is built by inserting the following keys in order: **50, 30, 70, 20, 40, 60**. Draw the resulting tree and state the order in which the keys are visited by an **in-order traversal**. **[4]** (AO3)

12(c) State the **Big O** time complexity of: (i) inserting a node at the head of a linked list; (ii) searching a **balanced** binary search tree of n nodes; (iii) accessing an element of an array by its index. **[3]** (AO1)

(Running total: 110)

Question 13 — Boolean algebra and logic circuits (11 marks)

13(a) Complete the truth table for the expression $Q = (\text{NOT } A) \text{ OR } (\text{NOT } B)$ and state the name of the single logic gate to which this expression is equivalent. **[4]** (AO3)

13(b) Using the laws of Boolean algebra, simplify the expression $Q = A \cdot (A + B) + A \cdot C + C$ to its simplest form. Show each step and name the law used. **[4]** (AO3)

13(c) A counter circuit uses a **D-type flip-flop**. State the purpose of a flip-flop in a sequential circuit, and explain why flip-flops are described as the building blocks of computer **memory/registers**. **[3]** (AO2)

(Running total: 121)

Question 14 — Networking and security (7 marks)

14(a) Explain what is meant by **encryption** when transmitting data across a network, and state why **HTTPS** is used in preference to **HTTP** for online banking. **[3]** (AO2)

14(b) Describe how a **proxy server** can improve both the **performance** and the **security** of a network. **[2]** (AO2)

14(c) Explain the difference between a **virus** and a **worm**. **[2]** (AO1)

(Running total: 128)

Question 15 — Extended response: legal, moral and ethical issues (12 marks)

A ride-hailing company deploys an **algorithm that automatically decides driver pay and which jobs each driver is offered**. The algorithm uses location data, the driver's acceptance history and customer ratings. Drivers are not told how the algorithm reaches its decisions, and a driver whose rating falls below a threshold is automatically deactivated without human review.

15 Discuss the **legal, ethical and social issues** raised by this automated decision-making system. In your answer you should consider the interests of the **drivers**, the **company** and **society**, and reach a justified conclusion about whether the system should be used in this form. **[12]** (AO3)

This image shows a blank sheet of white paper with horizontal blue ruling lines. The lines are evenly spaced and run across the width of the page. There are no margins, text, or other markings on the paper.

(Running total: 140)

\newpage