

Recap Checkpoint 6 — Full Year 12 Cumulative (Pre-Mock): 1.1, 1.3–1.5 + 2.1–2.3

Name: _____ Date: _____ Mark: _____ / 46

OCR H446 cumulative recap — mixes every topic taught so far. Show all working.

Questions

Q1 [3] (AO1). (1.1 — Processors) State **three** factors that affect the **performance** of a processor, and for each give a brief explanation of its effect.

.....

.....

.....

.....

Q2 [4] (AO2). (1.4 — Number bases) Show all working.

.....

.....

.....

.....

.....

.....

(a) Convert denary **181** to **8-bit binary**. [1]

.....

.....

(b) Convert **181** to **hexadecimal**. [2]

.....

.....

.....

(c) Convert binary **1010 0110** to denary. [1]

Q3 [4] (AO2). (1.4 — Two's complement) Using **8-bit two's complement**, calculate $-40 + 25$.

(a) Show 40 and 25 in 8-bit binary. [1]

(b) Form the two's complement representation of -40 . [1]

(c) Perform the addition and give the final **denary** result. [2]

Q4 [3] (AO2). (1.4 — Boolean algebra / floating point)

(a) State why floating-point numbers are **normalised**. [1]

(b) Simplify $A + A \cdot B$ and name the law used. [2]

Q5 [4] (AO1). (1.3 — Networks)

(a) Explain the difference between **circuit switching** and **packet switching**. [2]

(b) State **two** items of data added to a packet's **header**. [2]

Q6 [3] (AO1/AO3). (1.5 — Legal/ethical) Self-driving cars must sometimes "decide" how to act in an unavoidable collision.

Discuss **one ethical** issue this raises and identify **who** might be held **legally responsible** in a crash. [3]

.....

.....

.....

Q7 [4] (AO2). (2.1 / 2.2 — *Computational thinking + programming*)

.....

.....

.....

.....

.....

.....

(a) State the difference between a **procedure** and a **function**. [1]

.....

.....

.....

(b) Explain the difference between **passing a parameter by value** and **by reference**. [2]

.....

.....

.....

(c) State **one** advantage of using **local** variables over **global** variables. [1]

.....

.....

Q8 [5] (AO2). (2.3 — *Algorithm trace*) A list contains [7, 2, 9, 4, 1]. Carry out a **bubble sort**, showing the list after **each complete pass**. State how many passes are needed before the list is sorted, and give the **worst-case** time complexity of bubble sort.

.....

.....

.....

.....

.....

.....

.....

Q9 [4] (AO1/AO2). (2.3 — *Big O reasoning*)

.....

.....

.....

.....

.....

.....

(a) State the worst-case Big O of: insertion sort, merge sort, and a binary search. **[3]**

.....

.....

.....

.....

(b) Explain why merge sort is preferable to insertion sort for very large datasets, referencing growth rates. **[1]**

.....

.....

Q10 [6] (AO3). (2.3 — *Graphs, applied*) Using **Dijkstra's algorithm**, find the shortest **distance** and shortest **path** from **A** to **E** in the weighted, undirected graph below. Show a table of tentative distances and the order in which nodes are visited.

Edges (undirected, weighted):

A-B = 2, A-C = 5, B-C = 1, B-D = 7, C-D = 3, C-E = 8, D-E = 2

.....

.....

.....

.....

.....

.....

.....

This image shows a full page of white paper with horizontal dashed lines, typical of primary school writing paper. The lines are evenly spaced and run across the width of the page. There are no margins, text, or other markings on the paper.

[illegible]