

Mock Paper 1 — Computer Systems (H446/01)

Time allowed: 2 hours 30 minutes · Total: 140 marks · Answer all questions.

Instructions: Show all working on calculations and logic questions. Mark against the mark scheme at the end.

AO key: **AO1** = knowledge & understanding · **AO2** = application · **AO3** = analysis/evaluation/design.

Running mark tally is shown beside each question. Whole-paper total is verified at the very end.

Section A / questions

Question 1 — Processor architecture and the FDE cycle (8 marks)

A CPU uses the Von Neumann architecture and contains the registers PC, MAR, MDR, CIR and ACC.

1(a) State the role of the **Program Counter (PC)** and the **Memory Address Register (MAR)** during the fetch stage. **[3]** (AO1)

1(b) Describe **three** factors, other than clock speed, that affect the performance of a processor. **[3]** (AO1)

1(c) Explain **one** advantage of a Harvard architecture over a Von Neumann architecture for an embedded system. **[2]** (AO2)

(Running total: 8)

Question 2 — Storage devices (7 marks)

2(a) State **two** characteristics of a solid-state drive (SSD) that make it suitable for use in a laptop. [2] (AO1)

2(b) Compare optical storage with magnetic storage, giving **three** distinct points of comparison. [3] (AO2)

2(c) A digital camera stores photographs on a removable memory card. State the **type** of storage technology used and justify why it is appropriate. [2] (AO2)

(Running total: 15)

Question 3 — Operating systems (9 marks)

3(a) Explain how a **paging** memory-management technique allows a program larger than physical RAM to run. [4] (AO1)

3(b) Describe the purpose of an **interrupt** and explain the role of the **interrupt service routine (ISR)**. [3] (AO1)

3(c) State **one** difference between a **multi-tasking** and a **multi-user** operating system. **[2]** (AO1)

(Running total: 24)

Question 4 — Translators and the compilation process (9 marks)

4(a) State **three** differences between a **compiler** and an **interpreter**. **[3]** (AO1)

4(b) The compilation of source code passes through four stages: lexical analysis, syntax analysis, code generation and optimisation. Describe what happens during **lexical analysis** and **syntax analysis**. **[4]** (AO1)

4(c) Explain why a programmer might choose to distribute software as **bytecode** for a virtual machine rather than as native machine code. **[2]** (AO2)

(Running total: 33)

Question 5 — Software development methodologies (7 marks)

5(a) A start-up is building a mobile app where the client's requirements are expected to change frequently. Justify why an **Agile** methodology would be more suitable than the **Waterfall** model. **[4]** (AO2)

5(b) Describe **three** features of the **Extreme Programming (XP)** methodology. **[3]** (AO1)

(Running total: 40)

Question 6 — Object-oriented programming (9 marks)

A program models library members. A base class `Member` has the attributes `name` and `memberID`. A subclass `StudentMember` adds the attribute `course` and overrides the method `borrowLimit()`.

6(a) Explain what is meant by **inheritance** and **encapsulation**, using this scenario to illustrate each. **[3]** (AO2)

6(b) Write the class definition for `Member` in pseudocode (or a language of your choice), including a constructor and a `getDetails()` method. Use private attributes with public accessor methods. **[4]** (AO3)

6(c) Explain what is meant by **polymorphism** and give an example using `borrowLimit()`. **[2]** (AO2)

(Running total: 49)

Question 7 — Assembly language and addressing modes (8 marks)

A processor uses the Little Man Computer (LMC)-style instruction set. Consider this program:

```
      INP
      STA num
loop  LDA total
      ADD num
      STA total
      LDA num
      SUB one
      STA num
      BRP loop
      LDA total
      OUT
      HLT
num   DAT
total DAT 0
one   DAT 1
```

7(a) Trace the program for an input of **3**. State the final value output and explain in one sentence what the program computes. **[4]** (AO3)

7(b) Explain the difference between **immediate** and **direct (absolute)** addressing, and state **one** reason a processor also provides **indexed** addressing. **[4]** (AO1)

(Running total: 57)

Question 8 — Compression, encryption and hashing (10 marks)

8(a) Explain the difference between **lossy** and **lossless** compression, giving **one** suitable use case for each. **[3]** (AO1)

8(b) Describe how **run-length encoding (RLE)** compresses data and state **one** type of data for which it is ineffective. **[3]** (AO2)

8(c) Explain how **symmetric** encryption differs from **asymmetric** encryption, and describe how asymmetric encryption can be used to create a **digital signature**. **[4]** (AO2)

(Running total: 67)

Question 9 — Databases and SQL (10 marks)

A `Booking` table and a `Customer` table store data for a car-hire company:

```
Customer(CustomerID, Surname, City)
Booking(BookingID, CustomerID, CarReg, StartDate, Days)
```

9(a) State what is meant by a **primary key** and a **foreign key**, identifying one of each from the tables above. **[2]** (AO1)

9(b) Write an SQL statement to list the `Surname` and `City` of every customer who lives in `'Leeds'`, sorted alphabetically by `Surname`. **[3]** (AO3)

9(c) Write an SQL statement that lists the `Surname` of each customer together with the `CarReg` and `StartDate` of all their bookings of **5 or more** days. **[5]** (AO3)

(Running total: 77)

Question 10 — Networks and TCP/IP (10 marks)

10(a) Describe the role of each of the four layers of the **TCP/IP stack**. [3] (AO1)

10(b) Explain how the **Domain Name System (DNS)** resolves a URL into an IP address, referring to the hierarchy of DNS servers. [4] (AO2)

10(c) Explain the difference between **circuit switching** and **packet switching**, and state why packet switching is used on the internet. [3] (AO2)

(Running total: 87)

Question 11 — Number representation (12 marks)

11(a) Convert the denary number **-42** into **8-bit two's complement**. Show your working. [3] (AO2)

11(b) A floating-point number uses an **8-bit mantissa** and a **4-bit exponent**, both in two's complement, with an assumed binary point after the first mantissa bit. The stored value is:

mantissa = 0101 1000 exponent = 0011

Calculate the denary value this represents. Show your working, and state whether the number is **normalised**, justifying your answer. [5] (AO3)

11(c) Perform the binary addition 0110 1101 + 0101 0011 in 8 bits. State the 8-bit result and explain whether **overflow** has occurred if the values are interpreted as signed two's complement. [4] (AO3)

(Running total: 99)

Question 12 — Data structures (10 marks)

12(a) Explain the difference between a **stack** and a **queue**, and give **one** real use of each in a computer system. [3] (AO1)

12(b) A **circular queue** is implemented in an array of size 5 with **front** and **rear** pointers. Explain **why** a circular queue is preferred to a linear queue, and describe how the **rear** pointer wraps around. [4] (AO2)

12(c) State the **Big O** time complexity of: (i) adding an item to the top of a stack; (ii) a linear search of an unsorted list of n items; (iii) a binary search of a sorted list of n items. **[3]** (AO1)

(Running total: 109)

Question 13 — Boolean algebra and logic circuits (12 marks)

13(a) Complete the truth table for the expression $Q = (A \text{ AND NOT } B) \text{ OR } (\text{NOT } A \text{ AND } B)$, and state the name of the single logic gate that this expression is equivalent to. **[4]** (AO3)

13(b) Using the laws of Boolean algebra, simplify the expression $Q = A.B + A.(B + C) + B.(B + C)$ to its simplest form. Show each step and name the law used. **[4]** (AO3)

13(c) A safety system sounds an alarm ($Z = 1$) when **either** a door sensor **D** is open **and** the system is armed **A**, **or** when a panic button **P** is pressed (regardless of the other inputs). Write the Boolean expression for **Z** and draw the logic circuit using AND, OR and any other required gates. **[4]** (AO3)

(Running total: 121)

Question 14 — Networking and security (7 marks)

14(a) Explain the difference between a **LAN** and a **WAN**, referring to ownership and geographical scale. **[2]** (AO1)

14(b) Describe how a **firewall** using **packet filtering** helps protect a network. **[3]** (AO2)

14(c) Explain why a **star** network topology is more robust than a **bus** topology when a single connection fails. **[2]** (AO2)

(Running total: 128)

Question 15 — Extended response: legal, moral and ethical issues (12 marks)

A large retailer introduces an **AI-driven facial-recognition system** in its stores. The system scans the faces of every customer who enters, matches them against a database of known shoplifters, and alerts

security staff in real time. Camera footage and biometric data are stored on the company's servers for 12 months.

15 Discuss the **legal, ethical and privacy issues** raised by this system. In your answer you should consider the interests of customers, the retailer and society, and reach a justified conclusion about whether the system should be deployed. **[12]** (AO3)

This image shows a single sheet of white paper with horizontal blue ruling lines. The lines are evenly spaced and run across the width of the page. There are no margins, text, or other markings on the paper.

(Running total: 140)

\newpage