

Recap Checkpoint 3 — after 1.4 (Data Types, Data Structures & Boolean Algebra) — cumulative 1.1–1.4

Name: _____ Date: _ **Mark:** _____ / 35

OCR H446 cumulative recap — mixes every topic taught so far. Show all working.

Questions

Q1. State **one** difference between **CISC** and **RISC** processors, referring to the instruction set. **[2]** (AO1) — 1.1.2

Q2. Explain what is meant by **virtual memory** and give **one** drawback of relying on it heavily. **[3]** (AO1/AO2) — 1.2.1

Q3. Place the four stages of compilation in the correct order, and name the stage that **removes redundant instructions to make the object code more efficient**: *code generation, lexical analysis, optimisation, syntax analysis*. **[3]** (AO1) — 1.2.2

Q4. A company hashes stored passwords but **encrypts** the customer data it transmits. Explain, referring to the **key difference between hashing and encryption**, why each technique is appropriate for its purpose. **[3]** (AO2) — 1.3.1

Q5. Convert the denary number **89** into: (a) 8-bit binary **[1]** (AO2)

(b) hexadecimal **[2]** (AO2)

Show your working. **[3 total]** — 1.4.1

Q6. Using **8-bit two's complement**, calculate **39 – 52**. You must: (a) show 39 and 52 in 8-bit binary **[1]** (AO2)

(b) form the two's complement of 52 **[1]** (AO2)

(c) perform the addition and state the final **denary** result **[2]** (AO2)

[4 total] — 1.4.1

Q7. A floating point value is shown as **0.0001101 × 2⁴** (mantissa with the point after the sign bit, exponent in denary). (a) Normalise the mantissa and state the new exponent. **[2]** (AO2)

(b) Explain **why** numbers are normalised. **[1]** (AO1)

[3 total] — 1.4.1

Q8. Simplify the Boolean expression $A \cdot (\bar{A} + B)$ using Boolean identities. Show each step and name the identities used. **[3]** (AO2) — 1.4.3

Q9. Complete the truth table for $F = (A + B) \cdot \neg(A \cdot B)$ and state which single logic gate it is equivalent to. **[4]** (AO2) — 1.4.3

A	B	F
0	0	
0	1	
1	0	
1	1	

Q10. A **stack** (implemented in an array) is initially empty. The following operations are applied in order: push 8, push 3, push 5, pop, push 9, pop. (a) State the value returned by **each** pop operation. **[2]** (AO3)

(b) State the contents of the stack (bottom → top) after all operations, and explain why a stack is described as **LIFO**. **[2]** (AO3)

[4 total] — 1.4.2

Q11. The values **60, 40, 80, 30, 50, 70** are inserted, in that order, into an initially empty **binary search tree**. (a) Draw or describe the resulting tree. **[2]** (AO3)

