

Rajalakshmi Engineering College

Name: Mahathi B

Email: mahathi.b.2024.csd@rajalakshmi.edu.in

Roll no: 241701029

Phone: 9841411040

Branch: REC

Department: CSD

Batch: 2028

Degree: B.E - CSD

Scan to verify results



2024_28_IV_CSD_OOPS Using Java Lab

2028_REC_OOPS using Java_Week 1_Q6

Attempt : 1

Total Mark : 10

Marks Obtained : 10

Section 1 : Coding

1. Problem Statement

Joey is learning about bitwise operations and is working on a project that involves extracting specific bits from integers. He needs to write a program that takes an integer and the number of bits N as input and outputs the value of the lowest N bits of the integer.

Help Joey in his project to understand and visualize how bitwise operations work in practical scenarios.

Input Format

The first line of input consists of an integer X, representing the given integer.

The second line consists of an integer N, representing the number of bits to extract.

Output Format

The output displays "Result: " followed by an integer representing the value of the lowest N bits of the given integer.

Refer to the sample output for formatting specifications.

Sample Test Case

Input: 85

2

Output: Result: 1

Answer

```
// You are using Java
import java.util.Scanner;
class bit{
    public static void main(String args[]){
        Scanner sc = new Scanner(System.in);
        int x = sc.nextInt();
        int y = sc.nextInt();
        int a=(1<<y)-1;
        int b=(x&a);
        System.out.printf("Result: %d",b);
    }
}
```

Status : Correct

Marks : 10/10