



Cambridge International AS & A Level

CANDIDATE
NAMECENTRE
NUMBER

--	--	--	--	--

CANDIDATE
NUMBER

--	--	--	--

COMPUTER SCIENCE**9618/31**

Paper 3 Advanced Theory

October/November 2025**1 hour 30 minutes**

You must answer on the question paper.

No additional materials are needed.

INSTRUCTIONS

- Answer **all** questions.
- Use a black or dark blue pen.
- Write your name, centre number and candidate number in the boxes at the top of the page.
- Write your answer to each question in the space provided.
- Do **not** use an erasable pen or correction fluid.
- Do **not** write on any bar codes.
- You may use an HB pencil for any diagrams, graphs or rough working.
- Calculators must **not** be used in this paper.

INFORMATION

- The total mark for this paper is 75.
- The number of marks for each question or part question is shown in brackets [].
- No marks will be awarded for using brand names of software packages or hardware.

This document has **12** pages. Any blank pages are indicated.

- 1 The composite record data type, *ClubMember*, is defined in pseudocode as:

```

TYPE ClubMember
  DECLARE Code : INTEGER
  DECLARE LastName : STRING
  DECLARE FirstName : STRING
  DECLARE Telephone : STRING
  DECLARE JoinDate : DATE
  DECLARE Fees : REAL
  DECLARE FeesPaid : BOOLEAN
ENDTYPE

```

- (a) (i) Write the **pseudocode** statement to set up a variable for one record of the composite data type, *ClubMember*.

.....
 [1]

- (ii) Write the **pseudocode** statements to assign the following values to the variable set up in part (a)(i):

- 984632 to Code
- TRUE to FeesPaid

.....

 [2]

- (b) An enumerated data type, *Activity*, is required, so that a new field, *Choice*, can be added to the composite data type, *ClubMember*, to allow members to choose an activity.

- (i) Write the **pseudocode** statement for the type declaration of *Activity* to hold the names of the available activities:

Badminton, Football, Golf, Snooker, Swimming, Tennis.

.....

 [2]

- (ii) Write the **new pseudocode** statement required to update the declaration of *Choice* in the definition of *ClubMember*.

.....
 [1]



2 Numbers are stored in a computer system using binary floating-point representation with:

- 12 bits for the mantissa
- 4 bits for the exponent
- two's complement form for both the mantissa and the exponent.

(a) Write the normalised floating-point representation of the following positive binary number using this system.

0.00000001110101101

Mantissa

--	--	--	--	--	--	--	--	--	--	--	--

Exponent

--	--	--	--

[2]

(b) Calculate the normalised binary floating-point representation of -76.1875 in this system. Show your working.

Mantissa

--	--	--	--	--	--	--	--	--	--	--	--

Exponent

--	--	--	--

Working

.....

.....

.....

.....

.....

.....

.....

[4]



3 (a) Explain why protocols are essential for communication between computer systems.

.....

.....

.....

..... [2]

(b) POP3 is an email communication protocol.

Identify and describe **two** other communication protocols that are used when sending or receiving emails.

Protocol 1

Description

.....

.....

Protocol 2

Description

.....

..... [4]

(c) Describe **two** ways in which packet switching ensures a complete message is received when passing messages across a network.

1

.....

.....

.....

2

.....

.....

..... [4]



- 4 (a) A scheduling routine determines how processes are managed by the operating system.

Identify **two** scheduling routines.

- 1
2 [2]

- (b) Describe **two** ways in which the complexities of the computer hardware are hidden from the user.

- 1
.....
.....
.....
2
.....
.....
..... [4]

- 5 (a) Identify **two** items commonly found within a digital certificate.


- 1
.....
2
..... [2]

- (b) Explain why a digital certificate is required to validate a digital signature.

-
.....
.....
.....
.....
..... [3]



6 (a) The diagram shows a logic circuit.



Complete the truth table for the given logic circuit.
Show your working.

			Working space				
A	B	C	P	Q	R	S	Z
0	0	0					
0	0	1					
0	1	0					
0	1	1					
1	0	0					
1	0	1					
1	1	0					
1	1	1					

[3]



- (b) (i) Complete the Karnaugh map (K-map) for the Boolean expression:

$$\bar{A}.B.C + \bar{A}.B.\bar{C} + A.\bar{B}.C + A.B.\bar{C}$$

		BC			
A	0	00	01	11	10
	1				

[2]

- (ii) Draw loop(s) around appropriate group(s) in the K-map to produce an optimal sum-of-products.

[2]

- (iii) Write the Boolean expression from your answer to part **b(ii)** as a simplified sum-of-products. Do **not** carry out any further simplification.

..... [2]

- 7 (a) Identify **one** Artificial Intelligence (AI) algorithm to find the shortest distance between two points on a graph.

..... [1]

- (b) Describe Deep Learning.

..... [5]



- 8 (a) Outline the purpose of lexical analysis during the compilation of a program.

.....

.....

.....

..... [2]

- (b) Write the Reverse Polish Notation (RPN) for the given infix expression:

$$(2 - 6) * (13 + 7) / 5$$

.....

.....

.....

..... [2]

- (c) The RPN expression:

$$d \ a \ b \ + \ * \ c \ a \ - \ /$$

is to be evaluated, where:

$$a = 6, \ b = 12, \ c = 15 \ \text{and} \ d = 5.$$

Show the changing contents of the stack as the RPN expression is evaluated.

[4]



- 9 (a) A stack has been implemented using pseudocode to store a maximum of 100 string items using the global variables in the following table:

Identifier	Data type	Description	Initialisation value
Base	INTEGER	pointer for the bottom of the stack	0
Top	INTEGER	pointer for the top of the stack	-1
StackArray	STRING	1D array to implement the stack	[0:99]
Max	INTEGER	maximum number of items in the stack	100

The value of `Top` is incremented each time a data item is added to the stack and decremented every time a data item is removed.

- (i) Complete the **pseudocode** for the function to remove a data item from the stack.

```

FUNCTION Pop() .....
    DECLARE DataItem : STRING
    DataItem ← ""

    IF ..... THEN

        DataItem ← .....

        Top ← .....
    ELSE
        DataItem ← "You cannot remove data; the stack is empty"
    ENDIF

    .....
ENDFUNCTION
    
```

[5]

- (ii) Write the **pseudocode** to output the data item removed from the stack with an appropriate message.

.....

..... [1]



(b) A stack is used to implement recursion.

State the **three** essential features of recursion.

- 1
- 2
- 3
- [3]

10 Explain what is meant by **exception handling**.
Include an example of a possible cause of an exception in your answer.

Explanation

Example

[3]



- 11 The table shows assembly language instructions for a processor that has one register, the Accumulator (ACC).

Label	Instruction		Explanation
	Opcode	Operand	
	LDM	#n	Load the number n to ACC
	LDD	<address>	Load the contents of the location at the given address to the ACC
	LDI	<address>	The address to be used is at the given address. Load the contents of this second address to the ACC
	ADD	<address>	Add the contents of the given address to the ACC
	SUB	<address>	Subtract the contents of the given address from the ACC
	STO	<address>	Store the contents of the ACC at the given address
<label>:		<data>	Gives a symbolic address <label> to the memory location with contents <data>
# denotes a denary number, e.g. #123 <label> can be used in place of <address>			

- (a) Write **assembly language** code, using **only** the given instruction set to:

- store the denary value 100 as a named constant
- subtract the constant from the value contained in address 632
- store the result in variable `Answer`.

Show the initialisation of the constant and `Answer` in the table provided.

.....

.....

.....

.....

.....

.....

Label	Contents

[6]

- (b) The address 632 contains the value 45.

State the value of `Answer` after the code described in part (a) has executed.

..... [1]



Permission to reproduce items where third-party owned material protected by copyright is included has been sought and cleared where possible. Every reasonable effort has been made by the publisher (UCLES) to trace copyright holders, but if any items requiring clearance have unwittingly been included, the publisher will be pleased to make amends at the earliest possible opportunity.

To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced online in the Cambridge Assessment International Education Copyright Acknowledgements Booklet. This is produced for each series of examinations and is freely available to download at www.cambridgeinternational.org after the live examination series.

Cambridge Assessment International Education is part of Cambridge Assessment. Cambridge Assessment is the brand name of the University of Cambridge Local Examinations Syndicate (UCLES), which is a department of the University of Cambridge.

