SC20260B Pinout

Ball	Name	Function	Ball	Name	Function	Bal		Function	Ball	Name	Function
A1 A2	Vss PI6	GND PWM8.2	E6 E7	Vdd	Vdd PDR ON	J11 J12		Vss NC	N16 N17	Vss NC	Vss NC
A3	PI5	PWM8.1	E8	PDR_ON	RESERVED pull to GND			Vdd	N1/ P1	Vssa	Vssa
A4	PI4	DC D5	E9	Vdd	Vdd	J14		SPI5 SCK	P2	PH3	FMC SDNE0
A5	PB5	SPI3 MOSI	E10	PJ13		J15		LCD G6 PWM1.1	Р3	PH4	LCD G5 ADC3.15
A6	Vddldo	Vddldo	E11	Vdd	Vdd FMC D2	J16		Vss	P4	PH5	FMC SDNWE
A7 A8	Vcap PK5	Vcap LCD B6	E12 E13	PD1 PC8	FMC D3 SDMMC1 D0 UART5 R1	J17 S K1	Vss NRST	Vss NRST	P5 P6	PI15 PJ1	LCD G2
A9	PG10	DC D2	E14	PC9	SDMMC1 D1 UARTS CT			UART7 RX ADC3.8	P7	PF13	FMC A7
A10	PG9	DC VS	E15	PA8	DC XCLK	К3	PF7	UART7 TX ADC3.3	P8	PF14	FMC A8
A11	PD5	UART2 TX	E16		USBC P	K4	PF8	UART7 RTS PWM13.1 ADC3.7	P9	PE9	FMC D6
A12 A13	PD4 PC10	UART2 RTS SDMMC1 D2 UART3 TX	E17 F1	NC	USBC N NC	K5 K6	Vdd NC	Vdd NC	P10 P11	PE11 PB10	FMC D8 I2C2 SCL
A14	PA15	PWM2.1 UART4 RTS	F2	NC	NC NC	K7	Vss	Vss	P12	PB11	I2C2 SDA
A15	PI1	SPI2 SCK	F3	PI10	ETH RX ER	K8	Vss	Vss	P13	PH10	DC D1
A16	PIO	PWM5.4	F4	PI11		К9	Vss	Vss	P14	PH11	PWM5.2
A17 B1	Vss Vbat	Vss Vbat	F5 F6	Vdd NC	Vdd NC	K10 K11		Vss Vss	P15 P16	PD15 PD14	FMC D1 FMC D0
B2	Vss	Vss	F7	NC	NC NC	K12		NC NC	P17	Vdd	Vdd
В3	PI7	PWM8.3	F8	NC	NC	K13		Vdd	R1	PC2_C	ADC3.0
B4	PE1	FMC NBL1	F9	NC	NC	K14		SPI5 MISO PWM1.2	R2	PC3_C	ADC3.1
B5	PB6	QSPI NCS	F10 F11	NC NC	NC NC	K15		Vss	R3 R4	PA6	DC PIXCLK PWM13.1 ADC12.3
B6 B7	Vss PB4	Vss SPI3 MISO	F11 F12	NC NC	NC NC	K16		NC NC	R5	Vss PA7	Vss ETH CRS DV PWM14.1 ADC12.7
B8	PK4	LCD B5	F13	PC7	UART6 RX PWM3.2		Vdda	Vdda	R6	PB2	QSPI CLK
В9	PG11	ETH TX EN	F14	PC6	UART6 TX PWM3.1	_	PC0	ADC123.10	R7	PF12	FMC A6
B10	PJ15	LCD B3	F15	PG8	FMC SDCLK	L3	PF10	ADC3.6	R8	Vss	Vss
B11 B12	PD6 PD3	UART2 RX UART2 CTS	F16 F17	PG7 Vdd33usb	Vdd33usb	L4 L5	PF9 Vdd	UART7 CTS PWM14.1 ADC3.2 Vdd	R9 R10	PF15 PE12	FMC A9 FMC D9
B13	PC11	SDMMC1 D3 UART3 RX	G1	PF2	FMC A2	L6	NC	NC	R11	PE15	FMC D12
B14	PA14		G2	NC	NC	L7	Vss	Vss	R12	PJ5	LCD R6
B15	PI2	SPI2 MISO PWM8.4	G3	PF1	FMC A1	L8	Vss	Vss	R13	PH9	DC D0 PWM12.2
B16 B17	PH15 PH14	LCD G4 CAN1 RX UART4 RX	G4 G5	PF0 Vdd	FMC A0 Vdd	L9	Vss Vss	Vss Vss	R14 R15	PH12 PD11	DC D3 PWM5.3 QSPI IO0
C1	PC15	OSC32 OUT	G6	NC	NC	L10		Vss	R16	PD11	QSPI IO1
C2	PC14	OSC32 IN	G7	Vss	Vss	L12		NC	R17	PD13	QSPI IO3
C3	PE2	QSPI IO2	G8	Vss	Vss	L13		Vdd	T1	PA0_C	ADC12.0
C4 C5	PEO PB7	FMC NBL0 PWM4.2 APP	G9	Vss	Vss	L14 L15		SPI5 MOSI	T2	PA1_C	ADC12.1 DAC2
C6	PB3	SPI3 SCK PWM2.2	G10 G11	Vss Vss	Vss Vss	L16		Vss NC	T3 T4	PA5 PC4	ADC12.19 DAC2 ETH RXD0
C7	PK6	LCD B7	G12	NC	NC	L17		NC	T5	PB1	PWM3.4 ADC12.5
C8	PK3	LCD B4	G13	Vdd	Vdd	M1		Vref+	T6	PJ2	LCD R3
C9	PG12		G14	PG5	FMC BA1	M2		ETH MDC	T7	PF11	FMC SDNRAS
C10 C11	Vss PD7	Vss MOD	G15 G16	PG6 Vss	Vss	M3 M4		ADC123.12 ADC12.13	T8 T9	PG0 PE8	FMC A10 FMC D5
C12	PC12	SDMMC1 CK	G17	Vdd50usb	Vdd50usb	M5		Vdd	T10	PE13	FMC D10
C13	Vss	Vss	H1	PI12	LCD HSYNC	Me		NC	T11	PH6	PWM12.1
C14	PI3	SPI2 MOSI	H2	PI13	LCD VSYNC	M7		NC NC	T12	Vss	Vss
C15 C16	PA13 Vss	Vss	H3 H4	PI14 PF3	LCD CLK FMC A3	M8 M9		NC NC	T13	PH8 PB12	CAN2 RX UART5 RX
C17	Vddldo	Vddldo	H5	Vdd	Vdd	M1		NC	T15	. 512	USBH P
D1	PE5	DC D6 PWM15.1	Н6	NC	NC	M1:		NC	T16	PD10	FMC D15
D2		DC D4	H7	Vss	Vss	M1:		NC Vdd	T17	PD9	FMC D14
D3 D4	PE3 PB9	LDR I2C1 SDA PWM17.1	H8 H9	Vss Vss	Vss Vss	M1:		Vdd UART8 RX PWM1.3	U1 U2	Vss PA3	Vss PWM2.4 ADC12.15
D5	PB8	12C1 SCL PWM16.1	H10	Vss	Vss	M1		Vss	U3	PA4	DC HS ADC12.18 DAC1
D6	PG15	FMC SDNCAS	H11	Vss	Vss	M1	6 NC	NC	U4	PC5	ETH RXD1
D7	PK7	LCD DE	H12	NC	NC Vd d	M1		NC Vert	U5	PB0	PWM3.3 ADC12.9 UART4 CTS
D8 D9	PG14 PG13	ETH TXD1 ETH TXD0	H13 H14	Vdd PG4	Vdd FMC BA0	N1 N2		Vref- FMC SDCKE0	U6 U7	PJ3 PJ4	LCD R4 LCD R5
D10	PJ14		H15	PG3	THE DAG	N3		ETH MDIO	U8	PG1	FMC A11
D11	PJ12	LCD G3	H16	PG2	FMC A12	N4	PA1	ETH REF CLK	U9	PE7	FMC D4
D12	PD2	SDMMC1 CMD	H17	PK2	LCD G7	N5		PWM5.1 ADC1.16 WKUP	U10	PE14	FMC D11
D13 D14	PD0 PA10	FMC D2 UART1 RX	J1 J2	PH1 PH0	OSC OUT OSC IN	N6 N7		Vdd	U11 U12	Vcap Vddldo	Vcap Vddldo
D14	PA9	UART1 TX	J3	Vss	Vss	N8		Vdd	U13	PH7	I2C3 SCL
D16	PH13	CAN1 TX UART4 TX	J4	PF5	FMC A5	N9		FMC D7	U14	PB13	CAN2 TX UART5 TX
D17	Vcap	Vcap	J5	PF4	FMC A4	N10		Vdd	U15		USBH N
E1 E2	NC	NC	J6 J7	NC Vss	NC Vss	N11		Vdd Vdd	U16 U17	PD8	FMC D13
E3	PI9 PC13	TAMPER	J <i>7</i>	Vss Vss	Vss Vss	N12 N13		Vdd UART8 TX	017	Vss	Vss
E4	PI8		J9	Vss	Vss	N14					
E5	PE6	DC D7 PWM15.2	J10	Vss	Vss	N15	PJ6	LCD R7			