

# Safe Isolation Procedure – LV Installations

Category: Safety & Regulatory Code

This generic sequence is intended to support safe isolation of LV circuits. It does not replace your company procedure or national standards.

1. **PLAN:** Confirm the work scope, affected circuits and potential backfeeds. Ensure test equipment is available and proven.
2. **IDENTIFY:** Locate the correct circuit on the diagrams and in the distribution board. Cross-check labels, schedules and physical wiring.
3. **INFORM:** Notify affected users that the supply will be isolated and agree on the timing.
4. **ISOLATE:** Operate the isolating device (main switch, breaker, disconnect) to the OFF position.
5. **SECURE:** Apply an approved lock-off device and warning tag. Each person working should apply their own lock where required.
6. **PROVE TESTER:** Verify your voltage indicator on a known live source.
7. **TEST FOR ABSENCE OF VOLTAGE:** Test between all live conductors and between live and earth at the point of work.
8. **RE-PROVE TESTER:** Immediately re-check the indicator on a known live source.
9. **WORK:** Proceed with the task, maintaining control of keys and access.
10. **RESTORE:** When work is complete, remove tools, remove locks/tags in line with procedure, and restore supply. Inform users.

Always use company-specific forms or checklists if provided.