

A	B	C		S ₆	S ₅	S ₄	S ₃	S ₂	S ₁	S ₀	Display
0	0	0		0	1	1	1	0	0	1	C
0	0	1		1	1	1	0	1	0	0	H
0	1	0		1	1	1	0	1	1	1	A
0	1	1		1	0	1	0	1	0	0	N
1	0	0		1	1	0	1	1	1	1	G
1	0	1		1	0	1	1	0	1	1	Z
1	1	0		1	1	1	1	0	0	1	E
1	1	1		0	0	0	0	0	0	0	

S_6

	BC'		BC	B'C		B'C'
A	1		0	1	1	1
A'	1		1	1	0	0

$$S_6 = BC' + A'C + AB'$$

S_5

	BC'		BC		B'C		B'C'	
A	1		0		0		1	
A'	1		0		1		1	

$$\begin{aligned} S_5 &= BC' + B'C' + A'B' \\ &= C' + A'B' \end{aligned}$$

S_4

	BC'		BC		B'C		B'C'	
A	1		0		1		0	
A'	1		1		1		1	

$$S_4 = BC' + B'C + A'$$

S_3

	BC'	BC	B'C	B'C'
A	1	0	1	1
A'	0	0	0	1

$$S_3 = AC' + AB' + B'C'$$

S_2

	BC'	BC	B'C	B'C'
A	0	0	0	1
A'	1	1	1	0

$$S_2 = AB'C' + A'B + A'C$$

S_1

	BC'	BC	B'C	B'C'
A	0	0	1	1
A'	1	0	0	0

$$S_1 = A'BC' + AB'$$

S_0

	BC'		BC	B'C		B'C'	
A	1		0	1		1	
A'	1		0	0		1	

$$\begin{aligned} S_0 &= BC' + B'C' + AB' \\ &= C' + AB' \end{aligned}$$