Start	Step 1	Step 2	Step 3	Step 4	Step 5	Step 6	Step 7	Step 8	Step 9	Step 10	Step 11
_	$E \rightarrow T E_{prime}$	$T \rightarrow F T_prime$	$F \rightarrow IDENTIFIER$	$T_{prime} \rightarrow \varepsilon$	E_prime → PLUS T E_prime	$T \to F T_prime$	$F \rightarrow IDENTIFIER$	T_prime → STAR F T_prime	$F \rightarrow IDENTIFIER$	$T_{prime} \rightarrow \epsilon$	E_prime $\rightarrow \varepsilon$
E	T E_prime	F T_prime E_prime	IDENTIFIER T_prime E_prime	IDENTIFIER E_prime	IDENTIFIER PLUS T E_prime	IDENTIFIER PLUS F T_prime E_prime	IDENTIFIER PLUS IDENTIFIER T_prime E_prime	IDENTIFIER PLUS IDENTIFIER STAR F T_prime E_prime	IDENTIFIER PLUS IDENTIFIER STAR IDENTIFIER T_prime E_prime	IDENTIFIER PLUS IDENTIFIER STAR IDENTIFIER E_prime	IDENTIFIER PLUS IDENTIFIER STAR IDENTIFIER