

OPERATIONAL PHILOSOPHY – SERVICE LONG MARCH TYRE

Single Line Diagram (SLD)

- According to SLD, operational philosophy (OP) is given below.

Operational Philosophy

Operational philosophy of 02 x JMS620-11kV is given below:

Grid Parallel Operation & Island/Load Sharing:

- 02 x JMS620 can operate in grid parallel mode. INCOM-1 is considered as Grid VCB.
- In case of grid interruption or failure, 02 x JMS620 will do transition of mode and operate in island/load sharing mode.
- Upon restoration of grid, 02 x JMS620 will again switch to grid parallel mode.

Bus-coupler Control & Synchronization

Bus-coupler control and synchronization is included details as given below.

Generally:

- BC-1 will remain normally closed.

When BC-1 is opened in fault condition:

- Grid VCB remains closed & keep feeding bus-1
- 2x620 remain in operation on bus-2

When BC-1 fault condition is removed:

- Operator generate command for BC-1 synchronization
- MCP automatically synchronize BC-1 (Bus-1 & Bus-2)
- 2x620 shifts to Grid Parallel mode.