

Exp No: 4**7 SEGMENT DISPLAY USING AT89C51 USING PROTEUS****AIM:**

To write an assembly language program for 7 Segment Display Using AT89C51 using Keil and Proteus

PROGRAM:

```
ORG 000H
UP:MOV P2,#0C0H
ACALL DELAY
MOV P2,#0F9H
ACALL DELAY
MOV P2,#0A4H
ACALL DELAY
MOV P2,#0B0H
ACALL DELAY
MOV P2,#99H
ACALL DELAY
MOV P2,#92H
ACALL DELAY
MOV P2,#82H
ACALL DELAY
MOV P2,#0F8H
ACALL DELAY
MOV P2, #80H
ACALL DELAY
MOV P2,#90H
ACALL DELAY

DELAY: MOV R5,#10
H1:MOV R4,#180
H2:MOV R3,#255
H3:DJNZ R3,H3
DJNZ R4,H2
DJNZ R5,H1
RET
END
```

