diskette, and pray. For those who want to try their hands at being a consultant, here's what you need to know to save your files. Disk Doctor will ask you whether you want to recover files by sector or by group. By making a print-out of DDT, and studying it carefully, the necessary numbers can be decided. (Refer to *"Disk Snooping,"* in the Dec/Jan issue, page 50, for a detailed explanation.)

About the only thing Disk Doctor doesn't do is save the file you've got hovering in memory when you can't write it to the diskette because of a bad sector. So far, I don't know of anything that will. *(See editor's note.)* Following, is a brief summary of the program's features:

Ward A	Assign bad groups to Morgue
Ward B	Transplant sectors or groups to recovery disk
Ward C	Recover damaged disk by copying to another
Ward D	Recover erased files
Ward E	Directory of recoverable erased files
Exit X	Exit to system

That's Disk Doctor. If you need a program with all these capabilities, it's well worth the price. If all you need is a straightforward recovery program, pass it up. You'll save some money.

Cheryl Peterson

See "Save Your ASCII" in the April/May issue of the Companion for do-it-yourself instructions on recovering WordStar memory contents. There is also a software product called IMAGE put out by Tanstaafl (6813 Kettering Circle, Fair Oaks, CA 95628) that performs WordStar memory recall automatically.—bb

Osbaud; a Baud Rate Generator

With my Osborne 1, I can up and down-load files from mainframes at high speed, drive a $10,000 high-speed band printer at 19200 baud, communicate with a 110 baud ASR33 Teletype machine, and connect to a Televideo 920C CRT running at 9600 baud for certain experimental applications (including 80-column display).

How! There's no magic involved—I simply installed Advent Products $59.95 "Osbaud" baud rate generator and instantly had 16 dip switch selectable baud rates.

Osbaud is a small auxilliary circuit board that is soldered to the main logic board in the area behind the serial port. The 16 different rates are selected via dip switches through a small slot cut in the venting grill. A small metallic self-adhesive chart fastens to the keyboard and indicates the various settings.

Installation of Osbaud is not difficult but it does require some technical competency. The instructions and photos that accompany Osbaud are excellent and were written assuming first-time access to Ozzie's insides. Advent even provides the difficult to find .050" allen wrench that removes the brightness and control knobs—a thoughtful touch. You will need a Phillips screwdriver, Xacto knife (to cut across a circuit trace), and a low wattage soldering iron. I suggest having a dealer perform the installation if you're unsure what end of the soldering iron gets hot.

Osbaud is soldered to pins 4 and 12 of the 6850 UART, pin 7 of the 74LS32, and pin 7 of the 74LS04. Caution must be exercised here: Osbaud's posts are not mechanically connected to the IC leads. An improperly soldered joint may break away if the main logic board is flexed, or the Osbaud circuit board has pressure applied to it.

Osbaud is a carefully designed and constructed package. It does not hinder any part of the computer's electronics and it can be used with double density, 80-column display, or modem options. Nevertheless, please note that installing any product that alters the original design of the computer *voids your warranty.*

Osbaud is available from:

Advent Products, Inc.
965 N. Main St.
Orange, CA 92667
(714) 997-0800

It comes with both blue/gray, black/brown case instructions.

Brad Baldwin

The CRT Connection

Before Osborne's 80-column SCREEN-PAC was released a popular question was, "How do I connect an external CRT as a remote terminal in order to have a 80-column 12" display?" Here's one way:

- Set your computer for 9600 baud using Osbaud or the method shown on page 22 in the Technical Manual.
- Connect a standard serial cable between the terminal and your computer. This cable is all that is required:
  1 ----- 1
  2 ----- 2
  3 ----- 3
  7 ----- 7
- Change the CRT's dip switches for:
  1 start bit
  1 stop bit
  8 data bits
  no parity
  full duplex
- Assign devices with STAT CON: = CRT:

The end result is a 80-column, 9600 baud refreshed, block cursor screen. Note that these procedures are untested with terminals other than Televideo.