RC override arbiter: the joystick as a kill switch

Status: design, not built. No board has been bought and no firmware or vehicle-side code exists yet.

A small board between the two command sources and the actuators decides who drives. The remote joystick can always take the vehicle; the Orin drives only while the auto-mode switch is ON, its heartbeat is alive and nobody has touched the joystick. Any of those failing latches the board out of autonomous mode until a person switches OFF and ON again.

Why the vehicle needs it

Today a physical selector switch picks the Orin path or the joystick path for the throttle and steering signal wires. Nothing arbitrates between them, and three failures go unnoticed:

- **A dead Orin keeps driving.** The PCA9685 generates its pulses on its own and holds the last pulse width forever after the last I2C write. If the Orin hangs, crashes or loses I2C, the VESC keeps receiving the last throttle, and its own timeout never fires because pulses keep arriving.
- **A silent Autoware keeps driving.** `actuator.py` stores the latest control command in `control_callback` and its 100 Hz `timer_callback` drives toward it without checking its age.
- **The remote driver cannot take over** while the selector points at the Orin; someone has to reach the vehicle and flip it.




Figure 1: Wiring today

What changes

One board is added, the selector switch is rewired as an auto-mode switch, and the Orin gains a heartbeat on a spare PCA9685 channel. The motor, ESC, servo, receiver and PCA9685 stay as they are.




Figure 2: Wiring with the arbiter

Part	Change
Arbiter board	new: Seeed XIAO RP2350 and a 74LVC245 on a small carrier
Selector switch	becomes the auto-mode switch, a 3PDT toggle
PCA9685 ch2	new heartbeat output, written by the actuator node
VESC	input app changes from PPM to UART; timeout and brake current set
Orin	reads one GPIO line that says whether it is in control
External RGB LED	optional, if the onboard LED is not visible from outside

Modes

The board has five modes. Both disengaged modes are latched: the only way back to AUTO is the auto-mode switch going OFF and then ON.




Figure 3: Modes

Mode	Who drives	LED
MANUAL (switch OFF)	joystick	off
ARMING (switch just turned ON)	joystick	green, 1 Hz blink
AUTO	Orin, joystick watched	green, steady
DISENGAGED: takeover	joystick	amber, 4 Hz blink
DISENGAGED: Orin lost	brake first, then joystick	red, 4 Hz blink alternating with full brightness

“Disengaged” is the term AV testing uses for autonomous control ending, whether the safety driver took over or the system failed, which is why one mode covers both causes. The two look different on the LED because one was chosen and the other was not.

Transitions:

- **MANUAL to ARMING:** the switch goes OFF to ON. A board that powers up with the switch already ON stays in MANUAL until it sees a real OFF to ON, so a reset or brown-out cannot re-enter AUTO by itself. The switch is debounced for 50 ms.
- **ARMING to AUTO:** 1 s of steady heartbeat with both sticks centred, so the vehicle does not jump when the switch flips.
- **ARMING to DISENGAGED (Orin lost):** no heartbeat within 5 s, so a forgotten Orin start is not silent.
- **AUTO to DISENGAGED (takeover):** either stick past its deadband for two consecutive receiver frames.
- **AUTO to DISENGAGED (Orin lost):** the heartbeat has not toggled for 150 ms, or the radio link is lost. Without a radio nobody can take over, so the vehicle stops rather than keep driving autonomously.
- **Any mode to MANUAL:** the switch goes OFF.

In DISENGAGED (Orin lost) the board commands the VESC to brake at once and holds the brake while the joystick throttle sits at neutral. Steering passes through immediately; throttle passes through as soon as the driver moves it. Radio loss in MANUAL or after a takeover also brakes.

Heartbeat

The actuator node toggles PCA9685 ch2 between 1.2 ms and 1.8 ms pulses on every fifth tick of its 100 Hz loop (a 20 Hz toggle, each state held for three 60 Hz frames), and only while the latest control command is younger than 200 ms.

The heartbeat rides on the PCA9685 rather than a separate GPIO or serial line because one signal then proves the whole chain at once: Autoware publishing, the actuator node running, I2C working and the PCA9685 responding. A thread that toggled a GPIO would stay alive with Autoware or I2C stuck.

The board declares the Orin lost after 150 ms without a toggle, that is three missed toggles. Worst case from Autoware going silent to brake is about 350 ms (200 ms command age plus 150 ms).

The same command-age check belongs in `actuator.py` independently of the board: the node should command neutral throttle on a stale command instead of driving on the last one.

Wiring




Figure 4: Pin-level wiring

The same wiring as a harness drawing, with every wire and part listed, is `wiring.svg`, generated with WireViz from `wiring.yml`; it is wide, so zoom in.

XIAO pin	GPIO	Signal	Through
D0	26	receiver steer in	74LVC245 A1 to B1
D1	27	receiver throttle in	A2 to B2
D3	5	Orin throttle in, PCA ch0	switch pole A, then A3 to B3
D4	6	Orin steer in, PCA ch1	switch pole B, then A4 to B4
D5	7	Orin heartbeat in, PCA ch2	A5 to B5
D8	2	auto-mode switch sense, internal pull-up, low = ON	switch pole C to GND
D6	0	UART0 TX to VESC RX	
D7	1	UART0 RX from VESC TX	
D9	4	steering servo out	330 ohm
D10	3	AUTO state to an Orin 40-pin GPIO	1 kohm
D12 (back pad)	20	external LED data, optional	330 ohm
5V		power from the receiver 5 V rail	1N5819 Schottky
3V3		74LVC245 supply	

Spare: D2 (GPIO28) on the edge; D11 (GPIO21, UART1 RX) reserved for a serial receiver; D13 to D18 on the back pads. The onboard RGB LED is GPIO22 with its power enable on GPIO23. Pin numbers are from the arduino-pico board definition for the XIAO RP2350.

Notes on the wiring:

- **The switch cuts the Orin in hardware.** Poles A and B carry the Orin throttle and steer; their commons go to the level shifter and their OFF throws to GND through 10 kohm, so with the switch OFF nothing from the Orin reaches the board and its inputs do not float. Pole C only reports the position. The heartbeat does not pass through the switch.
- **Every input is level shifted.** The RP2350 pins are 3.3 V and not 5 V tolerant. The PCA9685 outputs 5 V when its logic runs at 5 V, and some receivers do too. The 74LVC245 runs at 3.3 V and accepts 5 V inputs, so it covers both cases; tie DIR to VCC, OE to GND, and the unused A6 to A8 to GND.
- **The VESC is commanded over UART.** The board is the only device that commands it, translating both the Orin's and the joystick's pulses into brake, current and speed-limit commands. The servo still takes a pulse.
- **One common ground** for the receiver, PCA9685, board, VESC signal, servo and Orin header.
- **Power** comes from the receiver's 5 V rail through the diode, about 4.7 V at the XIAO 5V pin; the board draws tens of mA. If the servo rail runs above 5.5 V, a 5 V regulator goes in front of the diode.

Board choice

Board	Size	GPIO	LED	Verdict
Arduino Nano (ATmega328P)	45 x 18 mm	20, 5 V	1	no: one UART, shared with USB
Seeed XIAO RP2040	21 x 17.8 mm	11	RGB	too few pins once LED and heartbeat are added
Cytron Maker Nano RP2040	49.6 x 21.1 mm	22	2 RGB, buzzer	fits; no Taiwanese seller found
Raspberry Pi Pico	51 x 21 mm	26	1	fits; large
Seeed XIAO RP2350	**21 x 17.8 mm**	**19**	**RGB**	**chosen**: small, onboard RGB LED, sold by icshop.com.tw (NT$295)

The RP2350 has two Cortex-M33 cores at 150 MHz, 520 KB SRAM, two UARTs and twelve PIO state machines. The PIO measures the five input pulses to 1 us without the CPU, one core runs only the arbitration loop at 1 kHz, and the hardware watchdog covers a hung firmware. CPU load is well under 1 %. The link that needs care is the VESC UART: a 10-byte command at 500 Hz takes 43 % of 115200 baud, so telemetry for odometry needs a higher baud rate.

Configuration outside the board

- **VESC Tool, App Settings:** app to use = UART; timeout 50 ms (default 1000 ms); timeout brake current above 0 A (the default 0 A coasts); throttle ramp for slowing down set to 0. Set `max-speed` from the wheel diameter, gear ratio and motor poles, and store the Orin-mode cap (about 15 km/h) as the default; the board raises it only while the joystick drives, so after any reset the vehicle starts capped.
- **Receiver:** failsafe set to no pulses, or to neutral throttle.
- **Orin:** the vehicle interface reads the state line and reports MANUAL on `control_mode` whenever it is low, so the PID stops integrating while the Orin is not in control.

Response time

With the joystick on a 50 Hz pulse receiver, from stick movement to the VESC receiving the new command:

Stage	Time
Radio link	10 to 30 ms, depends on the radio
Receiver output frame	up to 20 ms
Takeover confirmation, two frames	40 ms
UART command to the VESC	under 1 ms
Total	**about 50 to 90 ms**

At 40 km/h (11.1 m/s) that is 0.6 to 1.0 m. A receiver with serial output (CRSF or SBUS) on D11 and a high-rate radio link bring it to about 10 ms. The speed cap matters more than either: braking distance from 40 km/h is about 9 m at 0.7 g, from 15 km/h about 1.3 m.

Failure	Time to brake
Auto-mode switch turned OFF	immediate in hardware; joystick in control within one frame
Orin, actuator node or I2C dies	150 ms
Autoware stops publishing	about 350 ms
Board firmware hangs	watchdog, then no commands; the VESC brakes on its 50 ms timeout
Radio lost	receiver failsafe, then brake

Odometry from the VESC

The VESC reports signed electrical RPM even with a sensorless motor, which is how F1TENTH cars get odometry (the ROS 2 `vesc` driver and `vesc_to_odom`, one `speed_to_erpm_gain` fitted over a measured run). It is signed, finer than the KY-003 hall sensor and stays valid during a takeover. It is unreliable near standstill, misses wheel slip, and its steering comes from the commanded angle, which is wrong while the joystick drives. Reading it would go through the arbiter's UART link or a separate USB connection to the Orin, read-only either way.

Open items

- [ ] Transmitter and receiver model: decides pulse or serial input and whether the receiver outputs 5 V.
- [ ] Servo rail voltage: whether the 5 V input needs a regulator.
- [ ] Orin 40-pin header pin for the state line.
- [ ] XIAO RP2350 5V pin input range, from its schematic.
- [ ] Bench test: a logic analyzer on the receiver output and the board's outputs, to measure the takeover latency against the table above.
- [ ] Vehicle side: heartbeat on PCA9685 ch2, the command-age check in `actuator.py`, and the state line in the vehicle interface.

Regenerating the figures

The sources sit next to the SVGs in `assets/rc-override-arbiter/`:

```
cd docs/design/assets/rc-override-arbiter
for f in today block states pins; do dot -Tsvg $f.dot -o $f.svg; done
uvx wireviz -f s wiring.yml     # writes wiring.svg; delete the wiring and wiring.gv byproducts
```

The PDF beside this note, `rc-override-arbiter.pdf`, is this file with its figures; rebuild it after any edit, from the repository root:

```
typst compile --root docs/design docs/design/assets/rc-override-arbiter/pdf.typ docs/design/rc-override-arbiter.pdf
```

Sources

- VESC firmware, vedderb/bldc: `applications/app_ppm.c`, `applications/appconf_default.h`, `lispBM/README.md`
- Seeed XIAO RP2350 wiki and the arduino-pico board definition
- icshop XIAO category, prices read 2026-10-12
- F1TENTH odometry calibration