

This is the GALv3 Body mod that accepts SureFire patterned flashlight heads.

This includes M300 heads, Kiji heads, Malkoff E2XT, etc.

The same o-ring used for the GALv3 adjustable illuminator can be used (15x1.5mm o-ring)

Build Instructions:

- The Illum- wire should be stripped and tinned about 0.5" long.
 - Feed the wire into the hole on the inside of the threaded area until the insulation is all the way to the hole.
 - This is to prevent shorting between the positive and negative terminals
 - Feed the tinned wire up along the channel, and hook it over the top and back into the inside.
 - Trim off any excess that goes too far into the inside area.
-
- The Illum+ wire should be soldered to a AAA positive terminal (no spring) and glued into the bottom of the inside area
 - Some other contact can be used, just make sure it doesn't contact the negative wire

Note: In the images, the wire colors are backwards. Take note of which wire you are wiring to which part.

