Eastron SDM120CTM Smart Meter Modbus Protocol Implementation V1.3

1 MODBUS Protocol Message Format

The MODBUS Protocol defines the format for the master's query and the slave's response.

The query contains the device (or broadcast) address, a function code defining the requested action, any data to be sent, and an error-checking field.

The response contains fields confirming the action taken, any data to be returned, and an error-checking field. If an error occurred in receipt of the message then the message is ignored, if the slave is unable to perform the requested action, then it will construct an error message and send it as its response. The MODBUS Protocol functions used by the Eastron Digital meters copy 16 bit register values between master and slaves. However, the data used by the Eastron Digital meter is in 32 bit IEEE 754 floating point format. Thus each instrument parameter is conceptually held in two adjacent MODBUS Protocol registers. Query

The following example illustrates a request for a single floating point parameter i.e. two 16-bit Modbus Protocol Registers.

First Byte Last Byte

Slave	Function	Start	Start	Number	Number	Number	Error	Error
Address	Code	Address	Address	of	of	of	Check	Check
		(Hi)	(Lo)	Points	Points	Points	(Lo)	(Hi)
				(Hi)	(Lo)	(Lo)		

Slave Address: 8-bit value representing the slave being addressed (1 to 247), 0 is reserved for the broadcast address. The Eastron Digital meters do not support the broadcast address.

Function Code: 8-bit value telling the addressed slave what action is to be performed. (3, 4, 8 or 16 are valid for Eastron Digital meter)

Start Address (Hi): The top (most significant) eight bits of a 16-bit number specifying the start address of the data being requested.

Start Address (Lo): The bottom (least significant) eight bits of a 16-bit number specifying the start address of the data being requested. As registers are used in pairs and start at zero, then this must be an even number.

Number of Points (Hi): The top (most significant) eight bits of a 16-bit number specifying the number of registers being requested.

Number of Points (Lo): The bottom (least significant) eight bits of a 16-bit number specifying the number of registers being requested. As registers are used in pairs, then this must be an even number.

Error Check (Lo): The bottom (least significant) eight bits of a 16-bit number representing the error check value.

Error Check (Hi): The top (most significant) eight bits of a 16-bit number representing the error check value.

Response

The example illustrates the normal response to a request for a single floating point parameter i.e. two 16-bit Modbus Protocol Registers.

First Byte Last Byte

Slave	Function	Byte	First	First	Second	Second	Error	Error
Address	Code	Count	Register	Register	Register	Register	Check	Check
			(Hi)	(Lo)	(Hi)	(Lo)	(Lo)	(Hi)

Slave Address: 8-bit value representing the address of slave that is responding.

Function Code: 8-bit value which, when a copy of the function code in the query, indicates that the slave recognised the query and has responded. (See also Exception Response).

Byte Count: 8-bit value indicating the number of data bytes contained within this response First Register (Hi)*: The top (most significant) eight bits of a 16-bit number representing the first register requested in the query.

First Register (Lo)*: The bottom (least significant) eight bits of a 16-bit number representing the first register requested in the query.

Second Register (Hi)*: The top (most significant) eight bits of a 16-bit number representing the second register requested in the query.

Second Register (Lo)*: The bottom (least significant) eight bits of a 16-bit number representing the second register requested in the query.

Error Check (Lo): The bottom (least significant) eight bits of a 16-bit number representing the error check value.

Error Check (Hi): The top (most significant) eight bits of a 16-bit number representing the error check value.

Exception Response

If an error is detected in the content of the query (excluding parity errors and Error Check mismatch), then an error response (called an exception response), will be sent to the master. The exception response is identified by the function code being a copy of the query function code but with the most-significant bit set. The data contained in an exception response is a single byte error code.

First Byte Last Byte

Slave	Function	Error	Error	Error	
Address	Code	Code	Check	Check	
			(Lo)	(Hi)	

Slave Address: 8-bit value representing the address of slave that is responding.

Function Code: 8 bit value which is the function code in the query OR'ed with 80 hex, indicating that the slave either does not recognize the query or could not carry out the action requested.

Error Code: 8-bit value indicating the nature of the exception detected.

(See "Table Of Exception Codes" later).

Error Check (Lo): The bottom (least significant) eight bits of a 16-bit number representing the error check value.

Error Check (Hi): The top (most significant) eight bits of a 16-bit number representing the error check value.

2 Read Input Registers

2.1 MODBUS Protocol code 04 reads the contents of the 3X registers.

Example

The following query will request 'Volts 1' from an instrument with node address 1:

Field Name	Example(Hex)
Slave Address	01
Function	04
Starting Address High	00
Starting Address Low	00
Number of Points High	00
Number of Points Low	02
Error Check Low	71
Error Check High	СВ

Note: Data must be requested in register pairs i.e. the "Starting Address" and the "Number of Points" must be even numbers to request a floating point variable. If the "Starting Address" or the "Number of points" is odd then the query will fall in the middle of a floating point variable the product will return an error message.

The following response returns the contents of Volts 1 as 230.2. But see also "Exception Response" later.

Field Name	Example (Hex)
Slave Address	01
Function	04
Byte Count	04
Data, High Reg, High Byte	43
Data, High Reg, Low Byte	66
Data, Low Reg, High Byte	33
Data, Low Reg, Low Byte	34
Error Check Low	1B
Error Check High	38

2.2 Read Holding Registers

MODBUS Protocol code 03 reads the contents of the 4X registers.

Example

The following query will request the prevailing 'Network Node':

Field Name	Example (Hex)
Slave Address	01
Function	03
Starting Address High	00
Starting Address Low	00
Number of Points High	00
Number of Points Low	14
Error Check Low	C4
Error Check High	0B

Note: Data must be requested in register pairs i.e. the "Starting Address" and the "Number of Points" must be even numbers to request a floating point variable. If the "Starting Address" or the "Number of points" is odd then the query will fall in the middle of a floating point variable the product will return an error message.

The following response returns the contents of Demand Time as 1, but see also "Exception Response" later.

Field Name	Example (Hex)
Slave Address	01
Function	03
Byte Count	04
Data, High Reg, High Byte	3F
Data, High Reg, Low Byte	80
Data, Low Reg, High Byte	00
Data, Low Reg, Low Byte	00
Error Check Low	F7
Error Check High	CF

2.3 Write Holding Registers

MODBUS Protocol code 10 (16 decimal) writes the contents of the 4X registers.

Example

The following query will set the Network Node to 60:

Field Name	Example (Hex)
Slave Address	01
Function	10
Starting Address High	00
Starting Address Low	14
Number of Registers High	00
Number of Registers Low	02
Byte Count	04

Data, High Reg, High Byte	42
Data, High Reg, Low Byte	70
Data, Low Reg, High Byte	00
Data, Low Reg, Low Byte	00
Error Check Low	67
Error Check High	D5

Note: Data must be written in register pairs i.e. the "Starting Address" and the "Number of Points" must be even numbers to write a floating point variable. If the "Starting Address" or the "Number of points" is odd then the query will fall in the middle of a floating point variable the product will return an error message. In general only one floating point value can be written per query

The following response indicates that the write has been successful. But see also "Exception Response "later.

Field Name	Example (Hex)
Slave Address	01
Function	10
Starting Address High	00
Starting Address Low	14
Number of Registers High	00
Number of Registers Low	02
Error Check Low	E0
Error Check High	08

Register Map:

Function code 04 to read input parameters:

Address Register	Input Register Parameter	Modbus Protocol Start Address Hex				
	Parameter	Length (bytes)	Data Format	Units	Hi byte	Lo byte
30001	Voltage	4	Float	Volts	00	00
30007	Current	4	Float	Amps	00	06
30013	Active power	4	Float	Watts	00	0C
30019	Apparent power	4	Float	VA	00	12
30025	Reactive power	4	Float	VAr	00	18
30031	Power factor	4	Float	None	00	1E
30071	Frequency	4	Float	Hz	00	46
30073	Import active energy	4	Float	kWh	00	48
30075	Export active energy	4	Float	kWh	00	4A
30077	Import reactive energy	4	Float	kvarh	00	4C
30079	Export reactive energy	4	Float	kvarh	00	4E
30085	Total system power	4	Float	W	00	54

	demand					
30087	Maximum total system power demand	4	Float	W	00	56
30089	Import system power demand	4	Float	W	00	58
30091	Maximum Import system power demand	4	Float	W	00	5A
30093	Export system power demand	4	Float	W	00	5C
30095	Maximum Export system power demand	4	Float	W	00	5E
30259	current demand.	4	Float	Amps	01	02
30265	Maximum current demand.	4	Float	Amps	01	08
30343	Total active energy	4	Float	kWh	01	56
30345	Total reactive energy	4	Float	Kvarh	01	58

Function code 10 to set holding parameter $\,$, function code 03 to read holding parameter

Address		Register	Modbu		Description	
Register	Paramete	Protocol Start Address Hex		Description	Mode	
Negistei						
	Paramet	Format	Hi	Lo		
	ers		byte	byte		
	Demand Time				Read minutes into first demand calculation. When the	ro
					Demand Time reaches the Demand Period then the	
40001			00	00	demand values are valid.	
					Length: 4 byte	
					Data Format : Float	
	Demand Period		00	02	Write demand period: 0~60 minutes, Default 60.	r/w
40003					Range: 0~60, 0 means function closed	
.000					Length: 4 byte	
					Data Format : Float	
					Write relay on period in	r/w
	Relay Pulse Width				milliseconds: 60, 100 or 200, default	
40013			00	0C	100ms.	
					Length: 4 byte	
					Data Format : Float	
					Write the network port parity/stop bits for	r/w
	Network Parity Stop				MODBUS Protocol, where: 0 = One stop bit	
					and no parity, default. 1 = One stop bit and	
					even parity. 2 = One stop bit and odd	
40019			00	12	parity.3 = Two stop bits and no	
					parity.Requires a restart to become	
					effective.	
					Length: 4 byte	
					Data Format : Float	
40021	Meter ID		00	14	Ranges from 1 to 247,	r/w
					.Default ID is 1.	
					Length: 4 byte	
					Data Format : Float	
40029	Baud rate		00	1C	Write the network port baud rate for	r/w
					MODBUS Protocol, where:	
					0 = 2400 baud(default)	
					1 = 4800 baud.	
					2 = 9600 baud	
					5=1200 baud .	
					Length: 4 byte	
					Data Format : Float	
40051	CT1		00	32	CT Primary current	r/w

				Ranges from 5 to 9999, Default ID is 5 Length: 4 byte Data Format: Float	
40053	CT2	00	34	CT2 Range: 1A or 5A, Default 5A Length: 4 byte Data Format: Float	r/w
40087	Pulse 1 output mode	00	56	Write MODBUS Protocol input parameter for pulse out 1: 0001: Import active energy, 0002: Import + export active energy, 0004: Export active energy, (default). 0005: Import reactive energy, 0006: Import + export reactive energy, 0008: Export reactive energy, Length: 4 byte Data Format: Float	r/w
461457	Reset historical data	F0	10	00 00 = reset demand info Length : 2 byte Data Format:Hex	wo
463745	Time of scroll display	F9	00	Range: 0-30s Default 0:does not display in turns Length: 2 byte Data Format: BCD	r/w
463761	Pulse 1 output	F9	10	0000:0.001kWh/imp 0001:0.01kWh/imp(default) 0002:0.1kWh/imp 0003:1kWh/imp 0004:10kWh/imp 0005:100kWh/imp 0006:1000kWh/imp Length: 2 byte Data Format: Hex	r/w
463777	Measurement mode	F9	20	0001:mode 1(total = import) 0002:mode 2 (total = import + export) (default) 0003:mode 3 (total = import - export) Length: 2 byte Data Format: Hex	r/w
464513	Serial number	FC	00	Serial number Length: 4 byte Data Format: unsigned int32 Note: Only read	ro