

## 2.2 PQC Series Mixed Fixed type SVG Product Category

The Delta PQC Series Mixed Fixed type SVG is categorized by the capacity and wiring system. **Table 2-1** lists the information regarding the SVG module products.

**Table 2-1: PQC Series Mixed Fixed Type SVG Specifications**

| Product                                   | Model                                        | Capacity | Wiring System |
|-------------------------------------------|----------------------------------------------|----------|---------------|
| SVG Module                                | PQCS-400-50-50MM4                            | 50 kvar  | 3P4W          |
|                                           | PQCS-400-50-50MM3                            | 50 kvar  | 3P3W          |
|                                           | PQCS-400-100-100MM4                          | 100 kvar | 3P4W          |
|                                           | PQCS-400-100-100MM3                          | 100 kvar | 3P3W          |
|                                           | PQCS-400-150-150MM4                          | 150 kvar | 3P4W          |
|                                           | PQCS-400-150-150MM3                          | 150 kvar | 3P3W          |
| SVG Module<br>(Maintained from the Front) | SVG Module + Pluggable terminals(50/100kvar) |          |               |
| HMI Display                               | PQC-HMI-F (7")                               | N/A      | N/A           |
|                                           | PQC-HMI-F10 (10")                            | N/A      | N/A           |
| Accessories                               | Pluggable terminals(50/100kvar)              | N/A      | N/A           |



### NOTE:

Only 50kvar and 100kvar SVG can be used with pluggable terminals, For detailed information regarding the Pluggable terminals, please see **Chapter 3.5.2**.

### • SVG Module

The SVG module is available in two wiring modes, i.e. 3P3W and 3P4W, and is available in the following output capacity: 50kvar and 100kvar.

The 3P4W module shall be connected to a neutral line, which in turn will improve its ability of compensating the zero sequence current. The 3P3W model is not required to connect to the neutral line; as a result, it is not able to compensate the zero sequence current. **Figure 2-2** shows the SVG module appearance.