

3-4 Wiring Precautions

Open the motor wiring box cover to check whether the U, V, and W terminals are clearly marked and pay attention to the following instructions when wiring. Do NOT make any wrong connections.

 DANGER	☑ When wiring, turn off the AC motor drive power first. It takes a certain time for the internal DC capacitor to discharge. To avoid damage, use a voltmeter for testing. Wiring only after the voltage is lower than the safety voltage value of 25 V_{DC}. If the AC motor drive does not fully discharge, there will be residual voltage inside. Any wiring at this time causes short-circuit and fire. It is strongly suggested to operate the wiring under no-voltage conditions to ensure personnel safety. ☑ Only qualified persons are allowed to perform wiring. Make sure the power is turned off before wiring to prevent electric shock. ☑ Make sure the power is only applied to the U, V, and W terminals. Failure to comply may result in damage to the motor. The voltage and current must be in the range indicated on the nameplate (refer to Section 1-2 Nameplate Information). ☑ All units must be grounded directly to a common ground terminal to prevent damage from lightning strike or electric shock and reduce noise interference. ☑ Tighten the screws of the main circuit terminals to prevent sparks caused by screws loosened due to vibration.
 CAUTION	☑ For your safety, choose wires that comply with local regulations when wiring. ☑ Check the following items after finishing the wiring: 1. Are all connections correct? 2. Are there any loosen wires? 3. Are there any short circuits between the terminals or to ground?